



## LG 34WP60C LED Monitor LCD Screen Owner's Manual

[Home](#) » [LG](#) » LG 34WP60C LED Monitor LCD Screen Owner's Manual 

### Contents

- 1 LG 34WP60C LED Monitor LCD Screen
- 2 Product Information
- 3 OPEN SOURCE SOFTWARE
- 4 ASSEMBLING AND PREPARING
- 5 Basic Functions
- 6 USING THE MONITOR
- 7 Connecting AV Devices
- 8 USER SETTINGS
- 9 User Settings
- 10 TROUBLESHOOTING
- 11 PRODUCT SPECIFICATION
- 12 Factory Support Mode (Preset Mode, PC)
- 13 Documents / Resources
  - 13.1 References
- 14 Related Posts



**LG 34WP60C LED Monitor LCD Screen**



## Product Information

### Specifications

- **Model:** 34WP60C
- **Screen Type:** LED LCD
- **Backlight Type:** LED

### Assembling and Preparing

Before assembling the product, please note the following

- **CAUTION:** Make sure to follow the instructions to prevent damage to the product.
- **NOTE:** You can download and install the latest drivers and software from the LGE website ( [www.lg.com](http://www.lg.com) ).
- Supported Drivers and Software
  - Monitor Driver
  - OnScreen Control
  - Dual Controller
- Installation Priority
  - **Monitor Driver:** Recommended
  - **OnScreen Control:** Recommended
  - **Dual Controller:** Optional

### Product and Button Description

The monitor has a joystick button that allows you to easily control its functions. Here's how to use it

- Moving and Lifting the Monitor
  - When moving or lifting the monitor, follow the instructions provided to prevent scratches or damage.

- Tilt the monitor sideways to ensure safe transportation.
- Power On
  - Press the joystick button once with your finger to turn on the monitor.
- Power Off
  - Press and hold the joystick button for more than 5 seconds with your finger to turn off the monitor.
- Volume Control
  - You can control the volume by moving the joystick button left or right.

## Using the Monitor

Here are instructions on how to connect the monitor to different devices

- Connecting to a PC
  - **HDMI Connection:** Follow the provided steps to connect the monitor to your PC using an HDMI cable.
  - **DisplayPort Connection:** Follow the provided steps to connect the monitor to your PC using a DisplayPort cable.
- Connecting AV Devices
  - **HDMI Connection:** Follow the provided steps to connect the monitor to your AV devices using an HDMI cable.
- Connecting Peripherals
  - **Connecting Headphones:** Connect your headphones to the audio output port on the monitor.

## User Settings

Here's how to access and adjust the user settings on the monitor

- **Activating the Main Menu**
  - Press the joystick button to activate the main menu.
- **Main Menu Features**
  - Explore the different features available in the main menu to customize your monitor settings.
- **User Settings**
  - Access the menu settings to further customize and adjust the monitor according to your preferences.

## Troubleshooting

If you encounter any issues with the monitor, refer to the troubleshooting section in the user manual for possible solutions.

## FAQ

- **Q: Where can I find more information about the licenses for my model?**
  - A: Visit [www.lg.com](http://www.lg.com) for more information on the license.
- **Q: What are the trademarks mentioned in the manual?**
  - A: The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.
- **Q: How can I secure the monitor using the Kensington lock?**
  - A: The connector for the Kensington security system is located at the bottom of the monitor. For installation and usage instructions, refer to the Kensington lock owner's manual or visit

## **LG LED Monitor applies LCD screen with LED backlights.**

- Please read this manual carefully before operating your set and retain it for future reference.
- 34WP60C
- [www.lg.com](http://www.lg.com)
- Copyright © 2021 LG Electronics Inc. All Rights Reserved.

## **LICENSE**

Each model has different licenses. Visit [www.lg.com](http://www.lg.com) for more information on the license.



The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

## **OPEN SOURCE SOFTWARE**

### **NOTICE INFORMATION**

- To obtain the source code that is contained in this product, under GPL, LGPL, MPL, and other open source licenses that have the obligation to disclose source code, and to access all referred license terms, copyright notices and other relevant documents, please visit <http://opensource.lge.com>.
- LG Electronics will also provide open source code to you on CD-ROM for a charge covering the cost of performing such distribution (such as the cost of media, shipping, and handling) upon email request to [opensource@lge.com](mailto:opensource@lge.com).
- This offer is valid to anyone in receipt of this information for a period of three years after our last shipment of this product.

## **ASSEMBLING AND PREPARING**

### **CAUTION**

- Always use genuine LG components to ensure safety and product performance.
- The product warranty will not cover damage or injury caused by the use of unauthorized components.
- It is recommended that use the supplied components.
- If you use generic cables not certified by LG, the screen may not display or there may be image noises.
- Illustrations in this document represent typical procedures, so they may look different from the actual product.
- Do not apply foreign substances (oils, lubricants, etc.) to the screw parts when assembling the product. (Doing so may damage the product.)
- Applying excessive force when tightening screws may cause damage to the monitor. Damage caused in this way will not be covered by the product warranty. Do not carry the monitor upside down by just holding the base. This may cause the monitor to fall off the stand and could result in personal injury.
- When lifting or moving the monitor, do not touch the monitor screen. The force applied to the monitor screen may cause damage to it.

## NOTE


- The components may look different from those illustrated here.
- Without prior notice, all product information and specifications contained in this manual are subject to change to improve the performance of the product.
- To purchase optional accessories, visit an electronics store or an online shopping site, or contact the retailer from where you purchased the product.
- The power cord provided may differ depending upon the region.

## Supported Drivers and Software

You can download and install the latest version from the LGE website ([www.lg.com](http://www.lg.com)).

Drivers and Software	Installation Priority
Monitor Driver	Recommended
OnScreen Control	Recommended
Dual Controller	Optional






## Product and Button Description



## How to Use the Joystick Button

You can easily control the functions of the monitor by pressing the joystick button or moving it left/right/up/down with your finger.

## Basic Functions

		<b>Power on</b>	Press the joystick button once with your finger to turn on the monitor.
		<b>Power off</b>	Press and hold the joystick button once more than 5 seconds with your finger to turn off the monitor.
		<b>Volume control</b>	You can control the volume by moving the joystick button left/right.


#### NOTE

The joystick button is located at the bottom of the monitor.

#### Moving and Lifting the Monitor

When moving or lifting the monitor, follow these instructions to prevent the monitor from being scratched or damaged and to ensure safe transportation, regardless of its shape or size.

- Place the monitor in the original box or packing material before attempting to move it.
- Before moving or lifting the monitor, disconnect the power cord and all other cables.
- Hold the bottom and side of the monitor frame firmly. Do not hold the panel itself.
- When holding the monitor, the screen should face away from you to prevent it from being scratched.
- When transporting the monitor, do not expose the monitor to shock or excessive vibration.
- When moving the monitor, keep it upright and never turn the monitor on its side or tilt it sideways.




#### CAUTION

- Avoid touching the monitor screen as much as possible.
  - This may result in damage to the screen or some of the pixels used to create images.
- If you use the monitor panel without the stand base, its joystick button may cause the monitor to become unstable and fall, resulting in damage to the monitor or human injury. In addition, this may cause the joystick button to malfunction.

#### Installing on a Table

Lift the monitor and place it on the table in an upright position. Place the monitor at least 100 mm (3.94 inches) away from the wall to ensure sufficient ventilation.



## CAUTION

- Unplug the power cord before moving or installing the monitor. There is risk of electric shock.
- Make sure to use the power cord that is provided in the product package and connect it to a grounded power outlet.
- If you need another power cord, please contact your local dealer or the nearest retail store.

## Adjusting the Angle

1. Place the monitor mounted on the stand base in an upright position.
2. Adjust the angle of the screen.


The angle of the screen can be adjusted forward or backward from  $-5^{\circ}$  to  $15^{\circ}$  for a comfortable viewing experience.

## WARNING

- To avoid injury to the fingers when adjusting the screen, do not hold the lower part of the monitor's frame as illustrated below.
- Be careful not to touch or press the screen area when adjusting the angle of the monitor.


**NOTE**

The left or right side of the monitor head can be slightly rotated up or down (up to 3°). Adjust the horizontal level of the monitor head.

**Using the Kensington Lock**

- The connector for the Kensington security system is located at the bottom of the monitor.
- For more information on installation and usage, refer to the Kensington lock owner's manual or visit the website at <http://www.kensington.com>.
- Connect the monitor to a table using the Kensington security system cable.



**NOTE**

The Kensington security system is optional. You can obtain optional accessories from most electronics stores.

**Installing the Wall Mount Plate**

This monitor meets the specifications for the wall mount plate or other compatible devices.


**NOTE**

- The wall mount plate is sold separately.
- For more information on installation, refer to the wall mount plate's installation guide.
- Be careful not to apply too much force while mounting the wall mount plate as it may cause damage to the screen.
- Remove the stand before installing the monitor on a wall mount by performing the stand attachment in reverse.

**Installing on the Wall**


Install the monitor at least 100 mm (3.94 inches) away from the wall and leave about 100 mm (3.94 inches) of space at each side of the monitor to ensure sufficient ventilation. Detailed installation instructions can be obtained from your local retail store. Alternatively, please refer to the manual for how to install and set up a tilting wall mounting bracket.

-



To install the monitor to a wall, attach a wall mounting bracket (optional) to the back of the monitor.

- Make sure that the wall mounting bracket is securely fixed to the monitor and to the wall.
1. If you use screws longer than the standard length, it may damage the inside of the product.
  2. A non-VESA standard screw may damage the product and cause the monitor to fall. LG Electronics is not liable for any accidents relating to the use of non-standard screws.


<b>Wall Mount (mm)</b>	100 x 100
<b>Standard screw</b>	M4 x L10
<b>Number of screws</b>	4
<b>Wall Mount Plate (Optional)</b>	LSW 149 

#### NOTE

- Use the screws specified by VESA standards.
- The wall mount kit includes the installation guide and all necessary parts.
- The wall mounting bracket is optional. You can obtain optional accessories from your local dealer.
- The length of the screw may differ for each wall mounting bracket. Be sure to use the proper length.
- For more information, please refer to the user manual for the wall mounting bracket.

#### CAUTION

- Unplug the power cord before moving or installing the monitor to avoid electric shock.
- Installing the monitor on the ceiling or on a slanted wall may result in the monitor falling off, which could lead to injury. Use an authorized LG wall mount and contact the local dealer or qualified personnel.
- Applying excessive force when tightening screws may cause damage to the monitor. Damage caused in this way will not be covered by the product warranty.
- Use the wall mounting bracket and screws that conform to VESA standards. Damage caused by the use or misuse of inappropriate components will not be covered by the product warranty.
- When measured from the back of the monitor, the length of each installed screw must be 8 mm (0.3 inches) or less.



## USING THE MONITOR

- Illustrations in this manual may differ from the actual product.
- Press the joystick button, go to Settings → Input, and then select the input option.

## CAUTION

- Do not press the screen for a prolonged time. This may cause image distortion.
- Do not display a still image on the screen for a prolonged time. This may cause image retention. Use a screensaver if possible.

## NOTE

- When connecting the power cord to the outlet, use a grounded (3-hole) power strip or a grounded power outlet.
- The monitor may flicker when turned on in an area where the temperature is low. This is normal.
- Sometimes red, green, or blue spots may appear on the screen. This is normal.

## Connecting to a PC

- This monitor supports the \*Plug and Play feature.
- **Plug and Play:** A feature that allows you to add a device to your computer without having to reconfigure anything or install any manual drivers

### HDMI Connection

Transmits digital video and audio signals from your PC to the monitor.

#### CAUTION

- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- Recommended HDMI cable types
  - High-Speed HDMI®/TM cable
  - High-Speed HDMI®/TM cable with Ethernet

### DisplayPort Connection

Transmits digital video and audio signals from your PC to the monitor.

#### NOTE

- There may be no video or audio output depending on the DP (DisplayPort) version of the PC.
- If you are using a Mini DisplayPort output graphics card, use a Mini DP to DP (Mini DisplayPort to DisplayPort) cable or gender that supports DisplayPort1.4. (sold separately)

## Connecting AV Devices

### HDMI Connection

HDMI transmits digital video and audio signals from your AV device to the monitor.

#### NOTE

- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- Recommended HDMI cable types
  - High-Speed HDMI®/TM cable
  - High-Speed HDMI®/TM cable with Ethernet

## Connecting Peripherals

### Connecting Headphones

Connect peripherals to the monitor via the headphones port.

## NOTE

- Peripheral devices are sold separately.
- If you use angled earphones, it may cause a problem with connecting another external device to the monitor. Therefore, it is recommended to use straight earphones.



Angled



Straight  
(Recommend)

- Depending on the audio settings of the PC and external device, headphones and speaker functions may be limited.


## USER SETTINGS

### NOTE




- Your monitor's OSD (On Screen Display) may differ slightly from that shown in this manual.
- When Beep Guide is activated, pressing the joystick button will take you to Settings right away.

### Activating the Main Menu


1. Press the joystick button on the bottom of the monitor.
2. Move the joystick up/down (▲/▼) and left/right (◀/▶) to set the options.
3. Press the joystick button once more to exit the main menu.



Joystick Button

Button	Menu Status		Description
	<b>Main menu disabled</b>		Enables the main menu.
	<b>Main menu enabled</b>		Exits the main menu. (Holding down the button to turn off the monitor. You can turn off the monitor this way at any time, including when the OSD is on.)
	◀	<b>Main menu disabled</b>	Adjusts the monitor volume level.
		<b>Main menu enabled</b>	Enters the <b>Input</b> features.
	▶	<b>Main menu disabled</b>	Adjusts the monitor volume level.
		<b>Main menu enabled</b>	Enters the <b>Settings</b> feature.
	▲	<b>Main menu disabled</b>	Enters the <b>Accessibility</b> menu.
		<b>Main menu enabled</b>	Turns off the monitor.
	▼	<b>Main menu disabled</b>	Enters the <b>Accessibility</b> menu.
		<b>Main menu enabled</b>	Enters the <b>Game Mode</b> feature.

## Main Menu Features



Main Menu	Description
Input	Sets input mode.
Power Off	Turns off the monitor.
Settings	Configures the screen settings.
Game Mode	Sets the game mode for gaming.
Exit	Exits the main menu.

## User Settings

### Menu Settings

1. To view the OSD menu, press the joystick button at the bottom of the monitor and then enter the Settings.
2. Configure the options by moving the joystick up/down/left/right.
3. To return to the upper menu or set other menu items, move the joystick to ◀ or pressing (⏻) it.
4. If you want to exit the OSD menu, move the joystick to ▶ until you exit.



Game Mode



Game Adjust



Picture Adjust



Input



General



### Game Mode on SDR(Non-HDR)signal.

Settings > Game Mode		Description
Game Mode	Gamer 1	In this mode, users can customize elements including game-related options.
	Gamer 2	<b>Gamer 1</b> and <b>Gamer 2</b> picture modes allow you to save two sets of customized display settings, including game-related setup options.
	FPS	This mode is optimized for FPS games.
	RTS	This mode is optimized for RTS Game.
	Vivid	Optimized the screen for vivid colors.
	Reader	Optimizes the screen for viewing documents. You can brighten the screen in the OSD menu.
	HDR Effect	Optimizes the screen for high dynamic range.

### Game Mode on HDR signal.

Settings > Game Mode		Description
Game Mode	Gamer 1	In this mode, users can customize elements including game-related options.
	Gamer 2	<b>Gamer 1</b> and <b>Gamer 2</b> picture modes allow you to save two sets of customized display settings, including game-related setup options.
	FPS	This mode is optimized for FPS games. It is suitable for very dark FPS games.
	RTS	This mode is optimized for RTS Game.
	Vivid	Optimized the screen for vivid colors.
	<b>NOTE</b> <ul style="list-style-type: none"> <li>• HDR content may not be operated properly depending on the Windows10 OS setting. Please check the HDR On / Off setting of Windows.</li> <li>• When the HDR function is turned on, the characters or picture quality may be poor according to Graphic card performance.</li> <li>• While the HDR function is on, screen flickering or cracking may occur when changing the monitor input or power on/off according to Graphic card performance.</li> </ul>	



Settings > Game Adjust		Description	
Game Adjust	1ms Motion Blur Reduction	On	<p>This mode minimizes motion blur in fast-moving videos. To take full advantage of this function, select 3440 x 1440 before enabling <b>1ms Motion Blur Reduction</b>.</p>  <p>This function is available for the following vertical frequency. (HDMI 85Hz, DP 100,144,160Hz)</p>
		Off	<p>Turns <b>1ms Motion Blur Reduction</b> Mode off.</p> 
		<p><b>NOTE</b></p> <ul style="list-style-type: none"> <li>• To reduce motion blur, brightness is reduced with backlight control.</li> <li>• <b>1ms Motion Blur Reduction</b> and <b>FreeSync</b> feature can not be used at the same time.</li> <li>• This function is game-optimized.</li> <li>• It is recommended to turn off when you are not using the gaming function.</li> <li>• Flicker may occur during <b>1ms Motion Blur Reduction</b> operation.</li> </ul>	

Game Adjust	FreeSync Premium	<p>Provides seamless and natural images by synchronizing the vertical frequency of the input signal with that of the output signal.</p> <p><b>CAUTION</b></p> <ul style="list-style-type: none"> <li>• <b>Supported Interface</b>: DisplayPort.</li> <li>• <b>Supported Graphic Card</b> : A graphic card that supports AMD's FreeSync is necessary.</li> <li>• <b>Supported Version</b> : Make sure to update the graphic card to the latest driver.</li> <li>• For more information and requirement, refer to AMD website at <a href="http://www.amd.com/FreeSync">http://www.amd.com/FreeSync</a></li> <li>• <b>FreeSync Premium</b> and <b>1ms Motion Blur Reduction</b> cannot be enabled simultaneously.</li> </ul>	
		<b>Extended</b>	<p>Enable wider frequency range of FreeSync function than basic mode.</p> <p>The screen may flicker during the game play.</p>
		<b>Basic</b>	Enable basic frequency range of FreeSync function.
		<b>Off</b>	FreeSync function off.
	Black Stabilizer	<ul style="list-style-type: none"> <li>• You can control the black contrast to have better visibility in dark scenes.</li> <li>• Increasing the <b>Black Stabilizer</b> value brightens the low gray level area on the screen. (You can easily distinguish objects on dark game screens.)</li> <li>• Reducing the <b>Black Stabilizer</b> value darkens the low gray level area and increases the dynamic contrast on the screen.</li> </ul>	

Game Adjust	Response Time	<p>Sets a response time for displayed pictures based on the speed of the screen. For a normal environment, it is recommended that you use <b>Fast</b>.</p> <p>For a fast-moving picture, it is recommended that you use <b>Faster</b>.</p> <p>Once <b>Faster Mode</b> is selected, <b>Motion Blur</b> may occur depending on the content.</p>	
		<b>Faster</b>	Sets the response time to Faster.
		<b>Fast</b>	Sets the response time to Fast.
		<b>Normal</b>	Sets the response time to Normal.
		<b>Off</b>	Does not use the response time improvement feature.
	Crosshair	<p>Crosshair provides a mark on the center of the screen for First Person Shooter (FPS) games. Users can select the Crosshair that fits their gaming environment among four different Crosshairs.</p>	
	Game Reset	Do you want to reset your Game settings?	
		<b>No</b>	Cancel the select.
		<b>Yes</b>	Returns to the default settings.

Settings > Picture Adjust		Description	
Picture Adjust	Brightness	Adjusts the brightness of the screen.	
	Contrast	Adjusts the contrast of the screen.	
	Sharpness	Adjusts the sharpness of the screen.	
	Gamma	Mode 1, Mode 2, Mode 3	The higher the gamma value, the darker the image becomes. Likewise, the lower the gamma value, the lighter the image becomes.
		Mode 4	If you do not need to adjust the gamma settings, select Mode 4.
	Color Temp	Custom	The user can adjust it to red, green, or blue by customization.
		Warm	Sets the screen color to a reddish tone.
		Medium	Sets the screen color to between a red and blue tone.
		Cool	Sets the screen color to a bluish tone.
		Manual	The user can fine – tune the color temperature.
	R/G/B	You can customize the picture color using <b>Red</b> , <b>Green</b> , and <b>Blue</b> colors.	
	Six Color	Meets the user requirements for colors by adjusting the hue and saturation of the six colors (Red, Green, Blue, Cyan, Magenta and Yellow) and then saving the settings.	
		Hue	Adjusts the tone of the screen colors.
		Saturation	Adjusts the saturation of the screen colors. The lower the value, the less saturated and brighter the colors become. The higher the value, the more saturated and darker the colors become.
	Black Level	Sets the offset level (for HDMI only).  • <b>Offset:</b> as a reference for a video signal, this is the darkest color the monitor can display.	
		High	Keeps the current contrast ratio of the screen.
		Low	Lowers the black levels and raises the white levels from the current contrast ratio of the screen.

Picture Adjust	DFC	On	Adjusts the brightness automatically according to the screen.
		Off	Disables the <b>DFC</b> feature.
	Picture Reset	Do you want to reset your picture settings?	
		No	Cancel the select.
		Yes	Returns to the default settings.

Settings > Input		Description	
Input	Input List	Selects the input mode.	
	Aspect Ratio	Adjusts the aspect ratio of the screen.	
		Full Wide	Displays the video in widescreen, regardless of the video signal input.
		Original	Displays video according to the aspect ratio of the video signal input.
		<b>NOTE</b> <ul style="list-style-type: none"> <li>The display may look the same for <b>Full Wide</b> and <b>Original</b> options at the recommended resolution.</li> </ul>	
	Auto Input Switch	When automatic input switch is set to <b>On</b> , display will automatically switch to new input when connected.	
		On	Enables <b>Auto Input Switch</b> .
		Off	Disables <b>Auto Input Switch</b> .

Settings > General		Description	
General	Language	Sets the menu screen to the desired language.	
	SMART ENERGY SAVING	High	Saves energy using the high-efficiency SMART ENERGY SAVING feature.
		Low	Saves energy using the low-efficiency SMART ENERGY SAVING feature.
		Off	Disables the SMART ENERGY SAVING feature.
		<b>NOTE</b> <ul style="list-style-type: none"> <li>The value of energy saving data may differ depending on panel and panel suppliers.</li> <li>If you select the option of <b>SMART ENERGY SAVING</b> is <b>High</b> or <b>Low</b>, monitor luminance become lower or higher depend on source.</li> </ul>	
	Power LED	On	The power LED turns on automatically.
		Off	The power LED turns off.
	Automatic Standby	Feature that automatically turns off the monitor when there is no movement on the screen for a period of time. You can set a timer for the auto-off function. ( <b>8H</b> , <b>6H</b> , <b>4H</b> and <b>Off</b> )	
	HDMI Compatibility Mode	HDMI Compatibility Mode feature can recognize the legacy equipment that does not support HDMI 2.0.	
		On	Enables <b>HDMI Compatibility Mode</b> .
		Off	Disables <b>HDMI Compatibility Mode</b> .
		<b>NOTE</b> <ul style="list-style-type: none"> <li>If the connected device does not support <b>HDMI Compatibility Mode</b>, the screen or sound may not work properly.</li> <li>Some older graphics cards do not support HDMI 2.0, but you can select HDMI 2.0 resolution in the control panel of window.</li> <li>This may cause the screen to appear abnormally.</li> </ul>	
	DisplayPort Version	Please set the DisplayPort version to match the version of the connected external device.	

General	OSD Lock	This feature disables the configuration and adjustment of menus.	
		On	Enables <b>OSD Lock</b> .
		Off	Disables <b>OSD Lock</b> .
		<b>NOTE</b> <ul style="list-style-type: none"> <li>All features are disabled except <b>Brightness, Contrast</b> in <b>Picture Adjust</b>, <b>Input, OSD Lock</b> and <b>Information</b> in <b>General</b>.</li> </ul>	
	Information	The display information will be shown the Total Power On Time, Resolution.	
	Reset to Initial Settings	Do you want to reset your settings?	
		No	Cancel the select.
		Yes	Returns to the default settings.

## TROUBLESHOOTING

Nothing is displayed on the screen.	
Is the monitor's power cord plugged in?	Check if the power cord is correctly plugged into the power outlet.
Is the power LED on?	Check the power cable connection and press the power button.
Is the power on and the power LED displaying white?	Check that the connected input is enabled ( <b>Settings &gt; Input</b> ).
Is the power LED blinking?	<ul style="list-style-type: none"> <li>• If the monitor is in sleep mode, move the mouse, or press any key on the keyboard, to switch the display on.</li> <li>• Check if the computer is turned on.</li> </ul>
Is the <b>The screen is not currently set to the recommended resolution. If you have no video or the screen flickers, see the troubleshooting guide in the product owner's manual.</b> message being displayed?	<ul style="list-style-type: none"> <li>• This occurs when signals transferred from the PC (graphics card) are out of the recommended horizontal or vertical frequency range of the monitor. Please see the Product Specification section of this manual to set the appropriate frequency.</li> </ul>
Is the <b>No Signal</b> message being displayed?	This is displayed when the signal cable between the PC and the monitor is missing or disconnected. Check the cable and reconnect it.
Have you installed the display driver?	<ul style="list-style-type: none"> <li>• Be sure to install the display driver from our web site: <a href="http://www.lg.com">http://www.lg.com</a>.</li> <li>• Make sure to check if the graphics card supports Plug and Play function.</li> </ul>

Some features are disabled.	
Are some functions not available when you press the Menu button?	The OSD is locked. Go to <b>Settings &gt; General</b> and set <b>OSD Lock</b> to <b>Off</b> .

The screen retains an image.	
Does image sticking occur even when the monitor is turned off?	<ul style="list-style-type: none"> <li>• Displaying a still image for a prolonged time may cause damage to the screen, resulting in the retention of the image.</li> <li>• To extend the lifetime of the monitor, use a screensaver.</li> </ul>

<b>Screen display is unstable and shaky. / Images displayed on the monitor leave shadow trails.</b>	
Did you select the appropriate resolution?	If the selected resolution is HDMI 1080i 60/50 Hz (interlaced), the screen may be flickering. Change the resolution to 1080p or the recommended resolution.

## NOTE

- **Vertical Frequency:** In order to display an image, the screen must be refreshed dozens of times per second, like a fluorescent lamp. The number of times the screen is refreshed per second is called vertical frequency, or refresh rate, and is represented by Hz.
- **Horizontal Frequency:** The time it takes to display one horizontal line is called the horizontal cycle. If 1 is divided by the horizontal interval, the result is the number of horizontal lines displayed per second. This is called horizontal frequency and is represented by kHz.
- Check if the graphics card's resolution or frequency is within the range allowed by the monitor and set it to the recommended (optimal) resolution Control Panel > Display > Menu in Windows. (The settings may differ depending on the operating system (OS) you use.)
- Not setting the graphics card to the recommended (optimal) resolution may result in blurred text, a dimmed screen, a truncated display area or misalignment of the display.
- The setting methods may be different depending on the computer or operating system, and some resolutions may not be available depending on the performance of the graphics card. If this is the case, contact the manufacturer of the computer or graphics card for assistance.
- Some graphics cards may not support 1920 x 1080 resolution. If the resolution cannot be displayed, contact the manufacturer of your graphics card.

<b>The display color is abnormal.</b>	
Does the display appear discolored (16 colors)?	Set the color to 24 bit (true color) or higher. In Windows, go to <b>Control Panel &gt; Display &gt; Menu &gt; Color Quality</b> . (The settings may differ depending on the operating system (OS) you use.)
Does the display color appear unstable or monochrome?	Check if the signal cable is connected properly. Reconnect the cable or reinsert the PC's graphics card.
Are there spots on the screen?	When using the monitor, pixilated spots (red, green, blue, white, or black) may appear on the screen. This is normal for an LCD screen. It is not an error, nor is it related to the monitor's performance.

<b>No sound from the headphone port.</b>	
Are images displayed using DP (DisplayPort) or HDMI input without sound?	<ul style="list-style-type: none"> <li>• Make sure that the headphone port connections are made properly.</li> <li>• Try increasing the volume with the joystick.</li> <li>• Set the audio output of the PC to the monitor you are using. On Microsoft Windows, go to <b>Control Panel &gt; Hardware and Sound &gt; Sound &gt; set the Monitor as default device</b>. (The settings may differ depending on the operating system (OS) you use.)</li> </ul>



## PRODUCT SPECIFICATION

LCD Screen	Color Depth	8-bit / 10-bit color is supported.	
Resolution	Max Resolution	<ul style="list-style-type: none"><li>• 3440 x 1440 @ 85 Hz (HDMI)</li><li>• 3440 x 1440 @ 160 Hz (DP)</li></ul>	
	Recommended Resolution	<ul style="list-style-type: none"><li>• 3440 x 1440 @ 85 Hz (HDMI)</li><li>• 3440 x 1440 @ 160 Hz (DP)</li></ul>	
Power Sources	Power Rating	19 V    2.4 A	
	Power Consumption (Typical)	<ul style="list-style-type: none"><li>• <b>On mode:</b> 48 W (Typical)*</li><li>• <b>Sleep Mode (Standby Mode):</b> ≤ 0.5 W **</li><li>• <b>Off Mode:</b> ≤ 0.3 W</li></ul>	
AC/DC Adapter	DA-48F19, manufactured by Asian Power Devices Inc. <ul style="list-style-type: none"><li>• ADS-48FSK-19 19048EPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC</li><li>• ADS-48FSK-19 19048EPK-1, manufactured by SHENZHEN HONOR ELECTRONIC</li><li>• ADS-48FSK-19 19048EPG-1, manufactured by SHENZHEN HONOR ELECTRONIC</li><li>• MS-Z2530R190-048M0-E, manufactured by MOSO POWER SUPPLY TECHNOLOGY CO LTD</li><li>• MS-V2530R190-048L0-DE, manufactured by MOSO POWER SUPPLY TECHNOLOGY CO LTD</li><li>• MS-V2530R190-048L0-US, manufactured by MOSO POWER SUPPLY TECHNOLOGY CO LTD</li><li>• <b>Output:</b> 19 V 2.53 A</li></ul>		
Environmental Conditions	Operating Conditions	Temperature	0 °C to 40 °C (32 °F to 104 °F)
		Humidity	Less than 80 %
	Storing Conditions	Temperature	-20 °C to 60 °C (-4 °F to 140 °F)
		Humidity	Less than 85 %

Dimensions	Monitor Size (Width x Height x Depth)	
	With Stand	<ul style="list-style-type: none"> <li>• 809.0 x 483.3 x 223.2 (mm)</li> <li>• 31.8 x 19.0 x 8.7 (inches)</li> </ul>
	Without Stand	<ul style="list-style-type: none"> <li>• 809.0 x 358.9 x 91.5 (mm)</li> <li>• 31.8 x 14.1 x 3.6 (inches)</li> </ul>
Weight (Without Packaging)	With Stand	6.8 kg (14.9 lbs)
	Without Stand	5.8 kg (12.7 lbs)

**Specifications are subject to change without notice.**

- The symbol means alternating current, and the symbol means direct current.
- The Power Consumption level can be different by operating condition and monitor setting.
  - The On mode power consumption is measured with LGE test standard (Full White pattern , Maximum resolution).
  - The monitor goes to the Sleep Mode in a couple of minutes (Max 5 minutes).

## **Factory Support Mode (Preset Mode, PC)**

### **(DisplayPort)**

Preset Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Polarity (H/V)	Remarks
640 x 480	31.469	59.94	-/-	
800 x 600	37.879	60.317	+/+	
1024 x 768	48.363	60.0	-/-	
1920 x 1080	67.5	60	+/-	
3440 x 1440	88.84	59.99	+/-	
3440 x 1440	151	100	+/-	
3440 x 1440	222.14	143.96	+/-	
3440 x 1440	244.26	159.96	+/-	DP Preferred timing

### **(HDMI)**

Preset Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Polarity (H/V)	Remarks
640 x 480	31.469	59.94	-/-	
800 x 600	37.879	60.317	+/+	
1024 x 768	48.363	60	-/-	
1920 x 1080	67.5	60	+/-	
3440 x 1440	43.76	29.95	+/-	
3440 x 1440	73.63	49.95	+/-	
3440 x 1440	127.35	84.96	+/-	HDMI Preferred timing.
2560 x 1440	183	120	+/-	

If you use an input timing that is outside the supported frequency, you may experience poor response speed or image quality.

### HDMI Timing (Video)

Preset Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Remarks
480P	31.5	60	
720P	45	60	
1080P	67.5	60	
2160P	135	60	

### Beep Guide

Menu	Location	Menu	Location	Menu	Location	
Game Mode	1	Game Adjust – Response Time – Fast	2 4 2	Picture Adjust – Gamma – Mode 4	3 4 4	
Game Mode – Gamer1	1 1	Game Adjust – Response Time – Normal	2 4 3	Picture Adjust – Color Temp	3 5	
Game Mode – Gamer2	1 2	Game Adjust – Response Time – Off	2 4 4	Picture Adjust – Color Temp – Custom	3 5 1	
Game Mode – FPS	1 3	Game Adjust – Cross Hair	2 5	Picture Adjust – Color Temp – Warm	3 5 2	
Game Mode – RTS	1 4	Game Adjust – Cross Hair – Red Cross	2 5 1	Picture Adjust – Color Temp – Medium	3 5 3	
Game Mode – Vivid	1 5	Game Adjust – Cros				

Game Mode – Reader	1 6	s Hair – Green Cross	2 5 2	Picture Adjust – Color Temp – Cool	3 5 4	
Game Mode – HDR Effect	1 7	Game Adjust – Cross Hair – Red Dot	2 5 3	Picture Adjust – Color Temp – Manual	3 5 5	
Game Adjust	2	Game Adjust – Cross Hair – Green Dot	2 5 4	Picture Adjust – Color Temp – Manual	3 5 5 1	
		Game Adjust – Cross Hair – Off	2 5 5		Slider	
Game Adjust – 1ms Motion Blur Reduction	2 1	Game Adjust – Game Reset	2 6	Picture Adjust – R/G/B	3 6	
Game Adjust – 1ms Motion Blur Reduction – On	2 1 1	Game Adjust – Game Reset – No	2 6 1	Picture Adjust – R/G/B – Red	3 6 1 Slider	
		Game Adjust – Game Reset – Yes	2 6 2	Picture Adjust – R/G/B – Green	3 6 2 Slider	
Game Adjust – 1ms Motion Blur Reduction – Off	2 1 2	Picture Adjust	3	Picture Adjust – R/G/B – Blue	3 6 3 Slider	
		Picture Adjust – Brightness	3 1	Picture Adjust – Six Color	3 7	
Game Adjust – Free Sync Premium	2 2	Picture Adjust – Brightness	3 1 1 Slider	Picture Adjust – Six Color – Red Hue	3 7 1 Slider	
Game Adjust – Free Sync Premium – Extended	2 2 1	Picture Adjust – Contrast	3 2	Picture Adjust – Six Color – Red Saturation	3 7 2 Slider	
		Picture Adjust – Contrast	3 2 1 Slider		3 7 3 Slider	
Game Adjust – Free Sync Premium – Basic	2 2 2	Picture Adjust – Sharpness	3 3	Picture Adjust – Six Color – Green Saturation	3 7 4 Slider	
		Picture Adjust – Sharpness	3 3 1 Slider		3 7 5 Slider	
Game Adjust – Black Stabilizer	2 3	Picture Adjust – Gamma	3 4	Picture Adjust – Six Color – Blue Hue	3 7 6 Slider	
Game Adjust – Black Stabilizer	2 3 1 Slider	Picture Adjust – Gamma – Mode 1	3 4 1	Picture Adjust – Six Color – Cyan Hue	3 7 7 Slider	
Game Adjust – Response Time	2 4	Picture Adjust – Gamma – Mode 2	3 4 2			
Game Adjust – Response Time – Fast	2 4 1	Picture Adjust – Gamma	3 4 3			

r		mma – Mode 3			
---	--	--------------	--	--	--

Menu	Location	Menu	Location	Menu	Location	
Picture Adjust – Six Color – Cyan Saturation	3 7 8 Slider	Input – Aspect Ratio – Original	4 2 2	General – SMART ENERGY SAVING	5 2	
Picture Adjust – Six Color – Magenta Hue	3 7 9 Slider	Input – Auto Input Switch	4 3	General – SMART ENERGY SAVING – High	5 2 1	
Picture Adjust – Six Color – Magenta Saturation	3 7 10 Slider	Input – Auto Input Switch – On	4 3 1	General – SMART ENERGY SAVING – Low	5 2 2	
Picture Adjust – Six Color – Yellow Hue	3 7 11 Slider	Input – Auto Input Switch – Off	4 3 2	General – SMART ENERGY SAVING – Off	5 2 3	
Picture Adjust – Six Color – Yellow Saturation	3 7 12 Slider	General	5	General – Power LED	5 3	
Picture Adjust – Black Level	3 8	General – Language	5 1	General – Power LED – On	5 3 1	
Picture Adjust – Black Level – High	3 8 1	General – Language – English	5 1 1	General – Power LED – Off	5 3 2	
Picture Adjust – Black Level – Low	3 8 2	General – Language – German	5 1 2	General – Automatic Standby	5 4	
Picture Adjust – DFC	3 9	General – Language – French	5 1 3	General – Automatic Standby – 8H	5 4 1	
Picture Adjust – DFC – On	3 9 1	General – Language – Spanish	5 1 4	General – Automatic Standby – 6H	5 4 2	
Picture Adjust – DFC – Off	3 9 2	General – Language – Italian	5 1 5	General – Automatic Standby – 4H	5 4 3	
Picture Adjust – Picture Reset	3 10	General – Language – Swedish	5 1 6	General – Automatic Standby – Off	5 4 4	
		General – Language – Finnish	5 1 7	General – HDMI Compatibility Mode	5 5	
		General – Language – Portuguese	5 1 8	General – HDMI Co		
		General – Language – Portuguese (Brazil)	5 1 9			

Picture Adjust – Picture Reset – No	3 10 1	General – Language – Polish	5 1 1 0	Compatibility Mode – On	5 5 1	
Picture Adjust – Picture Reset – Yes	3 10 2	General – Language – Russian	5 1 1 1	General – HDMI Compatibility Mode – Off	5 5 2	
Input	4	General – Language – Greek	5 1 1 2	General – DisplayPort Version	5 6	
Input – Input List	4 1	General – Language – Ukrainian	5 1 1 3	General – DisplayPort Version – 1.4	5 6 1	
Input – Input List – HDMI1	4 1 1	General – Language – Chinese	5 1 1 4	General – DisplayPort Version – 1.2	5 6 2	
Input – Input List – HDMI2	4 1 2	General – Language – Traditional Chinese	5 1 1 5	General – OSD Lock	5 7	
Input – Input List – DisplayPort	4 1 3	General – Language – Japanese	5 1 1 6	General – OSD Lock – On	5 7 1	
Input – Aspect Ratio	4 2	General – Language – Korean	5 1 1 7	General – OSD Lock – Off	5 7 2	
Input – Aspect Ratio – Full Wide	4 2 1					

Menu	Location
General – Information	5 8
General – Reset to Initial Settings	5 9
General – Reset to Initial Settings – No	5 9 1
General – Reset to Initial Settings – Yes	5 9 2


### Supplier's Declaration of Conformity Trade Name LG

- Responsible Party LG Electronics USA, Inc.
- **Address** 111 Sylvan Avenue, North Building, Englewood Cliffs, NJ 07632
- **E-mail** [lg.environmental@lge.com](mailto:lg.environmental@lge.com)

The model and serial number of the product are located on the back and on one side of the product. Record them below in case you ever need service.

- Model \_\_\_\_\_
- Serial No. \_\_\_\_\_

## Documents / Resources

	<b><a href="#">LG 34WP60C LED Monitor LCD Screen</a></b> [pdf] Owner's Manual 34WP60C LED Monitor LCD Screen, 34WP60C, LED Monitor LCD Screen, Monitor LCD Screen, LCD Screen, Screen
---	--

## References

- [LG Open Source](#)
- [FreeSync™ Technology | FreeSync Premium Pro HDR Games | AMD](#)
- [Computer Products & Accessories: Locks & Docks | Kensington](#)
- [LG Electronics & Home Appliances | Shop Now | LG USA](#)
- [User Manual](#)