



Eaton UPS battery replacements

Batteries are the heart of any UPS system, and we want to make sure they are always operating in the best possible condition.



Powering Business Worldwide

HOW TO EXTEND UPS LIFE WITH

Easy Battery+

Battery+

Eaton's battery design maintains runtime, even after multiple discharges, giving you the confidence that your batteries will perform as expected, and keep your applications up and running.

Easy Battery+

This is a service product which is offering a complete batteries tray to exchange the internal batteries. The whole batteries exchange process will be therefore much **quicker and safer** than swapping batteries one by one.



Reliability

- The battery is the main component of the UPS which needs to be replaced during the life time of the product
- The use conditions of the battery can drastically reduce if the UPS runs above 30°C
- Extend UPS life or prevent a battery failure by replacing the battery tray after 4 years



Flexibility

- Eaton has designed the UPS to replace the battery tray
- The replacement is safe and easy by removing the front panel
- The battery replacement is a hot swappable solution and does not need to switch off the load and UPS



Safety

- Every battery pack includes the safety notice to make sure that the battery installation is safe

Battery+






Battery+ provides tested and certified new loose batteries for your UPS.

Eaton UPS compatibility list




To find the kit suitable for your UPS you can use the

 [Eaton Battery Replacement Selector](#)

or check the table bellow




Easy Battery+	Reference	Compatibility
	EB001SP / EB001WEB	5SC 3000i RT2U, 5PX 3000i RT2U Netpack, 5130 2500 RT 2U, 5130 3000 RT 2U, EX / Pulsar M 2200 VA 2U, EX / Pulsar M 3000 VA 2U
	EB002SP / EB002WEB	5PX 3000i RT3U, 5130 3000 RT 3U, EX / Pulsar M 2200 VA 3U, EX / Pulsar M 3000 VA 3U, EX 2200 3U Marine, EX 3000 3U Marine
	EB003SP / EB003WEB	9SX 2000i Rack2U, 9SX 3000i Rack2U, 9SX EBM 72V Rack2U (Qty: 2), 9130 2000 RM, 9130 3000 RM
	EB004SP / EB004WEB	5SC 2200i RT2U, 5PX 1500i RT2U, 5PX 1500i RT2U Netpack, 5PX 2200i RT2U, 5PX 2200i RT2U Netpack, 5130 1250 RT 2U, 5130 1750 RT 2U
	EB005SP / EB005WEB	9130 2000, 9130 3000, 9130 2000 Marine tower, 9130 3000 Marine tower
	EB006SP / EB006WEB	9SX 5000i RT3U, 9SX 6000i RT3U, 9PX 5000i HotSwap, 9PX 5000i RT3U Netpack, 9PX 6000i HotSwap, 9PX 6000i RT3U Netpack
	EB007SP / EB007WEB	5SC 1000i
	EB008SP / EB008WEB	5P 850i, 5P 1150i
	EB009SP / EB009WEB	5P 1550i
	EB010SP / EB010WEB	5P 650i Rack1U
	EB011SP / EB011WEB	5P 850i Rack1U, 5P 1150i Rack1U
	EB012SP / EB012WEB	Eaton 5P 1550i Rack1U
	EB013SP / EB013WEB	EX 1000, EX 1500, EX 1500 RT2U Marine

Eaton UPS compatibility list

Easy Battery+	Reference	Compatibility
	EB014SP / EB014WEB	9130 1500 RM
	EB020SP / EB020WEB	5SC 1000i Rack2U
	EB021SP / EB021WEB	5SC 1500i Rack2U
	EB022SP / EB022WEB	5SC 1500i
	EB023SP / EB023WEB	5SC 750i
	EB024SP / EB024WEB	9130 700
	EB025SP / EB025WEB	9130 1000, 9130 1000 Marine tower
	EB026SP / EB026WEB	9130 1500
	EB027SP / EB027WEB	9130 1000 RM
	EB028SP / EB028WEB	9SX 700i
	EB029SP / EB029WEB	9SX 1000i, 9SX 1000i Marine
	EB030SP / EB030WEB	9SX 1500i
	EB031SP / EB031WEB	9SX 2000i, 9SX 3000i, 9SX 3000i Marine
	EB032SP / EB032WEB	9SX 5000i (Qty:4), 9SX 6000i (Qty:4), 9130 5000 (Qty:4), 9130 6000 (Qty:4)
	EB033SP / EB033WEB	9SX 1000i Rack2U, 9SX EBM 36V Rack2U (Qty: 2)

Eaton UPS compatibility list

Easy Battery+

Easy Battery+	Reference	Compatibility
	EB034SP / EB034WEB	9SX 1500i Rack2U, 9SX EBM 48V Rack2U (Qty: 2)
	EBP-1613I / EBP-1616IWEB	5PX 1000i RT2U G2, 5PX 1000i RT2U Netpack G2, 5PX EBM 48V RT2U G2(Qty: 2), 9PX 1000i RT2U, 9PX 1000i RT2U Netpack, 9PX 1500i RT2U, 9PX 1500i RT2U Netpack, 9PX EBM 48V RT2U (Qty: 2), 9PX 1500i RT2U Marine
N/A	EBP-1614I / EBP-1614IWEB	5PX 1500i RT2U G2, 5PX 1500i RT2U Netpack G2
	EBP-1616I / EBP-1616IWEB	5PX EBM 72V RT2U G2(Qty: 2), 9PX 2200i RT2U, 9PX 2200i RT2U Netpack, 9PX EBM 72V RT2U (Qty: 2)
	EBP-1617I / EBP-1617IWEB	5PX 2200i RT2U G2, 5PX 2200i RT2U Netpack G2, 5PX 3000i RT2U G2, 5PX 3000i RT2U Netpack G2, 9PX 3000i RT2U, 9PX 3000i RT2U Netpack
	EBP-1702I / EBP-1702IWEB	5PX 2200i RT3U G2, 5PX 3000i RT3U G2, 9PX 3000i RT3U, 9PX 3000i RT3U HotSwap FR, 9PX 3000i RT3U HotSwap DIN, 9PX 3000i RT3U HotSwap BS, 9PX 3000i RT3U HotSwap HW, 9PX 3000i RT3U HotSwap IEC, 9PX 3000i RT3U Marine
	EBP-1703I / EBP-1703IWEB	5PX EBM 72V RT3U G2(Qty: 2), 9PX 2200i RT3U, 9PX 2200i RT3U HotSwap FR, 9PX 2200 RT3U HotSwap DIN, 9PX 2200i RT3U HotSwap BS, 9PX 2200i RT3U HotSwap HW, 9PX 2200i RT3U HotSwap IEC, 9PX EBM 72V RT3U (Qty: 2)

Battery+

 68750SP / B68750WEB	3S 450 FR, 3S 450 DIN, 3S 550 FR, 3S 550 DIN, 3S 550 BS, 3S 550 IEC, Ellipse ECO 500 FR, Ellipse ECO 500 DIN, Ellipse ECO 500 IEC, 5S 550i, Protection Station 500 FR, Protection Station 500 DIN
 68760SP / B68760WEB	3S 700 FR, 3S 700 DIN, 3S 700 IEC, 3S 700BS, Ellipse ECO 650 FR, Ellipse ECO 650 DIN, Ellipse ECO 650 IEC, Ellipse ECO 650 USB FR, Ellipse ECO 650 USB DIN, Ellipse ECO 650 USB IEC, 5S 700i, Ellipse PRO 650 FR, Ellipse PRO 650 DIN, Ellipse PRO 650 IEC, Protection Station 650 USB FR, Protection Station 650 USB DIN, 3S 700 FR, 3S 700 DIN, 3S 700 IEC
 68761SP / B68761WEB	Ellipse ECO 1200 USB FR, Ellipse ECO 1200 USB DIN, Ellipse ECO 1200 USB IEC, 5S 1000i, Ellipse PRO 1200 FR, Ellipse PRO 1200 DIN, Ellipse PRO 1200 IEC, EX 700
 68765SP / B68765WEB	3S 850 FR, 3S 850 DIN, 3S 850 BS Ellipse ECO 800 USB FR, Ellipse ECO 800 USB DIN, Ellipse ECO 800 USB IEC, Ellipse PRO 850 FR, Ellipse PRO 850 DIN, Ellipse PRO 850 IEC, 5SC 500i, 5P 650i, Protection Station 800 USB FR, Protection Station 800 USB DIN
 68766SP / B68766WEB	Ellipse ECO 1600 USB FR, Ellipse ECO 1600 USB DIN, Ellipse ECO 1600 USB IEC, 5S 1500i, Ellipse PRO 1600 FR, Ellipse PRO 1600 DIN, Ellipse PRO 1600 IEC

Datasheet Easy Battery+ / Battery+

TECHNICAL SPECIFICATIONS	EB001SP / EB001WEB	EB002SP / EB002WEB	EB003SP / EB003WEB	EB004SP / EB004WEB	EB005SP / EB005WEB	EB006SP / EB006WEB	EB007SP / EB007WEB	EB008SP / EB008WEB	EB009SP / EB009WEB	EB010SP / EB010WEB
Battery Characteristics										
Battery	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 5Ah	12V 9Ah	12V 9Ah	12V 9Ah	6V 9Ah
Number of battery	6	6	6	4	8	15	2	2	3	2
Battery pack voltage	72V	72V	72V	48V	96V	180V	24V	24V	36V	12V
Dimensions H x W x D / Weight										
Dimensions (mm)	75x215x475	104x215x315	75x104x465	75x215x315	104x290x315	112x215x467	68x210x155	116x215x470	68x260x205	37x210x170
Weight (kg)	16.15	16.36	15.2	11.38	24.5	28.25	6	6	9.2	2.5
Customer Service & Support										
Warranty	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year

TECHNICAL SPECIFICATIONS	EB011SP / EB011WEB	EB012SP / EB012WEB	EB013SP / EB013WEB	EB014SP / EB014WEB	EB020SP / EB0120WEB	EB021SP / EB021WEB	EB022SP / EB022WEB	EB023SP / EB023WEB	EB024SP / EB024WEB	EB025SP / EB025WEB
Battery Characteristics										
Battery	6V 9Ah	6V 9Ah	12V 9Ah	12V 9Ah	12 9Ah	12V 9Ah	12V 9Ah	12V 7Ah	12V 9Ah	12V 9Ah
Number of battery	4	6	3	4	2	3	3	2	2	3
Battery pack voltage	24V	36V	36V	48V	24V	36V	36V	24V	24V	36V
Dimensions H x W x D / Weight										
Dimensions (mm)	37x320x210	37x470x210	74x320x155	75x205x307	77x210x310	77x210x310	160x69x305	68x210x155	150x192x67	150x200x67
Weight (kg)	5.2	9	9.2	10.4	7.69	10.69	7.8	6	7.33	10.33
Customer Service & Support										
Warranty	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year

TECHNICAL SPECIFICATIONS	EB026SP / EB026WEB	EB027SP / EB027WEB	EB028SP / EB028WEB	EB029SP / EB029WEB	EB030SP / EB030WEB	EB031SP / EB031WEB	EB032SP / EB032WEB	EB033SP / EB033WEB	EB034SP / EB034WEB	EBP-1613I / EBP-1613IWEB
Battery Characteristics										
Battery	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah
Number of battery	4	3	2	3	4	8	5	3	4	4
Battery pack voltage	48V	36V	12V	36V	48V	96V	60V	36V	48V	48V
Dimensions H x W x D / Weight										
Dimensions (mm)	305x192x67	310x154x70	205x160x67	260x210x67	310x205x67	310x285x105	360x155x105	305x155x70	307x205x75	77x210x310
Weight (kg)	11.33	10.33	5.4	8.1	10.8	21.6	13.5	8.1	10.8	11.56
Customer Service & Support										
Warranty	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year

TECHNICAL SPECIFICATIONS	EBP-1614I / EBP-1614IWEB	EBP-1616I / EBP-1616IWEB	EBP-1617I / EBP-1617IWEB	EBP-1702I / EBP-1702IWEB	EBP-1703I / EBP-1703IWEB	68750SP / 68750WEB	68760SP / 68760WEB	68761SP / 68761WEB	68765SP / 68765WEB	68766SP / 68766WEB
Battery Characteristics										
Battery	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 9Ah	12V 5Ah	12V 7Ah	12V 7Ah	12V 9Ah	12V 9Ah
Number of battery	4	6	6	6	6	1	1	2	1	2
Battery pack voltage	48V	72V	72V	72V	72V	12V	12V	24V	12V	24V
Dimensions H x W x D / Weight										
Dimensions (mm)	75x215x315	77x210x470	77x210x470	110x210x310	110x210x310	106x70x90	100x65x151	100x130x151	100x65x151	100x130x151
Weight (kg)	11.55	16.1	16.1	16.56	16.56	1.95	2.5	5	2.5	5
Customer Service & Support										
Warranty	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year	1 year



How to install your battery pack?



[View the battery installation instructions videos](#)



[Click on the link or scan the QR code](#)



Powering Business Worldwide

Eaton
EMEA Headquarters
Route de la Longeraie 7
1110 Morges, Switzerland
Eaton.eu

© 2022 Eaton
All Rights Reserved
May 2022

Eaton is a registered trademark.

All other trademarks are property
of their respective owners.

Follow us on social media to get the
latest product and support information.

