




Installation Instructions



Smart Switch Relay Mechanism

Product Code:
KASTA-S350BH-W

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000(current edition) and other relevant Standards and Regulations.
 - Electricity **MUST** be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
 - Indoor use only. Not suitable for damp or explosive environments.
 - Complies to Australian Standards AS/NZS 60669.2.1, AS/NZS 60669.1, AS/NZS 4268, AS/NZS CISPR 15.
 - No user serviceable parts inside.
 - A load correction device – X2 Capacitor type 275Vac, 0.10µF, 40/110/56/B – has been included with your KASTA Switch Relay.
- If flickering of the luminaire load is experienced, connect the load correction device across the line output of the KASTA Switch Relay to improve performance.

FEATURES

- Relay for switching a load on and off.
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Push Button Control.
- Fits most Australian Standard wall mech apertures.
- Simple 2 wire connection-Active in and load out.
- Integral blue backlight that can be enabled/disabled after installation.
- Multi-way load switching possible using KASTA remote switches.
- Built-in thermal current overload protection.

FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
DELAYS TO OFF	3 CLICKS*
BACKLIGHT ON/OFF	7 CLICKS
FACTORY RESET	9 CLICKS

Turns lights on or off. When turned ON, lights will adjust to previous brightness setting.

Load automatically turns off after set time.

Disables or enables backlight on button.

Restores all settings back to factory.

*If successful, light will pulse the number of times that the switch was clicked, indicating function.

TECHNICAL SPECIFICATIONS

Supply: 220-240V AC 50Hz

Operating Temp: -20°C to 40°C

LED Load Wattage: 15W - 350W (Will require "Load Bypass" if less than 15W)
Small motors such as ceiling exhaust fans Max. 100 W (0.5 A @ 0.8 pf)

Thermal Derating: 25°C - 40°C (350W-175W)

Max Switch Load and Multi Gang: 350W I 1, 260W I 2, 190W I 3 (Multi Gang Derating on single switch plate)

CONNECTION DIAGRAM

