

Thank you for purchasing the HB32. With our baby mo

Please retain your original dated sales receipt for your HelloBaby product, you will need to provide a copy of y varranty status. Registration is not required for warr

Please make sure the following included in your pack rx2 Parent unit x 1 Camera unit x 1 User manual x 1 Wall-mounting kit x 1

#### 1. SAFETY INSTRUCTIOINS

CAUTION: Keep the device away from children.

Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of (more than 3ft (0.9m) away). Never use extension cords with AC Adapters. Only us the AC Adapters provided.

Choking hazard: This product contains small parts, please be careful when unpack and issemble the product.

Read and keep to instructions: All the safety and operating in structions should be read before the video baby monitor is operated. This product cannot replace respons

Water and moisture: This product is designed for indoor use only. The unit should not be exposed to rain, moisture, dripping or splashing. No objects filled with liquid should be laced on top of, or beside the product, such as a glass or vase. This item should not be use

DO NOT: Use the appliance if the cord or plug is damaged. If your baby monitor is not operating properly or has suffered any damage, contact "HelloBaby" service center to equest inspection and repair of the appliance in order to avoid any possible risk. DO NOT: Do not attempt to repair or adjust any of the electrical or mechanical functions o the unit. Otherwise, the guarantee will be made void.

entilation: This baby monitor should not be used on a bed, sofa, rug or similar surface that may block the ventilation openings, or be placed in an enclosed area such as a bookcase or drawer that may impede air flow. **Keep away from sources of heat:** This unit should not be exposed to direct heat sources

such as a candle, radiator, heat register, stove or other appliance that emits heat. The unit

Power source: This unit should only be used with the AC power adapters included in this package (rated 6V 600mA/). Damage requiring service: This unit should be serviced by qualified personnel only when

ects have fallen or liquid has been spilled into the product; The units have been exposed to rain;

The units do not appear to operate normally or exhibits a distinct change in performanc

sleeping or playing in their room anytime.

We offer one-year warranty from the original purchase date against defects in workmansh nd materials. If you have warranty or support issues, please contact our after-sales servi to confirm via email.

#### 3.INSTALLATION GUIDELINES

- \* To use your parent unit and camera unit together, you have to establish a radio link between them, and the range will be affected by environmental conditions
- \* Any large metal object, like a refrigerator, a mirror, a filling cabinet, metallic doors or einforced concrete between the baby and parent unit may block the radio signal.
- The signal strength may also be reduced by other solid structures,like walls, or by radic # r electrical equipment, such as TV, computers, cordless or mobile phones, fluorescent lights or dimmer switches.
- Jse of other 2.4GHz product, such as wireless networks (Wi-Fi routers), Bluetooth systems, or microwave ovens, may cause interference with this product, so keep the baby monitor away at least 5ft (1.5m) from such products, or turn them off if they cause

#### I. PLACEMENT OF THE BABY MONITOR

The camera can be placed on the desktop or mounted on the wall. Don't place baby monit on soft quiltsor blankets or in the corners of cupboards, shelves, etc; Keep the baby monit away from heat sources such as radiators, chimneys, cookers and direct sunlight; Keep the paby unit away from TV sets, microwave oven and radios. If interference occurs, move the amera to elsewhere; \* Place the camera within 6 feet (2 meters) of the area being monitored for optimum

performance.

# 5. GETTING STARTED

#### 5.1 TURN ON THE BABY UNIT:


- 1. Insert the DC plug of the power adapter into the DC jack in the rear of the Baby Unit;
- 2. Insert the other end of the power adapter into a suitable electrical outlet; 3. Once the adapter is connected, the power LED will light up; 5.2 TURN ON THE PARENT UNIT:
- L. Insert the DC plug of the power adapter into the DC jack in the side of the parent Unit; Insert the other end of the power adapter into a suitable electrical outle
- . Press and hold the power key on the top of the parent unit 4.Once parent unit is on, the power LED will light up and the image will display on the LCE


# 5.3 INFRARED NIGHT VISION (AUTOMATIC)

The infrared night vision function allows the camera to pick up images in dark or low light conditions. In this mode, only black and white images will be displayed on the

monitor, the optimum image lie in where baby unit is 6ft (2m) away from object. The camera is in night vision mode, the icon 🔰 will be displayed on the top of screen.

# 6.1 PARENT UNIT OVERVIEW:





#### 6. 3 ICONS OVERVIEW:

Till Signal Strength	■(11))) Volume	<b>⊕</b> Zoom
🕘 Alarm	ناماً Brightness	👤 Two-Way Talk
🎝 Lullaby	V Night vision	<b>vox</b> VOX
🖢 Camera	Battery Level	Temperature

#### 7. KEY OPERATION

7.1 POWER SAVE/SCREEN OFF

Short press the power  $\boldsymbol{\upsilon}$  key to turn on / off the screen 7.2 VOLUME ADJUSTMENT

Press the ▲ key to increase the volume; Press the ▼ key to decrease the volume;

7.3 BRIGHTNESS ADJUSTMENT Press the ◀ key to decrease the brightness; Press the ▶ key to increase the brightness

7.4 CAMERA VIEW / SCAN Press Scan ( key to view / scan camera; During scan mode, the scan icon ( will be displayed on the top of screen. And each camera's video will stay on the LCD around 10 seconds and then turn to next camera alternately;

7.5 DIGITAL ZOOM & PAN / TILT Press and hold the (2) key around 2 seconds to operate Zoom in / out; At the Zoom mod press the ◀ key to Pan left; press ▶ key to Pan right; press ▲ key to tilt up; press ▼ key to tilt down; During digital zoom mode, the zoom icon ⊕ will be displayed on the top of

Warm reminder: If you want to adjust the volume/Brightness, you have to exit the Zoom

7.6 TALK TO BABY Press and hold 🕏 key to enter two way talk mode. A microphone icon 🖢 will be displaye on the top of the LCD screen while this function is working. Release the button when ve

have finished talking and listening to the sound from the baby's room again. Note: When you are in the two-way talk mode, the parent unit speaker is muted.

# 8. MENU OPERATION

8.1 PAIRING THE CAMERA AND MONITOR

The baby unit is pre-registered to your parent unit. You do not need to register it again unless the baby unit loses its link with the parent unit. To re-register your baby unit, or register a new baby unit, follow the procedure below:

Note: Camera icon with "\*" means it is well registered. You should select and pair with the camera icon without "\*" sign.

1.Press the MENU (a) key then the menu will pop up;

2.Press the ◀/▶ key until the ② camera icon is highlighted, then press ▲/▼ key to

select your desired camera; 3. Press OK ( key to enter into sub-menu

4. Press ▲ / ▼ key to select ADD CAM P + then press OK ( key;

5. When the 'Pairing' sign displayed on the LCD screen, press the PAIR button on the back of camera:

6. Once paired, 'pair is succeed' shows on the LCD screen.

7. If failed, please repeat the above steps

8. Press the key to Exit.
8.2 DELETTING A CAMERA

. Press the MENU key and the menu will pop up; 2. Press the ◀ / ▶ key until the camera icon 🔓 is highlighted then press 🛦 / ▼ key to

select your desired camera; 3 Press OK ( key enter into sub-men

4. Press ▲ / ▼ key to select DEL CAM F then press OK (♣) key:

5. Press ▲ / ▼ key to select ▼; 6. Press OK ( key to confirm the o

7. Press the 📳 key to Exit. 8.3 VOX SETTING

This option in the parent unit menu allows you to set the microphone sensitivity of the baby unit. The microphone sensitivity determines what noise level the baby unit picks up, e.g.

ou would like to hear when your baby cries, but you may be less interested in its babbling. 1. Press the MENU (a) key and the menu will pop up

2. Press the ◀/▶ key until the icon VOX is highlighted, then press ▲/▼ key to select

3. Press OK key to confirm

Note: VOX-Lo is Low sensitivity level;

Note: VOX-Hi is High sensitivity leve

8.4 TEMPERATURE UNIT SETTING

1. Press the MENU/OK ∰ key and the menu will pop up; 2. Press the ◀ / ▶ key until the temperature icon ♂ is highlighted;

3. Press  $\blacktriangle$  /  $\blacktriangledown$  key to select between °F or °C ;

4. Press OK 🖺 key to confirm

5. Press the key to Exit.

Note: For this unit, The environment test temperature range is 0~50 °C.

Room temperature alarm setting

1. Enter the temperature selection interface, press ▼ direction key, choose Alert, then press **OK** key to enter setup;

2. Open the environment temperature alarm function, select ON, press OK key to confirm

close the environment temperature alarm function, select OFF; press OK key to confir . Set alarm temperature value Choose  $\mathbf{ON},$  then press  $\mathbf{OK}$  to confirm, enter the setup interface of high and low temperature; Now, the Hight value appears red box, press the press **OK** key to confirm; When the highest temperature alarm value is set, it will automatically jump into the lowest temperature alarm value set; When the Low temperature alarm value appears red box, press ▲ / ▼ key to make lowest environ temperature alarm value adjustment, then press **OK** key to confirm and the system returns to the superior directory automatically; If you don't want to change, press the

Return key to return to the superior directory; Note: the High temperature alarm range is 20-40  $^{\circ}$ C, and the Low temperature alarm range is 0-19 ℃. 8.5 LULLABY SETTING

You can soothe the baby to sleep by playing a gentle lullaby from the baby unit.

1. Press the MENU (a) key and the menu will pop up;

2. Press the ◀ / ▶ key until the lullaby ) icon is highlighted;

3. Press ▲ / ▼ key to select one of the 8 available lullabies, silence or looping;

4. Press OK ( key to confirm:

Note 1: Once the lullaby is turned on, the lullaby ) icon will display on the top of the Note 2: The lullaby default setting is OFF.

Note 3: Lullaby loop playing function is, play all the lullabies one time. 8.6 ALARM SETTING You can use the alarm to remind yourself to feed your baby / change diaper / sleeping, etc. 1. Press the MENU (a) key and the menu will pop up;

 Press the ◀ / ▶ key until the alarm icon is highlight Press ▲ key to decrement or press ▼ key to increment; 4. Press OK ( key to confirm:

Note 1: The minimum unit is 0.5 hour. The maximum setting is 4 hours (8 levels). Note 2: Once the alarm is turned on, alarm ② icon will display on top of the screen. Note 3: The alarm default setting is OFF. Note 4: When the alarm is ringing, press any key to answer it.

# 9. TROUBLE SHOOTING

The power adapters may not be properly connec No reception on the \* Confirm that the camera and monitor are ON; \* Camera may be far away from the monitor, Camera and monitor may not be properly paired; follow PAIRING instruction Move the monitor close to the camera; \* The camera or monitor may be placed too close to many metal objects \* Other electronic devices may be interfering with the signal; \* The battery power is running low; The camera and monitor may be placed too closed The volume on the monitor may be set too high; (high pitched noise Repower the baby unit (plug out the adapter, then plug it into t socket again);

Frequency	2400~2483.5MHz
Power adapter Input	Parent Unit: Input: 100-240VAC 50/60Hz
	Output: 6VDC 600mA
	Camera Unit: Input: 100-240VAC 50/60Hz
	Output: 6VDC 600mA
Operating Range	Up to 1000ft (300m) outdoor line of sight Up to 165ft (50m) indoor
Display	3.2" TFT LCD
Battery (Parent Unit)	Li-ion 3.7V 950mAh (3.515Wh)
Battery Life	Up to 8 hours
Camera unit and parent unit RF power ( for CE)	less than 20dBm
Operation environment	Temperature : +32F- +104F( 0 °C -40 °C )
	Relative Humidity : 15%-85%

Press the RESET key at the back of parent unit (behind the

# 11. MAINTENANCE

Clean your baby monitor with a slightly damp or anti-static cloth Never use cleaning agents or solvents.

# 12. DISPOSAL GUIDE FOR BATTERY AND PRODUCT

\* Do not attempt to repair or adjust any of the electrical or mechanical functions of the

\* Remember to dispose of the product in an environmentally responsible way: \* For proper collection and processing of these products, take them to the collection points designated by local authorities. You can also contact the store where you

# FCC AND IC REGULATIONS

This device complies with Part 15 of the FCC Rules. Operation is subject to the following tw conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operat

Changes or modifications not expressly approved by the part responsible for compliance

FCC Statement: This equipment has been tested and found to comply with the limits for a Class B digital  ${\sf S}$ device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonal protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communicatio owever, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or tel evision reception, which can be determined by turning the equipment off and on, the user is encouraged to try to

correct the interference by one or more of the following measures: -Reorient or relocate the receiving antenna

-Connect the equipment into an outlet on a circuit different from that to which the receiver -Consult the dealer or an experienced radio/TV technician for help."

ndustry Canada This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause nterference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils rac exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'anna brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre l This equipment complies with Industry Canada radiation exposure limits set forth for an

8

Cet équipement est conforme à l'exposition aux rayonnements Industry Canada limites tablies pour un environnement non contrôlé.

FCC/IC RF Radiation Exposure Statement Caution: This Transmitter must be installed to rovide a separation distance of at least 20 cm from all persons. IC Radiation Déclaration d'exposition Attention: Cet émetteur doit être installé pour ournir une distance de séparation d'au moins 20 cm de toute personne

# EU Declaration of Conformity (DoC)

Hereby, HelloBaby Technology (HK) Limited declares that the radio equipment type (Digital Video Baby Monitor HB32) is in compliance with RED Directive 2014/53/EU. he full text of the EU declaration of conformity is available on the website

Model: HB32


sponsible Party: Startline LLC Add: 22 Hazelwood Drive, Jericho, NY 11753 el: 1-516-681-3729

henzhen Videotimes Technology Co.,Ltd m 601, 6/F, Tower B, United Financial Building, No.1 Shihua Road, Futian Free Trade Zone, Shenzhen, China

mproper or incorrect use of batteries may cause corrosion or battery leakage, which ould cause personal injury or damage to property. Use only the types of the batteries CAUTION: Risk of Fire and Burns. Do Not Open, Crush, Heat Above 45 degree C or Incinerate

WARNING IR emitted from this product. Do not stare at operating lamp

**MARNING** 



# **AVERTISSEMENT**

DANGER D'ÉTRANGLEMENT: Des enfants se sont

HelloBaby®

Focus on Mom & Baby Care!



ÉTRANGLÉS avec des cordons électriques. Garde le cordonélectrique hors de la portée des enfants(à plus de 0.9m/3 pi du lit d'enfant). Ne pas enlever cette étiquette.

S SAD CE Z







www.hellobabv.net.cn

Ver: 1.3 Part No: 20040093B

Made in China