

CCT Remote

Model No.: C3

Product Feature

- 2.4GHz wireless transmitting technology , fast transmitting, stable signal and anti-interference
- Control multi devices at the same time
- Dim cct and brightness
- Support Miboxer/Milight 2.4G controller and light series
- Control Distance 30m
- Magnetic installation
- For commerical, hotel and home lighting





Product Parameter

Product Name: :	CCT remote	Working temperature: :	-10~40°C
Model No.::	C3	EMC standard(EMC):	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-3 V2.3.2
Working voltage:	3V(AAA*2PCS)	Security Standard (LVD) :	EN 61347-2-11:2001+A1: 2019 EN 61347-1: 2015+A1:2021 EN 62493:2015+A1:2022
Standby consumption:	15μA	Radio equipment (RED) :	ETSI EN 300 400 V2.2.1
Transmission:	6dBm	Certification:	CE、EMC、LVD、RED
Protocol:	2.4GHz RF		
Modulation:	GFSK		
Control Distance:	30M		

Remote

Remote Holder



Function



Function

Dim Brightness

Indicator is red



Up and down to change brightness

Dim CCT

Turn on light and short press "ON" 1 time, indicator is orange color while CCT mode is activated




Up and down to change color temperature


Link/Unlink

Link


controller must link with remote before using it



turn off light 10 seconds and turn on again



short press "ON" 3 times within 3 seconds




link is done once light flashes 3 times slowly




Link is failed if light doesn't flash, please repeat above steps
(Attention: can not link again if remote already finished linking)


Unlink



turn off light 10 seconds and turn on again



short press "ON" 5 times within 3 seconds




link is done once light flashes 10 times quickly




Unlink is failed if light doesn't flash, please repeat above steps
(Attention: no need to unlink if the light never be linked)

Installation



Remove the sticker on the holder



Stick the holder on the wall and put remote on the holder

Attention:

1. To control MiBoxer/Mi-Light 2.4G series products, Please refer to the product manual for compatibility.
2. Don't use it in humidity or high temperature area, please take out battery if don't use it frequently and keep it in dry or static electricity area
3. Don't use it near metal or strong magnetic area, it will affect signal and lost distance.



Made in China