



Z-Wave Protocol Implementation Conformance Statement

Z-Wave Floodlight with Motion Detector

General Information

Product Identifier:	EH403-3
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.01:00.07
Z-Wave Certification #:	ZC10-18056122

Product Features

Outdoor Use	Yes
IP (Ingress Protection) Rated	Yes
Supported Notification Types	Home Security
Sensors	Luminance
Color	Black

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0012
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Floodlight with Motion Detector

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	Command Class: -Device Reset Locally Notification -Notification Report -Binary Report -Sensor Multilevel Report Group Name: Lifeline
2 / 4	Command Class: -Basic Set Group Name: PIR Control

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic
