85*85mm 8折页 105克铜板纸

Smart Wall Switch User Guide

MH01-1/MH01-2/MH01-3/MH01-4

(Wi-Fi)

Notes Before Installation

1. Wi-Fi only support a 2.4GHz network.
2. Only support one way/single pole circuit, Not compatible with 3-way.
3. Basic electrical wiring knowledge or experience required, or please consult a professional electrician.
4. ON/OFF button also can be used as reset button, long press to reset your smart switch to factory defaults.Only do this if you are sure you want to erase all your settings.
5. Applicable only to control lamps, not recommended as other electrical breakers.

No Neutral Required / Neutral Required Version for WiFi

1

Installation

1.Open the package, you will see the switch and Iron plate.





2

2.Secure the Iron plate to the mounting box with 2 screws by screwdriver.



3.Snap the switch onto the Iron plate.



3

Installation Guide

Turn off circuit breaker
Find your light's control in your circuit breaker and turn it off
Then make sure the power is off by flipping your switch a few times.



4

Circuit Connection Diagram

Power Supply Mode: Neutral Wire Required



Safety Notice:
- Cut off the power before installation
- A neutral wire is needed to power the switch.

5

Circuit Connection Diagram

Power Supply Mode: NO Neutral Wire Required



Safety Notice:
- Cut off the power before installation
- No neutral wire
- Need connect the Capacitor it must to be connectedto L1 and Neutral Wire.

6

Specifications

Product Name	Smart Wall Switch
Specifications	MH01-1 / MH01-2/ MH01-3 / MH01-4
Power Supply Mode	With Neutral Wire (No Neutral Wire
Rated Voltage	AC100V-240V (50/60Hz)
Load Power	~LED: 5-150W /Gang(Max) ~Incandescent lamp: 1200W (Max)
Working Environment	-20°C~75°C
Static Power Loss	≤0.5W
Working Humidity	<95%
Wireless Standard	WiFi 2.4GHz IEEE802.11b/g/n
App Support	IOS/Android (Tuya / Smart Life)
Product Size	118x75x35mm

Indicator light meaning

Colour	Status	Description
Blue	Rapidly Blinks	Ready for connection (Default Mode Only)

7

Product Size



8

WiFi+Bluetooth

(New Pairing Mode with Simple Operations)

1.With WiFi+Bluetooth connected for automatic identifcation and easy configuration.
2.No more need to do so many complicated steps for pairing.
3.Quick and easy connection within 8 seconds.



9

Install the "Smart Life"APP

Step A :Find out "Smart Life" app in Apple app store, Google Play, or scan the QR code bellow and install it

The free app"Smart Life" is compatible with mobile devices the support IOS8.0 above, Android 4.4 above

Step B :Enter the register interface, input the email address/phone number for getting the verification code to register an account, Please just login if you already have a Smart Life account.

10

1. Setting Smart life App, How to Register and Login?
2. Download or Scan the QR Code and install Smart Life App.
3. Once download or Scan the QR Code, the App will ask you to register your device.

4. Enter your phone number or email which you prefer and select the country you live in.
5. Obtain verification ctde
6. Enter verification code.
7. Set Password.

11

Step C: Add the switch to smart life app

Note: this smart switch can only support 2.4G network and can not work with 5.0G network. Please check if your home network is 2.4 G and make sure that your phone has been connected to your Wi-Fi home network

(1)Tap"+" button on top right corner to add device, the tap"switch(Wi-Fi)" to enter next page.



12

Default Mode(Recommend)

Step 1:Make sure the indicator blinks rapidly, if not, hold the ON/OFF button for 5 seconds for reset.



Step 2:Enter Wi-Fi password to join your network

Step 3:Wait till device is connected successfully.

Step 4:Device added successfully you can modify device name.

13

APP Operation Interface Introduction



14

APP Operation Interface Function

15

Timing Function Steps



Step 1.
(add schedule)

Step 2.
(select switch)

Step 3.
(set timing rules)

16