Terima kasih karena Anda telah membeli AJAZZ AK820PRO. Produk ini dilengkapi dengan berbagai fitur dan efek lampu yang keren. Kami harap produk ini akan membawa Anda kenyamanan yang belum pernah Anda rasakan sebelumnya dalam menggunakan peranangkat periferal. Untuk informasi pengoperasian lebih lanjut, silakan kunjungi situs web resmi Ajazz untuk mengunduh diver produk.

1. Spesifikasi Dasar

Merek Produk: A.JAZZ

Nomor Model Produk: A.JAZZ AK820PRO

Type Transmisi Kabel: USB-A Nirkabel 2.4G + 5.1 Bluetooth

Tipe Antarmuka Kabel: Type-C terpisah

Ukuran Produk: 327 x 136 x 40mm

Berat Produk: ~910g

Kapasitas Baterai: 4000mAh

Bahan Casing: ABS cetakan injeksi

Baterai Kycaps: PBT material, Stagg OEM

Efek Lampu: RGB, 20 cell efek

Jumlah Tombol: 81 tombol + tombol putar pengatur suara logam

Produk Mounting: Gasket Mount

Matriks: NKRO

Kompatibilitas: Windows Vista / 7/8/10/11, MAC, Android

2. Switch/Light Description

Switch description

TYPE-C: USB-A Receiver Type-C interface

2.4G: 2.4G mode, toggle the switch to the right

USB: wired mode (default), toggle the switch to the middle

BT: BT mode, toggle the switch to the left

Mac: Mac system, toggle the switch to the right

Win: Win system (default), toggle the switch to the left

Indicator Light Description

Caps lock key: Caps lock switch indicator light

Press the Caps lock key and the white light is always on to turn on uppercase, and then press the Caps Lock key to turn off the white light to restore lowercase.

2. Indicator light " " : win lock indicator light

When the Fn+win key is pressed, the indicator is always on and the white light means that win is locked, and it will return to normal when pressed again to unlock.

3. Indicator light " " : low voltage indicator light

The red light flashes slowly when low voltage, the red light is always on when charging, and the red light turns off when it is fully charged.

3. Sleep Mode/Low Power State Bright

3.1. Sleep Mode

① Power saving sleep state: the backlight will be turned off after 5 minutes without key operation on the keyboard, press any button to wake up. The sleep time of the keyboard can be set to 30T(1.4h).

② Deep sleep state: Deep standby after 30 minutes of no key operation on the keyboard, BT is disconnected and sleeps, press any key to wake up the keyboard backlight and connect back to BT(1.4h).

3.2. Low Power State

① Low power state: the battery icon on the screen displays zero grids (indicator 3 is flashing red when low voltage is on)

② Charging status: The battery icon on the screen displays the grids, and there is a lightning mark next to it (indicator 3 indicator 3 is always red when charging)

③ Fully charged state: the battery icon on the screen displays five grids (the indicator light 3 is always on)

4. Mode Connection Description

4.1 BT mode connection: switch to BT position

BT Name	① .BT Channel 1	BT5.1 AK820 5.1-1
	② .BT Channel 2	BT5.1 AK820 5.1-2
	③ .BT Channel 3	BT5.1 AK820 5.1-3

BT channel:

① .Click the key: AK820 Pro + 1 click on the keyboard BT channel, AK820 Pro + 1 click on the keyboard BT channel, AK820 Pro + 1 click on the keyboard BT channel,