50mm

80mm

Tuya Smart

Instruction Manual
Scene Remote Control

Zigbee 3.0

English

ZS-SR-R01-EN-ED23

- Bitte scannen Sie den QR-Code, um das deutsche Handbuch, das Installationsvideo und die Funktion sanfttrübung zu erhalten
- Escanear el código QR para obtener el manual en español, el vídeo de instalación y la introducción de la función
- Veuillez scanner le code QR pour obtenir le manuel en français, la vidéo d'installation et l'introduction des fonctions
- Отсканируйте QR-код, чтобы получить руководство на русском языке, видео по установке и описание функций
- Scansionare il codice QR per ottenere il manuale in italiano, il video di installazione e la guida alle funzionalità per attivare la modalità
- Leia o código QR para obter o manual em português, o vídeo de instalação e a introdução das funções
- Ziskanuj kod QR, aby uzyskać instrukcję, filmy instalacyjne i funkcje
- QR コードをスキャンして、日本語の説明書、インストール ビデオ、機能ガイドを取得してください。
- امسح رمز QR للحصول على دليل باللغة العربية، وفيديو التثبيت، وشرح الوظائف.

Product Introduction

Zigbee | Scene Setting | Remote Control | Battery Power | Mechanical Push On/Off Button

This Scene Remote is powered by battery, which is developed under Zigbee communication. After connecting with Zigbee gateway and adding into Smart Life App, it allows you to quickly "set the scene" for a particular room or living scene, like Reading, Movie, and so on.Scene Remote is a time and energy-saving item alternative to the traditional hard-wired switch, with pouch button design.It can be stick on the wall or put it on everywhere you like.



Scene Remote Control Switch with Your Smart Home



Specification

Model:	ZR-SR-R01
Input Power:	CR 2032 button battery
Communication:	Zigbee 3.0
Dimension:	130×85×15mm
Standby current:	20uA
Working Temperature:	-10°C ~ 45°C
Working humidity:	<90%RH
Button lifecycle:	500K
Frequency Band:	2.405~2.480GHz
Maximum Radio Transmit Power:	≤ +20dBm

Installation and use

1. Energize the equipment
② Slide down to open the battery back cover
③ Remove the battery insulating gasket
④ Pull the battery tab to powered on, and the battery cover back
⑤ Press the button on the device, the indicator light is on, indicating that the device is working normally.

2.Multiple installation options, can be placed flat on any desktop, and the built-in magnet can also be attached to metal.

Connection and Operation



Indicator LED
Long press the button, the indicator will turn on. The indicator flash quickly, it means that the network is in network connection.
Scene Switch Operation Each one button can be adapted upto three different scenarios through the APP:
(Single Click) : Activate the 1st scene
(Double Click) : Activate the 2nd scene
Long Hold 3 s : Activate the 3nd scene

Preparation for Use

① **Download Smart Life App**

Please scan the QR code or download Smart Life on App store.

② **Registration or Log in.**
- Download "Smart Life"Application
- Enter the Registration interface,tap "Register" to create an account by entering your phone number to get verification code and Set password"Choose "Log in" if you already have a Smart Life account.

Add Device

Method one

1.Switch the device on
2.This device must work with Zigbee gateway, please add the gateway to Smart Life App first.
3.Make sure the device is within the effective signal coverage of your Zigbee gateway. Open Smart Life APP scan the QR code and follow the instructions to add the device.

29°C
Living Room
Scene
Device
Smart
Me
Scan this QR code
Add device
Zigbee Gateway
Zigbee Sub-device
Wi-Fi Device
Wi-Fi Gateway