

Power Supply Unit

OnePlus SUPERVOOC 80W
Dual Ports GaN Power Adapter Kit

Packing List

• Power Adapter ×1

• Type-C to Type-C Cable ×1

• User Manual ×1

Specifications

Specifications

MODEL: OSAB7CF3AY

INPUT: 100-130V ~ 50/60Hz 2.5A

Single port output :

Type-C: 5.0V = 3.0A 15.0W or 9.0V = 3.0A 27.0W or 12.0V = 3.0A 36.0W or 15.0V = 3.0A 45.0W or 20.0V = 2.75A Max 55.0W Max or 11.0V = 6.1A Max 67.0W Max or PPS: 5.0-11.0V = 5.0A Max 55.0W Max

USB-A: 5.0V = 3.0A 15.0W or 9.0V = 3.0A 27.0W or 12.0V = 2.5A 30.0W or 11.0V = 6.1A Max 67.0W Max

Dual-port output: 12.0W+30.0W or 12.0W+55.0W Max

INPUT: 200-240V ~ 50/60Hz 2.5A

Single port output :

Type-C: 5.0V = 3.0A 15.0W or 9.0V = 3.0A 27.0W or 12.0V = 3.0A 36.0W or 15.0V = 3.0A 45.0W or 20.0V = 2.75A Max 55.0W Max or 11.0V = 7.3A Max 80.0W Max or PPS: 5.0-11.0V = 5.0A Max 55.0W Max

USB-A: 5.0V = 3.0A 15.0W or 9.0V = 3.0A 27.0W or 12.0V = 2.5A 30.0W or 11.0V = 7.3A Max 80.0W Max

Dual-port outout: 15.0W+30.0W or 15.0W+67.0W Max

Operating temperature/humidity: 0℃~35℃/10%~95%RH

Storage temperature/humidity: -40℃~70℃/10%~95%RH

Applicable models: Support SUPERVOOC mobile phones, and can also provide charging services up to 5V/2A for other mobile phones.

INPUTDual-port outputUSB-AType-C

100-130V ~ 50/60Hz 2.5A

A+C: 12.0W+30.0W Max

5.0V = 2.4A

5.0V = 3.0A
9.0V = 3.0A
15.0V = 2.0A
20.0V = 1.5A Max

A+C: 12.0W+55.0W Max

5.0V = 2.4A

11.0V = 5.0A Max

200-240V ~ 50/60Hz 2.5A

A+C: 15.0W+30.0W Max

5.0V = 3.0A

5.0V = 3.0A
9.0V = 3.0A
15.0V = 2.0A
20.0V = 1.5A

A+C: 15.0W+67.0W Max

5.0V = 3.0A

11.0V = 6.1A Max

Note

1. DO NOT throw this product into fire. Doing so will result in danger.

2. DO NOT disassemble, open, smash, bend, penetrate, or destroy this product, or expose it to liquids. Keep the product away from high-temperature environments (such as direct sunlight) and heating sources (such as heaters and ovens).

3. Children must use this product under adult supervision.

4. DO NOT let children use or play with it by themselves so as to avoid accidents.

Reduction of hazardous substances

This device and any electrical accessories are compliant with local applicable rules on the restriction of the use of certain hazardous substances in electrical and electronic equipment. For declarations of conformity about REACH, please visit our website <https://service.oneplus.com/global/search/reach-regulation>.

Symbols Used

Class II Equipment

To identify equipment meeting the safety requirements specified for Class II equipment according to IEC 60417-5172.

For Indoor Use Only

To identify electrical equipment designed primarily for indoor use.

Alternating Current

To indicate on the rating plate that the equipment is suitable for alternating current only; to identify relevant terminals.

Direct Current

To indicate on the rating plate that the equipment is suitable for direct current only; to identify relevant terminals.

Waste Electrical and Electronic Equipment (WEEE)

This symbol (with or without a solid bar) means that according to local laws and regulations, your product and/or its battery shall be disposed of separately from household waste. When this product reaches the end of its life, you can give it to a competent recycling organization for handling. Proper recycling of your product will protect human health and the environment. If you are not sure what to do with e-waste, please contact your local authorities, retailer, or household waste disposal service.

EU Declaration of Conformity (DoC)

Huizhou Golden Lake Industrial Co., Ltd. declares that the Power Supply Unit(Model is OSAB7CF3AY) is in compliance with Directive 2014/35/EU and Directive 2014/30/EU and Directive 2011/65/EU.The full text of the EU declaration of conformity is available at the following internet address: <https://www.oneplus.com/support/manuals>.

UK Declaration of Conformity (DoC)

Huizhou Golden Lake Industrial Co., Ltd. declares that the Power Supply Unit(Model is OSAB7CF3AY) is in compliance with the essential requirements and other relevant provisions of Electromagnetic Compality Regulations 2016, Electrical Equipment(Safety) Regulations 2016 and RoHS regulations 2012 (S.I. 2012/3032).The full text of the UK declaration of conformity is available at the following internet address: [https://www](https://www.oneplus.com/support/manuals).

Version1.0

Never
Settle

Manufacturer: Huizhou Golden Lake Industrial Co., Ltd.
Dongjiang Industrial Estate, Shuikou Street, HuiCheng District,
Huizhou City, 516005 Guangdong, P.R. China

ErP Product Information

Huizhou Golden Lake Industrial Co., Ltd. hereby declares that its products conform to the Energy-related Products Directive (ErP) 2009/125/EC. For detailed ErP information and the user manuals required by the Commission Regulation, please visit: <https://service.oneplus.com/global/user-manual>.

Model	OSAB7CF3AY			
Manufacturer	Huizhou Golden Lake Industrial Co., Ltd.			
Manufacturer address	Dongjiang Industrial Estate, Shuikou Street, HuiCheng District, Huizhou City, 516005 Guangdong, P.R. China			
Input voltage	100-130V AC		200-240 V AC	
Input AC frequency	50/60 Hz			
	USB-A+ Type-C	USB-A+ Type-C	USB-A+ Type-C	USB-A+ Type-C
Output voltage	5.0V DC+ 5.0V DC	5.0VDC+ 20.0V DC	5.0V DC+ 5.0V DC	5.0VDC+ 20.0V DC
Output current	2.4A+2.0A	2.4A+1.5A	3.0A+2.0A	3.0A+1.5A
Output power	12.0W+10.0W	12.0W+30.0W	15.0W+10.0W	15.0W+30.0W
Average active efficiency	89.16%	87.80%	87.36%	87.17%
Efficiency at low load (10%)	85.30%	76.92%	77.76%	72.26%
No-load power consumption	0.052W	0.052W	0.074W	0.073W

Limited Warranty

Dear user, thank you for using this product. In case of any damage that is not caused by human factors, we will provide comprehensive warranty services according to local laws and regulations.

To protect your legal interests, please read the following notes carefully:

• A valid Proof of Purchase shall be issued by the seller at the time of purchase.

• Please keep your Warranty Card and Proof of Purchase for future reference.

• In case of any damage of the product that is not due to human factors, consumers are entitled to enjoy customer service free of charge by providing Warranty Card and Proof of Purchase within the warranty period.

The warranty is not applicable in the following cases:

1. The valid warranty period expires.

2. The product is damaged because it is accidentally dropped or immersed in water when in use.

3. Damages are caused by human factors such as unauthorized disassembly, modification, etc.

4. Damages are caused by force majeure (e.g. fires, earthquakes, and lightning).

5. Damages are caused by improper usage that does not conform to the user guide or operation manual.

6. Damages are caused by usage in environments not conforming to product specifications.

7. Information on Warranty Card or Proof of Purchase is inconsistent with the product serial number or has been altered.

8. The SN code of the product is missing, damaged, or blurred beyond recognition.

For more details about our warranty policy, please visit <https://oneplus.com/support>.

OnePlus SUPERVOOC 80W Dual Ports GaN Power Adapter Kit

Dear user, thank you for using this product. To better serve your needs, please read and fill out the warranty card.

User Information:

Name: _____

Phone NO: _____

Email: _____

Address: _____

Product Information

S/N: _____

Model: _____

Dealer Information

Date of Purchase: _____

Dealer's Name: _____

Dealer's Address: _____

OnePlus SUPERVOOC 80W Dual Ports GaN Power Adapter Kit

Dear user, thank you for using this product. To better serve your needs, please read and fill out the warranty card.

User Information:

Name: _____

Phone NO: _____

Email: _____

Address: _____

Product Information

S/N: _____

Model: _____

Dealer Information

Date of Purchase: _____

Dealer's Name: _____

Dealer's Address: _____