



Z-Wave Protocol Implementation Conformance Statement

Wall Plug US

General Information

Product Identifier:	FGWPB-111
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 4.01:04.01
Z-Wave Certification #:	ZC10-18026025

Product Features

Supported Notification Types	Power Management System
Switch Load Capacity Current	15A for resistive and inductive loads, 8A for incandescent loads.
Electric Load Type	Incandescent Inductive (e.g. Motor)
Switch Load Capacity Volt-Ampere	360
Supported Meter Type	Electric Energy
Sensors	Power
Firmware Updatable	Updatable by Consumer by RF
Color	White
Loads Controlled	3

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Wall Plug US

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x2000
Z-Wave Product Type:	0x1701
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“On/Off (Button)” devices in this group will be switched on or off when relay status is changed using the button (uses Basic command class).
3 / 5	“On/Off (Plug power)” devices in this group will be switched on or off depending on the current load of plugged device (uses Basic command class).

Supported Command Classes (21):

Application Status	Association Group Information V2
Association V2	Basic
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Multi-Channel Association V3	Notification V8
Powerlevel	Protection V2
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic
