



## Z-Wave Protocol Implementation Conformance Statement

### Wall Plug UK

#### General Information

Product Identifier:	FGWPG-111
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 4.02:04.02
Z-Wave Certification #:	ZC10-19086702

#### Product Features

Loads Controlled	3
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Power Management System
Electric Load Type	Incandescent Inductive (e.g. Motor)
Supported Meter Type	Electric Energy
Switch Load Capacity Current	13A for resistive loads, 8A for incandescent loads and 13A for inductive loads
Switch Load Capacity Volt-Ampere	700
Sensors	Power
Color	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

Wall Plug UK

## Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x1801
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

## Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“On/Off (Button)” devices in this group will be switched on or off when relay status is changed using the button (uses Basic command class).
3 / 5	“On/Off (Plug power)” devices in this group will be switched on or off depending on the current load of plugged device (uses Basic command class).

### Supported Command Classes (21):

Application Status	Association Group Information V2
Association V2	Basic
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Multi-Channel Association V3	Notification V8
Powerlevel	Protection V2
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic
-------