

Factory Reset

- Information About Factory Reset, on page 1
- Prerequisites for Performing Factory Reset, on page 1
- Performing Factory Reset, on page 1
- Performing Secure Erase, on page 2

Information About Factory Reset

Factory reset removes all the customer-specific data that has been added to a device since the time of its shipping. The erased data includes configurations, log files, boot variables, core files, and credentials such as Federal Information Processing Standard-related (FIPS-related) keys.

The device returns to its default license configuration after a factory reset.



Note

The factory reset is performed through an IOS CLI. A copy of the running image is backed up and restored after the reset.

Prerequisites for Performing Factory Reset

- Ensure that all the software images, configurations, and personal data are backed up.
- Ensure that there is uninterrupted power supply when the factory reset is in progress.
- Ensure that you take a backup of the current image.

Performing Factory Reset

SUMMARY STEPS

- 1. enable
- 2. factory-reset all secure 3-pass

DETAILED STEPS

| | Command or Action | Purpose |
|--------|---|---|
| Step 1 | enable | Enables privileged EXEC mode. |
| | Example: | Enter your password, if prompted. |
| | Device> enable | |
| Step 2 | factory-reset all secure 3-pass | Removes sensitive data from all the partitions that are currently being cleaned up by the factory-reset all command. |
| | Example: Device# factory-reset all secure 3-pass | |
| | | From Cisco IOS-XE 17.10 onwards, the following are the three passes to erase data in disk partitions: |
| | | • Write 0s |
| | | • Write 1s |
| | | Write a random byte |
| | | Note The factory reset takes 3 to 6 hours to be completed. |

Performing Secure Erase

SUMMARY STEPS

- 1. enable
- 2. factory-reset all secure

DETAILED STEPS

| | Command or Action | Purpose |
|--------|----------------------------------|--|
| Step 1 | enable | Enables privileged EXEC mode. |
| | Example: | Enter your password, if prompted. |
| | Device> enable | |
| Step 2 | factory-reset all secure | Erases all user data and metadata from bootflash. The erase |
| | Example: | is compliant with the National Institute of Standards and Technology (NIST) standards. |
| | Device# factory-reset all secure | Note The erase takes around 5 to 10 minutes. You need to boot a new image from TFTP post the secure erase as the image gets deleted. |