



Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Switch

General Information

Product Identifier: 39348 /54890 /54891/ ZW4008
Brand Name: UltraPro
Product Version: HW: 255 FW: 5.53
Z-Wave Certification #: ZC10-20096977

Product Features

Switch Type	Decorator Paddle Push with Indicator
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	1800
Neutral Wire Required	Yes
Switch Load Capacity Current	15
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3237
Z-Wave Product Type:	0x4952
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.04
Z-Wave Library Type:	Enhanced 232 Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Association Group 1 supports Lifeline, Binary Switch Report
2 / 5	Association Group 2 supports Basic Set and is controlled by pressing the ON or OFF button with the local load
3 / 5	Association Group 3 supports Basic Set and is controlled by double pressing the ON or OFF button

Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2
