

Z-Wave Protocol Implementation Conformance Statement

Z-Weather

General Information

Product Identifier: POPE005206
Brand Name: Popp
Product Version: HW: 1 FW: 1.00
Z-Wave Certification #: ZC10-16125341

Product Features

Outdoor Use Yes
Color Black

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x0400
Z-Wave Product Type: 0x0100
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.51.06
Z-Wave Library Type: Enhanced Slave
Z-Wave Device Type / Role Type: Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Too windy. If the threshold value for wind (Default value: 6m/s) is exceeded, the basic set is sent to all group

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Weather

3 / 5	It is getting bright. Sends BASIC SET command in the morning when brightness reached trigger level (Default value: 37%)
4 / 5	It is getting dark. Sends BASIC SET command in the evening when brightness reached trigger level (Default value: 37%)

Supported Command Classes (17):

Association Command Configuration	Association Group Info
Association V2	Basic
Battery	Configuration V2
Device Reset Locally	Language
Manufacturer Specific V2	Meter V3
Multi Channel Association V2	Multi-Command
Powerlevel	Sensor Multilevel V6
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Multi-Command
-------	---------------