



- \* press **Xbox** button to turn on the controller.
- \* hold **Xbox** button for 6 seconds to turn off the controller.



- \* 开机:按下 **Xbox** 键。
- \* 关机:按住 **Xbox** 键 6 秒。

Android



- \* system required: Android 9 or above

Bluetooth Connection

1. press **Xbox** button to turn on the controller, status LED starts to blink.
2. hold **pair** button for 3 seconds to enter its pairing mode, status LED starts to blink rapidly. (This is required for the very first time only)
3. go to your **Android device's Bluetooth setting**, pair with [**8BitDo SN30 Pro for Android**], LED stays solid when connection is successful.

Wired Connection

- \* OTG support is required on your Android device, please contact your device manufacturer for more details. Connect the controller to the USB port of your Android device, wait till the controller is successfully recognized by your Android device to play.

Android



- \* 要求 Android 系统版本为 9.0 或更高版本。

蓝牙连接

1. 按下 **Xbox** 键 开机, **状态指示灯** 闪烁。
2. 按住 **配对键** 3 秒至 **状态指示灯** 快速闪烁, 进入配对状态。(仅首次连接需要配对)
3. 打开 Android 设备蓝牙, 搜索 8BitDo SN30 Pro for Android 手柄连接, 连接完成后 **状态指示灯** 常亮。

有线连接

- \* 使用有线连接需要设备支持 OTG 功能, 请咨询设备制造商。使用 USB 线将手柄连接到 Android 设备的 USB 端口, 等待系统识别完成后即可使用。

Apple®

- \* required system: iOS 16.3, iPadOS® 16.3, tvOS® 16.3, macOS® 13.2 or above. Apple®, iPadOS®, macOS®, and tvOS® are trademarks of Apple Inc., registered in the U.S. and other countries.

Bluetooth Connection

1. press **Xbox** button to turn on the controller, status LED starts to blink.
2. hold **pair** button for 3 seconds to enter its pairing mode, status LED starts to blink rapidly. (This is required for the very first time only)
3. go to your **Apple device's Bluetooth setting**, pair with [**8BitDo SN30 Pro for Android**]. LED stays solid when connection is successful.

Wired Connection

- \* USB wired connection is only available for macOS or iPadOS devices with USB-C ports. Connect the controller to the USB port of your Apple device, wait till the controller is successfully recognized by your Apple device to play.

Apple

- \* 要求 iOS 16.3, iPadOS 16.3, tvOS 16.3, macOS 13.2 或更高版本。

蓝牙连接

1. 按下 **Xbox** 键 开机, **状态指示灯** 闪烁。
2. 按住 **配对键** 3 秒至 **状态指示灯** 快速闪烁, 进入配对状态。(仅首次连接需要配对)
3. 打开 Apple 设备蓝牙, 搜索 8BitDo SN30 Pro for Android 手柄连接, 连接完成后 **状态指示灯** 常亮。

有线连接

- \* 仅 macOS 和配备 USB-C 端口的 iPadOS 设备支持有线连接。使用 USB 线将手柄连接到 Apple 设备的 USB 端口, 等待系统识别完成后即可使用。

Button Swap



- \* LED blinks continuously when the swapped button is pressed.
  - \* the swapped buttons will not be saved after turn off the controller.
  - \* D-Pad, view, menu, LT, RT and Xbox buttons are not supported.
- Hold either two buttons you would like to swap, then press the **star** button to activate/deactivate the button swap.

快速交换按键



- \* 已交换过功能的按键, 按下时 **配置指示灯** 会持续闪烁。
  - \* 交换功能不会保存, 关机后恢复默认。
  - \* **方向键、视图键、菜单键、LT、RT、Xbox** 键不支持交换。
- 按住任意两个按键, 并按下 **星号键** 即可快速交换 / 取消交换按键功能。

Battery



Built-in 480mAh Li-on battery with 16 hours of play time, rechargeable with 1 to 2 hours charging time.

status -		LED indicator -
low battery mode	→	red LED blinks
battery charging	→	green LED blinks
battery charged	→	green LED stays solid

- \* the controller will turn off in 2 minutes with no connection or 15 minutes of inactivity when connected with Bluetooth.
- \* controller stays on with USB connection.

电源



配备 480mAh 可充电式锂电池, 可持续使用约 16小时, 充电时间约 1-2 小时。

电源状态		电源指示灯状态
电量不足	→	红灯闪烁
正在充电	→	绿灯闪烁
充电完成	→	绿灯常亮

- \* 开机后 2 分钟内未连接, 或连接后 15 分钟内无操作会自动关机。
- \* 使用有线连接时不会自动关机。

Ultimate Software

- \* it gives you elite control over every piece of your controller: customize button mapping, adjust stick & trigger sensitivity. Please visit support.8bitdo.com for the application.
- \* press **profile button** to activate/deactivate the custom profile. The profile indicator will not light up when using the default setting.

自定义配置

- \* 配置后可按 **配置键** 启用配置, 默认无配置。
- \* 请访问 app.8bitdo.cn 获取精英软件, 可对手柄按键映射、摇杆灵敏度、扳机键灵敏度等功能进行自定义配置

support



please visit support.8bitdo.com for further information & additional support.

技术支持



- \* 请访问 support.8bitdo.cn 了解详细信息。

