# Enbrighten Zigbee Outdoor Plug-in Smart Switch

# enbrighten®





### **Specifications**

**Power:** 120VAC, 60Hz **Signal Frequency:** 2.4GHz Maximum load for the Zigbee-controlled outlet: 600W (5A) incandescent/1/2 HP motor or 1800W (15A) resistive Zigbee controlled outlet is fused @ 5A. This fuse is not user serviceable

Range: Up to 150ft from controller or closest Zigee device

**Operating Temperature:** 14-104° F (-10-40° C) **Warranty:** 5-year limited product warranty

**Degree of Protection:** Type 3R For outdoor or indoor use

# **Design Features**

- · Remote ON/OFF control via the Zigbee controller
- · Manual ON/OFF control with the manual program button
- · Works with Google and Alexa (requires compatible hub\*)
- · Can be included in multiple groups and scenes
- One Zigbee remote controlled AC outlet
- Weather-and-impact resistant housing suitable for use outdoors in damp or wet conditions
- · Includes mounting hardware
- Over-the-air updates once joined to your Zigbee network, the smart switch can automatically receive updates through your Zigbee gateway
- · Zigbee 3.0 certified for simple pairing and integrated home automation
- · Black color
- · Visit ezzigbee.com/hubs for hub compatibility
- Trilingual Instruction manual (English, French, Spanish)

#### **Zigbee Features**

- Effortless device pairing to Zigbee certified gateways
- · Backward compatible with all generations of Zigbee devices
- · Supports wireless upgrades to future-proof your home
- \* Requires Zigbee hub or controller functions may vary depending on brand.



# **Device Configuration**

#### Adding your devices to a Zigbee network

Once the hub is ready to add the smart switch, pairing begins automatically when power is supplied. The switch appears in the controller's menu when paired.

#### To remove and reset the device

Choose to remove the lighting device as instructed by your hub. The controller indicates the smart switch was removed.

#### To return to factory defaults

If plugged in, unplug the switch. Press the program button while plugging in the switch –must release button within four seconds of plugging in the switch

## **Certifications & Compliances**







Compliances, specifications and availability are subject to change without notice

Distributed by Jasco Products Company LLC 10 E. Memorial Rd., Oklahoma City, OK

©Jasco 2020

V1 3/22/20

# **Related Products – Enbrighten Zigbee Smart Controls**



**43094**Plug-In
Dual-Outlet
Smart Switch



43096 Plug-In Dual-Outlet Smart Dimmer



43076 In-Wall Smart Switch, Paddle



In-Wall Smart Switch, Paddle 120/277



43084 In-Wall Smart Switch, Toggle



In-Wall
Smart Dimmer,
Paddle



In-Wall Smart Dimmer, Toggle



In-Wall Smart Outlet