

1.Does the Zigbee temperature and humidity detector include battery?

not included CR2450 battery

2.Can the product be used alone? Can link to the WIFI separately?

Zigbee detectors cannot be used alone and cannot be connected to WIFI separately. They must be used together with Zigbee gateway

3.How often are temperature and humidity updated?

A change in temperature of 0.3 degrees Celsius and a change in humidity of 6 percent will upload data. Under constant temperature, data will be uploaded every 5 minutes

Temperature & Humidity Sensor


Product user manual

*Please read the instruction manual carefully before using the product

-1-

Product information

The temperature and humidity sensor can detect the temperature and humidity in the environment in real time, and combines with other devices to implement intelligent application scenarios.



-2-

Product specification

Product name:	Temperature and Humidity Sensor
Battery type:	CR2450
Temperature detection range:	-10°C ~ 50°C
Temperature detection accuracy:	±0.6°C
Humidity detection range:	0%~95%RH (no condensation)
Humidity detection accuracy:	±6%
Wireless protocol:	Zigbee 3.0
Product size:	40*13mm

Packing list

• Sensor X 1 • User manual X 1 • Reset pin X 1

-3-

Preparation for use

● Smart Life APP

Before device binding operation, please install "Smart Life" APP on your phone and register account via email address. The App can be downloaded by scanning QR code or from Google Play or App store.



"Smart Life" App

-4-

● Ensure that your phone is connected with local WIFI 2.4GHz, Network and Bluetooth is enabled and have binded the Zigbee gateway to the APP.




● Make sure that the product is within the effective coverage of the gateway Zigbee network to ensure the effective connection between the product and the gateway.

-5-

Network Access Setting

- Install the battery to the device successfully, then enter into the Zigbee Gateway page, click "Add subdevice".
- Use the reset pin to insert the reset hole (as the following picture) for more than 5s until the indicator flashes.
- Then it will automatically search for Zigbee devices and add.



After adding successfully, you can find the device in the "My Home" list. If Zigbee gateway "search device" time more than 2 mins, will exit from matching. We can exit the gateway and enter into again to operate.

-6-