

dynamic BIOSENSORS

# **CHIP CLEANING KIT**

Detergent- and enzyme-based solutions for manual cleaning of chips

Dynamic Biosensors GmbH & Inc. CCK-1-1 v1.1





## **Product Description**

Order Number: CCK-1-1

Table 1. Contents and Storage Information

| Material                                | Сар         | Amount | Storage |
|---|-------------|--------|---------|
| Cleaning Solution 1 (detergent-based)   | Transparent | 1 mL   | RT      |
| Lyophilized Enzyme Powder               | Red         | 5 mg   | 2-8°C   |
| Tris-HCl Buffer (reconstitution buffer) | Transparent | 1 mL   | 2-8°C   |

The **heliX**<sup>cyto</sup> Chip Cleaning Kit contains Cleaning Solution 1 and Cleaning solution 2 for manual cleaning of the **heliX**<sup>cyto</sup> chip outside of the **heliX**<sup>cyto</sup> device.

For research use only.

This product has a limited shelf life, please see expiry date on label.



#### Reconstitution

The Cleaning solution 2 has to be **reconstituted prior first use** by dissolving the 5 mg lyophilized enzyme powder in 1 mL of Tris-HCl reconstitution buffer.

Reconstituted Cleaning solution 2 should be **aliquoted** (10 – 100 μL volumes) and stored at -20 °C.

Cleaning solution 1 is ready-to-use and does not require any preparation.



### **Application Note**

Manually cleaning **heliX**<sup>cyto</sup> chips extends their lifetime. This can be performed by injecting cleaning solutions into the microfluidic channel of the chip with a pipette. To reduce the introduction of dust particles into **heliX**<sup>cyto</sup> chips during manual handling and optimally wash out cell remnants it is recommended to:

- a. wear gloves when handling chips
- b. only use freshly filtered buffers
- c. always inject solutions into the entry port on the left side of the flipped chip



### heliX<sup>cyto</sup> chip cleaning protocol

- a. Fill the microfluidic channel with 10 µl fresh Cleaning solution 2
- b. **Seal** chip in- and outlet with clear sticky tape (e.g. Sellotape™, do not use tape that leaves glue remnants)
- c. Incubate at least 20 min at RT (or longer, e.g. overnight)
- d. Wash microfluidic channel 3 x with 10 µl Cleaning solution 1
- e. Wash microfluidic channel 3x with 10 µl water (Milli-Q or similar)
- f. Empty chip by pipetting 10 µl air.



#### **Contact**

**Dynamic Biosensors GmbH**Perchtinger Str. 8/10
81379 Munich
Germany

**Dynamic Biosensors, Inc.** 300 Trade Center, Suite 1400 Woburn, MA 01801 USA

Order Information order@dynamic-biosensors.com
Technical Support support@dynamic-biosensors.com

www.dynamic-biosensors.com

Instruments and chips are engineered and manufactured in Germany. ©2024 Dynamic Biosensors GmbH | Dynamic Biosensors, Inc. All rights reserved.