



## Z-Wave Protocol Implementation Conformance Statement

### Slim Smart Door/Window Sensor

#### General Information

**Product Identifier:** 52249/ZW6308  
**Brand Name:** Jasco  
**Product Version:** HW: 1 FW: 7.07  
**Z-Wave Certification #:** ZC12-20080113

#### Product Features

**Firmware Updatable** Updatable by Consumer by RF  
**Battery Type** CR2450  
**Battery Quantity** 1

#### Z-Wave Product Information

**Supports Z-Wave Beaming Technology?** No  
**Supports Z-Wave Network Security?** Yes  
**Supports Z-Wave AES-128 Security S0?** No  
**Supports Security S2?** Yes: S2 Authenticated, S2 Unauthenticated  
**SmartStart Compatible?** Yes

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x3336  
**Z-Wave Product Type:** 0x4953  
**Z-Wave Hardware Platform:** ZGM130  
**Z-Wave Development Kit Version:** 7.13.5  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

**Group # / Max Nodes**      **Description**

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Slim Smart Door/Window Sensor

**Supported Command Classes (18):**

Application Status	Association Group Information V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2