

PTCam

.....

Laxihub
A Safer and Smarter Life for Everyone

QUICK GUIDE

EN Smart Pan Tilt Wi-Fi Camera



Compatible with Amazon Alexa & Google Assistant

Quick start guide

1. Packing list
2. Product description
3. Installation
4. Product configuration
5. Legal notice

1. Packing list



Camera X1



Power adaptor X1



Type-C cable X1





Quick guide X1



Warning sticker 1X

2. Product description



1. Microphone
2. Lens
3. LED indicator
4. SD card slot
5. Reset
6. Type-C port
7. Speaker


Notice

To reset the device, press and hold the reset button for 5s.
The camera beeps when the operation is complete.

Flashing red light (slow)	Wait for network config
Flashing red light (fast)	Connecting the network
Fixed red light	Network is malfunctional
Fixed blue light	Camera is working correctly

3. Installation

- 1 Put the camera on a flat surface.



4. Product configuration

Step 1 Turn on your camera.

Step 2 Connect your smartphone to the Wi-Fi network.

Step 3 Download Arenti app from the App Store or Google Play depending on your device.

Step 4 Launch the App and sign up for the first use.

Step 5 Follow the on-screen instructions to add your camera.

For more information, scan the QR code.



Notice

If you have multiple cameras, please follow step 5 again to add devices one by one.

To change Wi-Fi network, please restore the camera to factory settings and follow step 5 to add the camera.

Specifications

Sensor type	1/3" CMOS
Min. brightness	Color 0.1Lux@F2.0
	Black and white 0.01Lux@F2.0
Resolution	2 Mega pixels
Lens	3.6 mm F2.0
Shutter	1/15-1/10,000 per second
Infrared	High power LED with ICR
Infrared distance	10 meters
Pan/Tilt	0°~355°/-43°~77°
Video compression	H.264
Bit rate	32Kbps - 2Mbps
Max resolution	1920 x 1080
Framerate	1-25 per second
Picture settings	Support HD/SD; support flip
Storage	SD card (Max 256GB)
Audio	Two-way audio
Protocols	HTTP, DHCP, DNS, RTSP
WiFi standard	IEEE802.11b/g/n/ac
Frequency	2.4 GHz; 5 GHz
Bandwidth	20/40MHz
WiFi encryption	WPA-PSK/WPA2-PSK
Security	AES128
Working temperature	-20°C~50°C
Power	DC5V,1A
Consumption	4.5W MAX
Size(mm)	59 x 63 x 110

Specifications

Model	TPA-67F050100VU01
Input voltage	100-240V AC
Input frequency	50-60Hz
Output voltage	5V DC
Output current	1A
Output power	5W
Efficiency	73,62%
No-load Consumption	<0.1W

5. Legal notice

Support

www.laxihub.com

Symbols

=== Direct current (DC)



Don't throw batteries or out of order products with the household waste (garbage). The dangerous substances that they are likely to include may harm health or the environment. Make your retailer take back these products or use the selective collect of garbage proposed by your city.



Hereby, Laxihub, declares that the radio equipment type 'PTCam' is in compliance with the Directive 2014/53/EU

The full test of the EU declaration of conformity is available at the following Internet address:
www.laxihub.com

