100.0 mm

anko

Gaming Mouse Instruction Manual KC42902058

*Please read all the information carefully before you use the product and keep the manual for future reference.

100.0 mm

Safety Instructions:

Please read the instruction manual before using this device and follow all the safety instructions to avoid damage caused by improper use.

- Keep the instruction manual for future reference. Should this device be given to a third party, then this instruction manual must also be handed over.
- Use this device solely for its intended purpose.
- Only use this appliance indoors
- Keep the appliance away from all hot surfaces and naked flames.
- Always put the appliance on a level, stable, clean, dry surface.
- Protect the appliance from extreme heat and cold, dust, direct sunlight, humidity and drops or jets of water.
- Do not immerse the appliance in water or in other liquids.
- Do not open the housing under any circumstances. Do not introduce any objects into the interior of the housing.
- Should the device malfunction due to electrostatic discharge or a short power surge, disconnect it from your computer and then reconnect it again.

100.0 mm

Product overview:

Connecting the Mouse：

1. Plug the USB cable into a free USB port on the computer.
2. The Mouse will connect automatically and can be used immediately.

100.0 mm

Feature:

- DPI value: 1000-2400-3600-5000-7000-10000DPI (which can be set)
- Default lamplight DPI first level/red, second level/green, three level/blue, four level/yellow, five level/Cyan, six level/purple.
- 6 kinds of RGB light effect. (YO-YO mode / Neon mode / Breathing mode / Wave mode / Steady mode / LED OFF) The RGB light mode can be adjusted by "Left button + Right button".
- For more customized functions, please visit http://www.in-trainduty.com/downloads.html to download the KM42902058 driver.

100.0 mm

Supports:

Windows 2000/XP/Vista/Windows 7/8/10

Main interface of Driver and functions description:

100.0 mm



Key Function:

1. Left Key: left key function
2. Right Key: right key function
3. Middle Key: middle key function
4. Forward Key: enter to next page
5. Back Key: back to previous page
6. DPI+: switch to higher DPI value, without loop switch
7. DPI-: switch to lower DPI value, without loop switch
8. Sniper Key: locking DPI
9. Double Fire：Equivalent to click the left key for 2 times

100.0 mm

10. Fire Function: Speed rate can be adjust in software for the mouse key.
11. Group Function: Customize Ctrl、Shift、Alt、Win and any of the keyboard keys to combine key functions (support 3 reassemblies farthest, such as Ctrl + A + B)
12. Media Function: Include Player, Next, Previous, Stop, Mute, Play/Pause, Volumen+, Volume-.
13. Marco Function: See more details in Macro Editor
14. DPI Function: DPI+, DPI-, DPI LOOP, Sniper Key
15. Windows Function: Include My PC, Index, Search, Max, Min, Desktop, Run
16. Shortcut Function: Include New, Cut, Copy, Paste, Save, Print, Find, Redo, Undo, Select All.



100.0 mm

17. The report rate of mouse: with 125Hz/250Hz/500Hz/1000Hz to choose.
18. Mouse Speed of mouse: To adjust the movement speed of mouse.
19. Double Click Speed of mouse: To adjust the double-click speed of mouse.
20. Scroll Speed of mouse: To adjust the scroll wheel speed of mouse.
21. Export the current configuration: store the content that have been set to your computer.

100.0 mm

22. Import the configuration file: Load the existing documents from the computer.
23. Reset: Set the mouse to the factory default.
24. Save: Write the settings to mouse.

Macro Editor：

Macro management can record any keys of keyboard and the keys reaction time, number of keys cycles.

a. Click 【New】 to create a new file, such as a, b, c…
b. Select whether to increase the delay and the times of cycles
c. Click 【Start Record】 and start recording any keys of keyboard. The keys you recorded will display in the macro edit box.
d. After the recording, click 【Stop Record】
e. To revise the recording content, please make the following changes in the macro options:
Choose to insert the event: Right-click in the selected location to insert relevant content.
Delete: Delete the selected content
Modify: Modify the delay value and input key again

100.0 mm



f. After recording is completed, just exit the macro recording interface, no need to click the confirmation keys
g. Execute a macro, such as the mouse key 【Q】 key set to "macro functions", after recording is complete, press the mouse 【Q】 key to play the recorded content

100.0 mm

DPI settings:

100.0 mm

1. Six groups DPI: gear 1 / gear 2 / stalls 3 / stalls 4 / stalls 5 / stalls 6, check the selections
2. DPI setting： set the 6 groups DPI value, adjust the range of 200 ~ 10000DPI

Lighting settings:

10 kinds of light effect: Steady mode---Breathing mode---Neon mode---LED OFF---Twinkling mode---Wave mode---Gliding mode--- Finger Moving mode--- Vertical Flipping mode--- YO-YO mode--- Spotlight mode

100.0 mm

Uninstall:

Open the control panel and open the "Add or Remove Programs" window, find "KM42902058 Gaming Mouse" and click "delete" to complete the uninstall program.

100.0 mm