

marantz®



AV8805A

13.2Ch 8K UHD Pre-Amplifier with HEOS® Built-in and Voice Control

The versatile Marantz AV8805A pre-amplifier redefines the audiophile home cinema and music listening experience with 13.2 channel processing capability, 8K pass-through, and support for the latest in surround sound audio formats, such as Dolby Atmos®, DTS:X®, DTS:X® Pro, IMAX Enhanced®, and Auro-3D®. Marantz' proprietary technologies enhance any audio playback for the most demanding of listeners. Stream music throughout your home with HEOS® Built-in for a whole home audio experience from your favorite streaming services. With the new Marantz AV8805A, you get incredible fidelity and unparalleled audio precision.

- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices or with 8K upscaling from Full HD or 4K sources.
- Ideal for the most advanced home theater enthusiast: With 13.2 channel processing and 15.2 channel XLR and RCA outputs, and flexible pre-amplifier stages, enjoy your movies with a system you deserve.
- Featuring the most advanced 3D audio formats: Dolby Atmos®, Dolby Atmos Height Virtualization Technology, DTS:X®, DTS Virtual:X™, DTS:X® Pro, IMAX® Enhanced and Auro-3D® processing are all supported for total flexibility and compatibility.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV via eARC HDMI to allow uncompressed and object-based audio formats like Dolby Atmos® and DTS:X® directly from your smart TV app to your system.
- DTS:X® Pro support: DTS:X® Pro can process up to 13 channels, wowing listeners with the most cutting-edge DTS technology.
- Bringing you leading edge video compatibility: The latest High Dynamic Range format support including HDR10, HDR10+, HLG, Dolby Vision, 4:4:4 color resolution and BT.2020, as well as Dynamic HDR, to provide miraculous picture quality for brightness, clarity, and contrast.
- Experience the next chapter in movie entertainment: With 8K/60Hz pass-through or upscaling, Dynamic HDR and Quick Media Switching (QMS), enjoy the smoothest, most crystal-clear picture quality available.
- The latest in gaming thrills: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), enjoy your gaming experience with amazing imaging with reduced lag and tearing.
- Stream music from your favorite sources: Play songs from Spotify, Pandora, TIDAL, and more via AirPlay 2, Bluetooth, Wi-Fi, and the HEOS app. (Music streaming services may vary by region)

Modern Musical Luxury

8K UHD
HDR / HDCP 2.3

Dolby Atmos

DTS:X

Auro-3D

IMAX
ENHANCED

Dolby
VISION

HDR10+

HDMI

HEOS
BUILT-IN

works
with alexa

works with
Hey Google

JOSH

works with
Apple AirPlay

WiFi
CERTIFIED

Bluetooth

AUDYSSEY
MULTI-STEP
DYNAMIC VOLUME

AUDYSSEY
LFC

HiRes
AUDIO

roon
tested

Spotify

pandora

amazon
music

TIDAL

TUNE
IN

iHeartRADIO

DEEZER

napster

SOUNDCLOUD

SiriusXM

isf

Download on the
App Store

GET IT ON
Google Play

domotz

OVC

OVC

AV8805A

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro	• / • / •	
DTS Neo:X / DTS Neural:X	- / • (1 ch)	
DTS Virtual:X	•	
IMAX Enhanced	•	
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization / Dolby Atmos Music	• / • / • / •	
Dolby ProLogic IIz / Dolby Surround	- / •	
Auro 3D	•	
Multichannel Stereo	•	
Max Number of Processing (Preamp) Channels	13.2	
Sound Enhancements		
Discrete Power Amplifier	•	
Copper Plated Chassis	•	
Power Transformer: Toroidal / EI	• / -	
Current Feedback Topology	•	
Hyper Dynamic Amplifier Modules (HDAM)	•	
Pure Direct	•	
Gold Plated RCA Terminals	•	
Clock Jitter Reducer	•	
Audyssey	MultEQ XT32	
Audyssey Dynamic EQ / Dynamic Volume	• / •	
Audyssey LFC	•	
Compressed Audio Enhancer: MDAX2	•	
Network		
HEOS Multi-room and Streaming	•	
Bluetooth Re-transmit for Bluetooth headphones	•	
Alexa / Google Voice Assistant / Apple HomePod	• / • / •	
Network Audio Sharing	•	
Lossy Formats: MP3 / WMA / AAC	• / • / •	
Lossless Formats: FLAC / ALAC / WAV	•	
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •	
DSD Audio Streaming	• (2.8/5.6MHz)	
Gapless Playback	• (FLAC, WAV, ALAC, DSD)	
AirPlay Audio Streaming	• (AirPlay 2)	
Internet Radio	•	
Spotify Connect*	•	
Streaming Services	Amazon Music HD / Amazon Music / TIDAL / Deezer / iHeart Radio / Napster / Pandora / Soundcloud / Mood Mix	
SiriusXM	•	
Ethernet Ports	•	
Wi-Fi	•	
Bluetooth	•	
HDMI		
HDMI Inputs: Back / Front	7 / 1	
HDCP2.3 support	•	
HDMI Outputs: Main / Zone	2 / 1	
Video Conversion Analog -> HDMI	•	
Analog to HDMI scaling	up to 8K 60/50	
HDMI to HDMI scaling	up to 8K 60/50	
GUI Overlay on HDMI	•	
8K/60Hz / 4K/120Hz	• / •	
3D / 4K / CEC / ARC	• / • / • / •	
Enhanced ARC	•	
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	• / • / • / • / •	
ALLM (Auto Low Latency Mode) Pass-through for gaming	•	
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	• / • / •	
3D Signal Pass-Through	•	
8K Signal Pass-Through / Scaling / GUI Overlay	• / • / •	
4K Signal Pass-Through / Scaling / GUI Overlay	• / • / •	
HDMI Pass-Through in Standby Mode	•	
Picture Adjust / Noise Reduction	• / •	
CEC	•	
DSD Audio Capability	•	
Audio Return Channel	•	
Auto LipSync	•	

Multiroom / CI		
HEOS Multi-Room Integrated	•	
HEOS Link Compatibility: IR/ IP	• / •	
Multi-Room zones	3	
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog	• (2ch) / • (2ch) / • / •	
Zone Audio Output: Speaker / Preout	- / •	
Zone HDMI Output from HDMI Source	•	
IP Control / RS232 Control / Web Control / App Control	• / • / • / •	
IR Flasher In	•	
Marantz Remote Bus	•	
DC Trigger Output	2	
HDMI Diagnostics	•	
Others		
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32	
FL Display	2 lines + port hole	
Graphic User Interface - GUI	Advanced	
ISF Certification	•	
GUI Languages	3	
Setup Assistant	•	
Smart Select	•	
Firmware Update by Network / USB	• / •	
Variable Cross Over	•	
Optimized Bass Redirection	•	
Bass Sync	•	
ECO Mode	•	
Auto Power Off	•	
Sleep Timer	•	
Video Inputs/Outputs		
Composite In / Out	4+1 / 2	
Component In / Out	3 / 1	
HDMI In / Out	7+1 / 3	
Multi-Room Video Out: Video / HDMI	• / •	
Audio Inputs/Outputs		
Analogue In / Out	6+1 (1x XLR) / -	
Phono (MM) In	•	
Digital in: optical / coaxial	2 / 2	
Multi-Room Out: analog / digital	2 / -	
Multichannel Pre Out	• (15.2 RCA & 15.2 XLR)	
Subwoofer Out	2 (independent)	
7.1 multichannel input	•	
Other Inputs/Outputs		
Speaker A / B	Assignable pre out	
Bi-amp drive	Assignable pre out	
Multi-Room Speaker Terminal	Pre out	
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	• / • / - / • / •	
USB Audio / Made for iPod / Made for iPhone	• / AirPlay 2 / AirPlay 2	
AM/FM Tuner	•	
General+		
Metal Front Panel	•	
System Remote Control	RC039SR	
Pre-programmed / Learnable / LCD Display	• / • / •	
Power Consumption in W	90	
Standby Consumption in W	0.2	
CEC Standby Consumption in W	0.5	
Network Standby Consumption in W	3.5	
Maximum Dimensions		
Antenna: Horizontal: (W x D x H) in inches	17.3 x 18.1 x 7.3	
Antenna: Vertical: (W x D x H) in inches	17.3 x 18.1 x 9.8	
w/o Antenna: (W x D x H) in inches	17.3 x 17.7 x 7.3	
Weight in lbs	30.2	
UPC		
USA	AV8805A/U1B	699927161354
		Black

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/ third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com