

简体中文蓝牙耳机功率放大器

接口介绍

多功能按键: 切换工作模式, 切换UI, 进入/退出菜单

麦克风孔 播放/暂停键 电源推钮

音量加键: 上一曲, 音量加, 切换菜单 音量减键: 下一曲, 音量减, 切换菜单

Type-C充电/解码接口

显示屏

挂绳孔

4.4mm平衡耳机输出口

电池仓

3.5mm耳机输出口

1

简体中文蓝牙耳机功率放大器

3.5mm耳机输出口

挂绳孔

4.4mm平衡耳机输出口

电池仓

2

简体中文蓝牙耳机功率放大器

功能操作

开机: 滑动电源推钮开机关机
调节音量: 短按音量加/减键加/减音量
唤出菜单: 开机非菜单界面长按多功能按键约2s进入菜单退出菜单: 菜单界面长按多功能按键约2s退出菜单
菜单切换选择: 菜单界面短按音量加/减键切换菜单选项, 短按播放/暂停键选择确认
音乐换曲: 长按音量加键或音量减键

BT模式进入配对模式: (非菜单界面)

- 未配对过情况下: 开机后自动进入配对状态, 显示屏显示配对中
- 强制进入配对模式: 连接设备状态下长按播放/暂停键约5秒, 显示屏显示配对中

BT模式与手机连接成功后的按键操作: (非菜单界面)

播放/暂停/通话/挂断/取消呼叫: 短按播放/暂停按钮
拒接来电: 有来电时长按播放/暂停按钮约2s
拨打Siri/语音助手: 非菜单界面下双击播放/暂停按钮
蓝牙回连: 蓝牙配对状态下短按播放/暂停按钮
清除配对: 开机状态下, 同时按住音量加键和音量减键约5s
强制配对: 长按播放/暂停按钮约5s

3

简体中文蓝牙耳机功率放大器

同时连接两部手机: “RETRO NANO”与手机1成功连接后, 长按播放/暂停按钮约5s使“RETRO NANO”再次进入配对状态, 用手机2搜索“RETRO NANO”并连接成功后, 在手机1蓝牙设置界面点击已配对的设备“RETRO NANO”回连即可; 也可以在手机2与“RETRO NANO”连接成功后, 将“RETRO NANO”关机, 再开机, 可同时回连两部手机。

工作模式切换: 双击多功能按键切换工作模式

- PC模式: 双击多功能按键选择PC模式, 此时“RETRO NANO”选择为PC解码模式, USB可以给“RETRO NANO”充电和供电。
- BT模式: 双击多功能按键选择BT模式, 此时“RETRO NANO”选择为蓝牙接收模式, USB可以给“RETRO NANO”充电和供电。
- PHONE模式: 双击多功能按键选择PHONE模式, 此时“RETRO NANO”选择为手机解码模式, USB禁止给“RETRO NANO”充电 (RETRO NANO低电关机后强制充电)。

注: “RETRO NANO”机身上没有电池, 插上USB也能正常使用。

通过USB连接电脑解码

当使用“RETRO NANO”UAC模式时, 电脑端无需安装驱动程序, 连接电脑选择对应的输出设备即可。

4

简体中文蓝牙耳机功率放大器

注意事项

- ★请用配套的3.7V充电电池使用, 请勿安装非充电电池进行充电使用;
- ★请勿将电池正负极短路、反接;
- ★不可将电池与钥匙等金属物品放置在一起或放在小孩能触及的地方;
- ★请勿将设备置于温度过高或过低 (45°C以上0°C以下), 请勿将设备放置在车内等密闭高温环境中;
- ★电池浸水后禁止使用, 若出现鼓胀, 请勿继续使用;
- ★禁止拆解、撞击、挤压、刺破电池、自行焊接加工或将电池投入火中;
- ★避免用“RETRO NANO”以外的充电器给电池充电导致电池过充损坏;
- ★当长期没有使用本产品时, 需要对产品进行充电, 以保证电池的寿命。

包装清单

- RETRO NANO主机
- Type-C 转 Type-C数据线
- 快速入门
- 电池收纳盒
- 售后维修卡
- 挂绳
- 电池

5

简体中文蓝牙耳机功率放大器

了解更多

- 有关RETRO NANO的相关视频说明和常见问题解答 (FAQ), 请扫描RETRO NANO FAQ二维码。
- 了解更多产品信息, 请访问: www.fiiio.com
- RETRO NANO支持FIIIO Control APP控制, 欢迎扫码下载APP体验, 更多详细玩法, 请访问官网产品FAQ: <http://www.fiiio.com>

产品名称: 蓝牙解码耳机功率放大器
产品型号: F3085B
额定输入: 5V=1A
尺寸: 约55.1x37.5x13.7mm
重量: 约28.3g
执行标准: GB4943.1-2022
制造厂: 广州飞傲电子科技有限公司
地址: 广州市白云区龙归街道夏良龙良路21号
由于产品不断改进, 各项规格及设计随时更改, 恕不另行通知

6

环保材料说明

产品中有害物质的名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
PCB	X	O	O	O	O	O
PCBA焊点	X	O	O	O	O	O
元器件	X	O	O	O	O	O
显示屏*	X	O	O	O	O	O
电池*	X	O	O	O	O	O
外观件	O	O	O	O	O	O
配件*	X	O	O	O	O	O

注: 表中标记“X”的部件, 因全球技术发展水平限制而无法实现有害物质的替代。
“*”号部件表示如果在您所购买的产品中无该部件, 请忽略表中该部件信息。
O: 表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572-2011规定的限量要求以下。
X: 表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572-2011规定的限量要求。

根据中国电子行业标准SJ/T 11364-2014和相关的中国政府法规, 本产品及其某些内部或外部组件上可能带有环保使用期限标识, 取决于组件和组件制造商, 产品及其组件上的使用期限标识可能有所不同, 组件上的使用期限标识优先于产品上任何与之相冲突的或不同的环保使用期限标识。

此环保使用期限只适用于产品在规定的条件下工作

7

EnglishBluetooth DAC and Headphone Amplifier

Buttons and ports labeled

Multifunction button: Switch working mode, Switch UI, Enter/Exit menu

Microphone hole Play/Pause button* Power push button

Previous track button: Previous track, Volume up, Switch submenu Next track button: Next track, Volume down, Switch submenu

Type-C charging/decoding port

Display

挂绳孔

4.4mm balanced headphone out

电池仓

3.5mm headphone out

8

EnglishBluetooth DAC and Headphone Amplifier

3.5mm headphone out

挂绳孔

4.4mm balanced headphone out

电池仓

9

EnglishBluetooth DAC and Headphone Amplifier

Operation explained

Power on and off: Slide the power push button to power on and off the device.
Adjust volume: Short press the volume up/down button to turn up/down the volume.
Activate menu: When the device powers on and not on the menu page, hold the multifunction button for about 2s.
Exit menu: On the menu page, hold the multifunction button for about 2s.
Switch/Confirm menu: On the menu page, short press the volume up/down button to switch submenus, and short press the play/pause button to confirm.
Switch songs: Hold the volume up or volume down button.

Bluetooth pairing mode (not on the menu page):

- If the device is never paired: After the device powers on, it will automatically enter the pairing mode with the display showing "Pairing";
- Force the device to enter pairing mode: When the device is in the connecting state, hold the play/pause button for about 5s until the display shows "Pairing".

10

EnglishBluetooth DAC and Headphone Amplifier

Operation instructions after a successful pairing with a mobile phone through Bluetooth (not on the menu page):

Play/Pause, Answer/Hang up/Cancel a phone call: Short press the play/pause button.
Reject a phone call: Hold the play/pause button for about 2s.
Activate Siri/voice assistant: Double press the play/pause button when the device is not on the menu page.
Bluetooth reconnecting: Short press the play/pause button in the Bluetooth pairing state.
Clear pairing: When the device is on, hold the volume up and volume down buttons at the same time for about 5s.
Force a pairing: Hold the play/pause button for about 5s.
How to connect the RETRO NANO to two Bluetooth devices simultaneously:
After a successful pairing with device 1, hold the play/pause button for about 5s to enter the pairing mode again. Search for "RETRO NANO" on device 2 and pair it with the RETRO NANO. Back to device 1, select "RETRO NANO" in the Bluetooth device list and reconnect them. Or, restart the RETRO NANO after a successful pairing with device 2, so the RETRO NANO can connect to two Bluetooth devices simultaneously.

11

EnglishBluetooth DAC and Headphone Amplifier

Switch working modes: Double press the multifunction button

- PC mode: Double press the multifunction button to switch to the PC mode. At this time, the RETRO NANO is in PC mode, which can be powered and charged through USB.
- BT mode: Double press the multifunction button to switch to the BT mode. At this time, the RETRO NANO is in Bluetooth receiving mode, which can be powered and charged through USB.
- PHONE mode: Double press the multifunction button to switch to the PHONE mode. At this time, the RETRO NANO is in mobile phone decoding mode, which will be disabled from USB charging (it will be forced to charge if it is powered off for low battery).

Note: If the "RETRO NANO" is not placed with a battery, it still works when connecting to a USB.

Connect to the computer via USB for decoding

When the RETRO NANO is in UAC mode, no driver is required in the computer. Just select the RETRO NANO as the default audio output device after connecting it to the computer.

12

EnglishBluetooth DAC and Headphone Amplifier

Notes and precautions

- ★ Please use the 3.7V rechargeable battery included in the package with the device instead of other non-rechargeable batteries.
- ★ Please do not short-circuit or reverse the positive and negative terminals of the battery.
- ★ Please do not place the battery with metal objects such as keys or put it in a place where children can reach it.
- ★ Please do not place the device in circumstances of excessive high/low temperatures (above 45 or below 0°C), or in an enclosed high-temperature environment, such as in a car.
- ★ Please do not use the battery if it is soaked in water or severely swollen.
- ★ Please do not disassemble, hit, crush and puncture the battery, do not weld or process the battery on your own, and do not drop it into fire.
- ★ Please avoid charging the battery with chargers other than the one included with the RETRO NANO, which may cause damage to the battery by overcharging.
- ★ If the device is to be left unused for a long time, please recharge it periodically to preserve its battery life.

13


EnglishBluetooth DAC and Headphone Amplifier

List of items included

- RETRO NANO unit
- Battery
- Lanyard
- Warranty card
- Type-C to Type-C data cable
- Battery storage box
- Quick start guide

To learn more

- For related video instructions of the RETRO NANO and FAQ (Frequently Asked Questions), please scan the QR code below.
- To learn more about the product, please visit our website: www.fiiio.com
- The RETRO NANO can be controlled by the FIIIO Control App. Please scan the QR code below to download the app.



14


EnglishBluetooth DAC and Headphone Amplifier

Due to continuous improvement, every specification and design is subject to change at any time without further notice.

Hereby, Guangzhou Fiiio Electronics Technology Co., Ltd declares that this device is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at: www.fiiio.com/doc

Function	Frequency	Maximum output power
Bluetooth	2402-2480MHz	7.1dBm


WEEE Directive & Product Disposal

 At the end of its serviceable life, this product should not be handed as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Internal/Supplied Batteries:

This symbol on the battery indicates that the battery is to be collected separately. This battery is designed for separate collection at an appropriate collection point.

Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries.



15

EnglishBluetooth DAC and Headphone Amplifier

FCC NOTICE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. The equipment should be installed and operated with minimum distance 20 cm between the radiator & your body.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

16