



## Z-Wave Protocol Implementation Conformance Statement

### WallMote

#### General Information

**Product Identifier:** ZW129-A  
**Brand Name:** Aeotec  
**Product Version:** HW: 129 FW: 1.05  
**Z-Wave Certification #:** ZC10-17025439

#### Product Features

**Firmware Updatable** Updatable by Consumer by RF  
**Z-Wave Scene Type** Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? Yes  
Supports Security S2? No  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x0081  
**Z-Wave Product Type:** 0x0102  
**Z-Wave Hardware Platform:** ZM5101  
**Z-Wave Development Kit Version:** 6.61.00  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Wall Controller / Portable Slave

#### Association Group Information

**Group # / Max** **Description**

##### Nodes

1 / 1 Z-Wave Plus Lifeline. When touching the Button 1 to 2, the Central Scene Notification command will be sent to the associated node (1) in Association group 1.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

WallMote

- 3 / 5

When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5

When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5

When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.

## Supported Command Classes (16):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Security S0	Version V2
Wake Up V2	Z-Wave Plus Info V2

## Controlled Command Classes (3):

Basic	Switch Binary V2
Switch Multilevel V4	