



Instruction Manual Smart Switch Module MS-104











- Bitte scannen Sie den QR-Code, um das deutsche Handbuch, das Installationsvideo und die Eunktionsein-
- führung zu erhalten · Escanee el código QR para obtener el manual en español, el video de instalación y la introducción de la
- función Veuillez scanner le code QR pour obtenir le manuel en français, la vidéo d'installation et l'introduction des
- Отсканируйте QR-код, чтобы получить руководство на русском языке, видео по установке и описание
- · Leia o código QR para obter o manual em português, o vídeo de instalação e a introdução das funções



请扫描二维码获取中文说明书。 安装视频及功能介绍

Global international operation Whenever & Wherever You are, All-in-one Mobile App














Inhouse local operation













- Turn off the circuit breaker and use the electrical tester to
- Ensure the circuit breaker is off before wiring.



· Remove the old switch





Remove the switch and pull it away from the wall. Identify Line/Load Wire(Note:The color of your wire may be different from the color shown on the manual.)


INSTALLATION

▲ Warnings:

device.

- 1. Installation must be carried out by a qualified
- electrician in accordance with local regulations. 2. Keep the device out of the reach of children.
- 3. Keep the device away from water, damp or hot environment.
- 4. Install the device away from strong signal sources such as microwave oven that may cause signal interruption resulted in abnormal operation of the
- 5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.
- 6. Do NOT attempt to disassemble, repair or modify the device


TECHNICAL SPECIFICATIONS




Model	MS-104
Voltage	90-250V AC 50/60Hz
Current	10A
Wireless Protocol	Wi-Fi 2.4GHz IEEE 802.11b/g/n
Operation Temp.	-10°C - +40°C
Case Temp	Tc: +80°C (Max.)
Dims (WxDxH)	47 x 52 x 22.5 mm
IP Rating	IP20

WIRING DIAGRAM

1. With one 2 Gang switch



2. With 2 Gang 2 Way switches














3. With Wall Socket



Wiring Instructions and Diagrams

- 1. Turn off the power supply before carrying out any electrical installation work.
- 2. Connect wires according to the wiring diagram.
- 3.Insert the module into the junction box.
- 4.Connect the power supply and follow switch module configuration instructions.

Notes: Put your smartphone close to the switch module when you're configuring, and make sure you have min. 50% Wi-Fi signal.

FAQ

- Q1: What should I do if I can't configure the switch module?
- a. Please check whether device is powered on.
- b. Make sure your mobile and switch module are under the same 2.4 GHz WiFi network.
- c. Whether it's in good internet conditions.
- d. Make sure the password entered in App is correct.
- e. Make sure the wiring is correct.
- Q2: What device can be connected to this WiFi switch module?

Most of your household electrical appliances can be, such as lamps, laundry machine, coffe maker, etc.

Q3: What happens if the WiFi goes off?

You can still control the device connected the switch module with your traditional switch and once WiFi is active again the device connected to module will connect automatically to your WiFi network

Q4: What should I do if I change the WiFi network or change the password?

You have to re-connect our WiFi switch module to the new WiFi network according to the App User Manual.

Add Devices

Download Smart Life App






Please scan the QR code or download Smart Life on App store.

Registration or Log in

- · Download "Smart Life" Application
- . Enter the Register/Login interface:tap "Register" to create an account by entering your phone number to get verification code. and "Set password". Choose "Log in" if you already have a Smart Life account.

Configure the APP to the switch

· Preparation: Ensure the switch has been connected with electricity:ensure your phone has been connected to Wi-Fi and is able to connect to the Internet



Wi-Fi link method:(three pairing methods)

Complete the wiring of the switch module before pairing

3.1 Method one:

Scan the QR code to configure the network guide.









How to reset/re-pair WiFi code

- a. For reset button:long press the button on the module to hear the beep sounds continuously.
- b. For reset switch (Set as reset switch in APP): press the switch button for 10 times to hear the beep sounds continuously.

(If using rocker light switch, you should press the rocker light switch for 20 times)

c. For rocker light switch (Set as rocker switch in APP):press the switch button for 10 times(ON/OFF cycle for 5 times) to hear the beep sounds continuously.

(If using reset switch, you should press the reset switch for 5 times)

Note: This WiFi switch module fits for rocker light switch and reset switch meanwhile. Please pay attention to the different pairing modes.

3.2 Method two:

Pair and clear up the WiFi code withBluetooth and WiFi connected meantime.(New Updated)

1.Confirm the device beeps continuously, if not, please refer to page 14 for how to enter the network configuration.



2.Open Smart Life/Tuya App and Click"+",then the prompt page will automatically show on the screen Click "Add".



3. Select the device you want to add and click "+"



















4. Enter Wi-Fi Password and click "Next" waiting for completing the connection.

5.Add the device successfully, you can edit the name of the device to enter the device page by click "Done"




-


3.3 Method three:



Open the App, select "+" on top right and choose "Switch (Wi-Fi)" to add device.



Make sure your smart phone and WiFi switch module are under the same WiFi network at 2.4 GHz connection.Confirm when the switch module beeping rapidly.



The connecting will take about 10-120 seconds to complete depending on your network condition.



When pairing is done, the switch will be shown on the App.

33 How to achieve multi-control association

Note:Please confirm you have successfully finished the WiFi link method above for adding this switch to your Smart Life App before the association.

1.WiFi add another smart switch to the same Smart Life/Tuva App.(If there is a smart switch having been added before to the app,just go to next step.)

Note:There is no need to wire the new added switch to the light, only L and N are required for wirina.

2. Then you will see two devices in the app and click the main switch(as One gang switch as below) by entering into the next operation.



3.Click ∠ in the upper right corner and choose"Multi-Control Association, and then click "+" in the right corner



4. Choose the switch that you want to associate to and then choose the switch button that you want to control the same light.


5. Then go back to previous page, you will see two items in the page, one is your main switch, the other is the one you associate just now.

Note:Please confirm the associated switch is enabled



6. Now you are able to control your light with two switches.Do not associate another button in the same switch for multi-control.

7.If you want to add another third or more smart switches to control your light, just repeat the steps above.And you will see the result as below when you associate another new switch.















Enter Smart Life Skill in Alexa APP

1. Complete product networking configuration in the App


Complete the device's networking configuration according to the prompts in the App. Note: In the App, change the name of the device to an easily identifiable name such as Alexa: names are usually in English, such as "bed light".

2. Configure the Amazon Echo device

(If you have already configured Amazon Echo, you can skip this step. The following instructions are based on the iOS client.)

- Make sure you Amazon Echo device is powered on and connected to a Wi-Fi network.
- Open the Alexa App on your phone. After successful. login, tap on the menu in the upper left corner of the Home page, select "Settings" and tap "Set Up A New Device" to set up the Amazon Echo.
- · Choose your Amazon Echo device type and language for connecting. Press and hold the small dot on the device until the light turns yellow. Then tap "Continue" to connect to the hotspot.

. After connecting to the Amazon Echo hotspot, return to the page. At this point, the connection is successful





Tap "Continue" to proceed to the next step. Choose a Wi-Fi network to connect to Amazon Echo will take a few minutes to try to connect to the network. After the network connection is successful, tan "Continue". An introduction video will appear. After the video ends, tap "Continue" to jump to the Alexa Home page. You have now completed the Amazon Echo's configuration process.

3. Key step - Link Skill

. Tap on "Skill" in the Alexa App menu.



Then search for "App Name". Tap "Fnable" to enable the Skill

•Enter the App account and password, then tap "I ink Now" to link your App account to enable the Skill. Now you can start your smart home journey.





4. Common commands

Control the device via voice commands, now you can control your smart device with Echo. You can control your device (such as your bedroom light) with the following commands:

Alexa, turn on/off bedroom light, (Turn on/off the liaht)

Alexa, set bedroom light to 50 percent. (Set the light to any brightness)

Alexa, brighten/dim bedroom light. (Increase/weaken the brightness of the light)

Alexa, set bedroom light to green. (Adjust the color of the light)



Enjoy your smart life of home automation for lighting control by using our All-in-one mobile App wherever you are in the world or simply by voice control when you are sitting at home comfortably.

SERVICE

1. During the free warranty period, if the product breaks down during normal use, we will offer free maintenance for

2. Natural disasters/man-made equipment failures, disassembly and repair without the permission of our company no warranty card products beyond the free warranty period, etc., are not within the scope of free warranty 3.Any commitment (oral or written) made by the third party

(including the dealer/service provider) to the user beyond the warranty scope shall be executed by the third party 4.Please keep this warranty card to ensure your rights 5. Our company may update or change the products without notice. Please refer to the official website for the undates

RECYCLING INFORMATION

All products marked with the symbol for separate collection of waste electrical and electronic equipment (WEEE Directive 2012/19 / EU) must be disposed of separately from unsorted municipal waste. To protect your health and the environment, this equipment must be disposed of at designated collection points for electrical and electronic equipment designated by the government or local authorities. Correct disposal and recycling will help prevent potential negative consequences for the environment and human health. To find out where these collection points are and

WARRANTY CARD

Product Information

Product Name Product Type Purchase Date Warranty Period Dealer Information Customer's Name Customer Phone

Maintenance Records

Customer Address

	Failure date	Cause Of Issue	Fault Content	Principal	i
					i
					i
					i
i					i

Thank you for your support and purchase at we Moes, we are always here for your complete satisfaction, just feel free to share your great shopping experience with us.









If you have any other need, please do not hesitate to contact us first, we will try to meet your demand.

moessmart

MOES, Official

@moes smart

@moes smart

www.moeshouse.com



WENZHOU NOVA NEW ENERGY CO.,LTD Address: Power Science and Technology Innovation Center, NO.238, Wei 11 Road, Yueging Economic Development Zone.

Yueging, Zheijang, China Tel:+86-577-57186815 Email:service@moeshouse.com



AMZLAB GmbH Laubenhof 23, 45326 Essen Made In China