



PS Series Owners Manual

PS300

PS1000

PS2000

PS3000

PSX2000

PSX3000

PS5000



The Excelsior Power PS series of inverters have been carefully designed and manufactured to provide you years of reliable operation.

Please read this manual thoroughly before connecting and operating your inverter. Please keep the manual for future reference, as it contains information that you may require in the correct connection, operation and troubleshooting of this inverter.

Excelsior Power Inverters

Excelsior Power have been involved in the design, manufacture and importation of power conversion technology for over 25 years. The PS series of power inverters are highly advanced, microprocessor controlled units that provide the highest surge capabilities, so they can start difficult loads, such as TV's, Microwaves, Refrigeration units and even Air Conditioners.

Unlike many inverters, which can damage 240 Vac motors, such as those found in refrigerators, the PS series provide a Pure Sine Wave output, which is very clean and perfect for Mains operated equipment, so that motors and fridges don't overheat and fail prematurely. The PSX series also have a display on front to show battery voltage and load, which takes the guess work out of battery time and consumption.

They also achieve the highest efficiency (90% plus) which means cooler running, higher reliability and longer running time!

Excelsior Power Inverters convert 12 or 24 volt Direct Current to 240 Volt, alternating current at 50 Hz.

Installation

When connecting the inverter to the battery, use the thickest wires available, keep the length as short as possible, 2 meters maximum length. To find the recommended minimal cable size for your inverter, please refer to the Specifications section at the back of this manual. To calculate the minimum battery size recommended for your inverter in Amp/Hours, please see the Specifications section at the back of this manual.

Mount the inverter in a clean environment, that is free of dust, insects and moisture, Ensure that the inverter has enough space around it for ventilation, especially at the front and rear for the cooling fan.

Connecting your inverter

1. Make sure the switch on the front of the unit is in the off position (0)
2. Connect the wires to the inverter input terminals at the rear of the unit. Make sure to match the negative (Black) terminal to the inverter with the wire that connects to the negative terminal on the battery.
3. Connect the positive (red) terminal on inverter connecting a wire to the positive terminal of the battery.
4. Make sure the connections are good and secure.

WARNING: Do not reverse connect polarity to battery, as this will damage inverter, and is not covered under warranty!

Getting Started

When you turn on an appliance that operates using a motor, fluorescent lights, air conditioning, fridge and some electronic loads, it requires an initial surge of power to start. This surge of power can be many times the running, or continuous power rating of the appliance.

Fridges and Air conditioners can take many thousands of watts for the first second to start up.

A microwave can use up to double the rated cooking power, so an 800 Watt microwave can use up to 1600 Watts of electrical power.

To work out the current from your battery, divide the wattage of the appliance by the battery voltage; IE 100 watts / 12 volts = 8 Amps.

Although all Excelsior Inverters are electrically isolated and filtered to minimise signal interference, some interference with your TV may be unavoidable, especially with weak signals. However, here are some suggestions that may improve reception.

1. First, make sure the TV antenna produces a clear signal under normal operating conditions (normal grid power) Also make sure the antenna cables properly shielded and of good quality.
2. Try changing the position of the inverter, antenna cable and TV power cord.
3. Isolate the TV, it's power cord and antenna cable from the battery power by running an extension cord from the inverter to the TV.
4. Coil the TV power cord.
5. Coil the DC battery cables from the battery to the inverter.
6. Attach a ' Ferrite Data Line Filter' to the power cord.

Note:

Some inexpensive audio systems may produce a slight 'buzzing' sound when used from the inverter. This is caused by deficient filters in the audio system, The only solution to solve this problem is to use a sound system of a higher quality power supply.

Use of RCD's

RCD's may be used with the inverter, please ensure the earth connection of the front of the inverter is connected to the chassis of the vehicle or an earth stake.

TROUBLESHOOTING

PROBLEM: Low or no Output Voltage.....

REASON

SOLUTION

Poor contact with the
Battery Terminals

*Clean terminals thoroughly

Use of incorrect type of
Voltmeter to test inverter

*Use True RMS meter

PROBLEM: Overload LED stays on.....

REASON

SOLUTION

Battery voltage bellow
11 / 22 volts

Recharge or replace battery

Equipment being operated
Draws too much power

*Use a higher capacity
inverter or do not use
This equipment.

Inverter is too hot
(Thermal shutdown mode)

*Allow inverter to cool
*Check for adequate
Ventilation
*Reduce the load on the
Inverter to rated
Continuous power

PROBLEM: Works fine but wont start fridge.....

REASON

SOLUTION

Battery low shutdown
When fridge starts

*Try restarting after
10 mins
*Use thicker battery
Cable
*Check battery

TROUBLESHOOTING

PROBLEM: TV Interference.....

SYMPTOM

**Electrical Interference
From inverter**

SOLUTION

- *Add a ferrite data line
filter onto the TV power
Cord**
- *Twist input cables together
3 times every meter**
- *Keep the inverter as far as
Possible from TV**
- *Use better antenna**

PROBLEM: Low Battery Alarm on All The Time.....

REASON

**Battery voltage bellow
11 / 22 volts**

SOLUTION

- *Keep input voltage above
11 / 22 volts**

**Poor or weak battery
condition**

- *Recharge or replace battery**

**Inadequate power being
Delivered to the inverter
Or excessive voltage drop**

- *Use thicker cable**
- *Keep cable length as short
as possible**

PROBLEM: Appliance does not start.....

SYMPTOM

Appliance does not turn on

SOLUTION

- *Try turning inverter on
Then off, then on again**
- *Appliance has higher start
Up surge than inverter**

SPECIFICATIONS.....

MODEL NO.	MAXIMUM CONTINUOUS POWER	SURGE POWER	NO LOAD CURRENT	MINIMUM BATTERY AMP/HOUR	INPUT VOLTS	DIMENSIONS H / W / Dmm	MASS Kg	CABLE SIZE
PS300/12	300 WATT	600 WATT	0.3A	30	10-15	62*105*185	1.0	6MM SQ
PS300/24	300 WATT	600 WATT	0.3A	30	20-30	62*105*185	1.0	4MM SQ
PS1000/12	1000 WATT	2000 WATT	0.8A	50	10-15	78*180*296	2.8	16MM SQ
PS1000/24	1000 WATT	2000 WATT	0.5A	30	20-30	78*180*296	2.8	8MM SQ
PS2000/12	2000 WATT	4000 WATT	0.8A	100	10-15	78*180*396	4.0	25MM SQ
PS2000/24	2000 WATT	4000 WATT	0.5A	50	20-30	78*180*396	4.0	16MM SQ
PSX2000/12	2000 WATT	4000 WATT	0.8A	100	10-15	78*180*396	4.0	25MM SQ
PSX2000/24	2000 WATT	4000 WATT	0.5A	50	20-30	78*180*396	4.0	16MM SQ
PS3000/12	3000 WATT	6000 WATT	0.8A	200	10-15	78*180*396	4.0	40MM SQ
PS3000/24	3000 WATT	6000 WATT	1.3A	100	20-30	128*180*396	5.6	20MM SQ
PSX3000/12	3000 WATT	6000 WATT	0.8A	200	10-15	128*180*396	5.6	40MM SQ
PSX3000/24	3000 WATT	6000 WATT	1.3A	200	20-30	128*180*396	5.6	20MM SQ
PS5000/12	5000 WATT	10000 WATT	1.6A	400	10-15	160*210*500	12	60MM SQ
PS5000/24	5000 WATT	10000 WATT	1.0A	200	20-30	160*210*500	12	30MM SQ



Phone:03 9775 1590

Email: Enquiries@inverter.com.au

Website: www.excelsiorpower.com.au

Address:

Factory 1

16 Titan Drive

Carrum Downs

Vic, 3201