



## Z-Wave Protocol Implementation Conformance Statement

### S2 In-wall Smart Dimmer switch

#### General Information

Product Identifier:	MS11ZS
Brand Name:	Minoston
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-20096981

#### Product Features

Switch Type	Push Button
Firmware Updatable	Updatable by Consumer by RF
Electric Load Type	Dimmable LED Incandescent LED
Switch Load Capacity Watts	500W
Color	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xEE02
Z-Wave Product Type:	0xEE00
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave

(Continued)

S2 In-wall Smart Dimmer switch

Association Group Information

Group # / Max      Description

Nodes

1 / 3                Z-Wave Lifeline  
2 / 5                basic set command

Supported Command Classes (16):

- |                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Basic V2                     | Central Scene V3         |
| Configuration                | Device Reset Locally     |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Powerlevel               |
| Security S2                  | Supervision              |
| Switch Multilevel V4         | Transport Service V2     |
| Version V3                   | Z-Wave Plus Info V2      |

Controlled Command Classes (1):

- Basic V2