


Wireless keyboard User's Guide For surface pro 3/4/5/6/7



Package Includes:
User Manual x1
Bluetooth Keyboard x1
USB charger x1

Product Specifications

1. Bluetooth 5.0 Interface Standard
2. Operating Distance Available: 10meters
3. Modulation System: GFSK
4. Operating Voltage: 3.7v
5. Working Current: <3mA
6. Standby Current: <0.3mA
7. Sleeping Current: <40uA
8. Charging Current: > 200mA
9. Standby Time: > 100days
10. Charging Time: 2-3 hours
11. Lithium Battery Capacity: 500mA (backlight keyboard model)
12. Sustainable Working Time: > 100hours (when backlight turn off)
13. Lithium Battery Life: 3years
14. Key Strength: 80±10g
15. Key Life: 5 million Stroke
16. Operating Temperature: -10°C ~+50°C

Getting Started Guide

1. Switching power and Bluetooth connection indicator: After entering the pairing mode, the indicator light flashes. After the connection is successful, it goes out. Long press the shutdown key to flash for 3 times and then it turns off.
2. Caps Lock indicator: Lights up when the keyboard is in uppercase input.
3. Low battery indicator: flashes when the battery is too low, prompting to charge.
4. Charging indicator: It will light up when charging, and will be off after charging is completed.
5. ON/OFF button: press keep 3 seconds to on, and press keep 3 seconds to off
6. Reset key: When no button is pressed, use a needle to pry it here and press down
7. USBTYPE C Charging Dock: When the low battery lights on, please use the Original charging cable to charger it Switch

Bluetooth Keyboard Pairing

Windows device (take Surface as example)

1. Open your tablet into start interface.
2. Click setting option and then click Change PC settings option.
3. Into setting interface, click setting, add setting. Your tablet will into search matching state.
4. Turn on the power of keyboard, press FN+C 1 seconds, into pairing state.
5. The tablet will show device name of Uogic-keyboard, click it.
6. No password, find the keyboard Bluetooth on screen, connection successful.

Shortcuts Information

☆- F1	Screen brightness-	⏸ F4	Mute	🌞	Colors Conversion
☆+ F2	Screen brightness+	🔊 F5	Volume-	🔊 F6	Keypad backlight+
▶ F3	Play/Pause	🔊 F6	Volume+	🌡 F7	Keypad backlight-
Fn -C	Bluetooth search	🖱 F7	Touch Pad Switch		

Note: Only under the Windows systm can realize these functions; Unable to realize these functions under the Android, under the Android system can only implement simple mouse function.

	Win10 gesture function	Finger gestures	Finger action
One-finger gestures	Left-click like on a mouse	👉	Single finger tap
	Moves the cursor	👉	Drag your finger
	Move an item or select text	👉	Tap, immediately tap and hold, then drag
Two-fingers gestures	Right-click like on a mouse	👉👉	Two fingers tap
	Scroll though a screen vertically	👉👉	Slide two fingers vertically
	Scroll though a screen horizontally	👉👉	Slide two fingers horizontally
	Zoom in or out	👉👉	Pinch your thumb and forefinger together or move them apart
Three-fingers gestures	Open Cortana	👉👉👉	Three fingers tap
	Display Multitasking View	👉👉👉	Swipe three fingers up
	Show Desktop	👉👉👉	Swipe three fingers down
	Wswitch apps	👉👉👉	Swipe three fingers left or right
Four-fingers gestures	Open Action Center	👉👉👉👉	Four fingers tap

⚠ Attention:

1. When not use for long time , suggest to close keyboard , in order to prolong battery life.
2. In order to get longer battery life , charging before keyboard power light flashes, charging time must be better more than 2hours.

Energy saving sleep mode

When keyboard not use will be enter sleep mode after 15minutes, keyboard indicator will off , press any key 5s to wake it up when need use again , then keyboard indicator will turn on.

Troubleshooting

1. Make sure the power is turned on
2. Ensure keyboard operable distance
3. Make sure the battery has power
4. Ensure the device' s Bluetooth was turned on
5. Ensure the wireless keyboard was connected with the Bluetooth
6. Ensure the wireless keyboard paired successfully

Cleaning

Washing , alcohol or a similar cleaning agent decontamination keyboard.

Charging

1. Connect Genuine Parts USB cable B port to keyboard cradle
2. Connect USB cable A port to power adapter or computer USB port.
3. When charging , charge indicator lights will be blinking , after full lights automatically turn off

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.