



欢迎!

感谢您选择FreedConn(路翼)头盔蓝牙通讯对讲耳机Hero。  
通过购买FreedConn(路翼)的产品,您将获得最贴心的保障和最无忧的售后。我们带给您的所有产品都是按照性能和安全的最高标准制造。并且,我们提供2年的全面保修作为我们客户服务和客户满意理念的一部分。我们希望您的此次购物将可以给您带来多年优质体验。

**安全提示:**  
\*骑行中佩戴FreedConn头盔耳机会降低您的耳朵收听周围环境声音的能力。长期以最大音量听音乐,再加上暂时适应性,会使人听不到柔和的声音,可能会导致永久性的听力损伤。

**温馨提示:**  
\*为了使您能够获得最佳的音质体验效果,建议您安装时尽量确保耳机单元到耳朵的距离保持在2毫米的距离以内。  
\*确保您的 HERO 电池在初次使用前至少充电 2 小时。

## 基础功能操作

- 1:开关机键/对讲键**

  - 开机:长按 2秒
  - 关机:长按 3秒
  - 连接手机:关机状态,长按8秒
  - 清除配对:开机状态,长按开机键8秒
- 2:音量加键/上一曲**

  - 音量加:长按
  - 上一曲:单击
- 3:多功能键**

  - 暂停/播放音乐:单击
  - 接听电话:单击
  - 结束电话:单击
  - 拒接电话:长按2秒
  - 语音呼叫:长按2秒
- 4:音量减键/下一曲**

  - 音量减:长按
  - 下一曲:单击

## 2-6人群组对讲

- A B ... F

1 关机状态下,A-F依次按开机键 8秒到配对状态

2 任意一个队员单击对讲键发起配对

3 等待自动完成配对

4 开始对讲

1.当队员人数≤5人时,需在报数为“末”位的主机上双击对讲按钮才可启动群组对讲!

2.当小队人数=6人直接开启对讲
- 按住 8秒

单击

主机自动播报号数:“1号.....6号”

## 群组通话断开/恢复连接

注意:在群组通话时单击“对讲键”会断开前后序号的机器连接,再单击“对讲键”连后一台,或双击“对讲键”连前一台。

## 音乐分享

- A B

1.请参照2-6人群组对讲操作,建立两人对讲状态,然后关机。

2.A和B机各自连接手机蓝牙,打开音乐app;此时需双方都暂停播放。

3.双击任意一台主机对讲键建立双方的音乐分享模式

4.分享方按播放键,分享音乐(谁按播放键,谁为分享方)。


5.双击任意一台主机对讲键退出/回连音乐分享
- A或B 双击

A或B 单击

A或B 双击
- 注意:只有分享方才能单击多功能键暂停音乐,被分享方不能执行此操作,否则直接退出音乐分享。

## 连接两台手机

- 1 在关机状态下,长按开机键8”与其中一部手机配对,然后再次关机并与另一部手机重复该操作,即可与另一部手机配对。



- 2 两台手机播放音乐的操作:



只能在各自手机音乐app连接后点击播放,才播放哪台手机的音乐(播放暂停,上下曲,音量调节请参照前面章节)。

- 3 两台手机来电接听的操作:

A在通话时B有来电,按一下多功能键结束A通话,再按一下多功能键接通B来电。

## 切换手动或自动来电接听

同时按下开关机键+下一曲键(开机待机状态下)



## 微信语音来电

微信来电只能在手机上操作接听与挂断



## 语言切换

同时按下开关机键+多功能键(开机待机状态下)



## 连接第三方蓝牙耳机

- 1 开机待机状态,按“多功能键”8秒配对
- 2 第三方蓝牙耳机开启配对状态



- 3 轻按我方耳机“对讲键”即可与第三方耳机连接。



## 查看组队号码

多人对讲配对后,在开机状态,长按开机键和多功能键3秒




## 安装步骤

- 1 将夹子安在头盔左侧合适的位置

4 将耳机贴到魔术贴上
- 2 将主机固定在夹子上

5 将耳机插头插入耳机孔
- 3 将魔术贴贴到头盔内侧

## 产品清单



## 产品技术参数

**蓝牙版本:** 5.1  
**频率:** 2.4 GHz  
**重量:** 48克  
**尺寸:** 90mmx48mmx21mm  
**电源适配器:** 直流电5V 1A  
**电池容量:** 1100mAh  
**电池类型:** 可充电锂聚合物电池

**电池材料:** 锂离子聚合物  
**电池型号:** 802060  
**电压:** 3.7V  
**功率:** 4.07Wh  
**对讲时长:** 30小时  
**音乐时间:** 约26小时  
**充电时间:** 约2小时  
**待机时间:** 蓝牙无连接无操作待机15分钟自动关机

## 产品售后技术支持



# HERO Operation Guide



Waterproof



6 people conference talking



Make & receive phone calls

## Welcome!

Thank you for choosing Hero, a freedConn multi-scenario bluetooth intercom headset. By purchasing FreedConn's products, you will get the most intimate protection and the most hassle-free after-sales. All the products we present to you are manufactured to the highest standards of performance and safety. We also offer a 2-year full warranty as part of our philosophy of customer service and customer satisfaction. We hope that your purchase will bring you high-quality experience for many years.

### Safety tips:

\*Wearing a FreedConn headset while riding will reduce your ears' ability to pick up ambient sounds. Listening to music at maximum volume for a long time, with the addition of temporary adaptation, will prevent a person from hearing soft sounds, which may lead to permanent hearing damage.

### Warm reminder:

\*In order to enable you to obtain the best sound quality experience, it is recommended that you ensure the distance between the headset unit and the ears remain within 2 mm during installation.

\* Please make sure to charge the HERO battery for at least 2 hours before the first use.

## Basic functions operation guide

### 1. Switch on (off) button/intercom button

Switch On: Long press 2"

Switch Off: Long press 3"

Connect to Mobile Phone: Long press 8" under the power off state

Pairing Information Resting: Long press 8" under the power on state

### 2. Volume up/previous song button

Volume Up: Long press

Previous Song: Short press

### 3. Multi-function button

Pause/Play Music: Short press

Answering A Call: Short press

Ending A Call: Short press

Rejecting A Call: Long press 2"

Voice Dial: Long press 2"

### 4. Volume down/next song button

Volume Down: Long press

Next Song: Short press

## 2-6 people group conference talking



1 Long press the power on/off button of A to F devices about 8" to turn into pairing mode.

2 One of the team members short press the intercom button to initiate pairing.



HOLD 8"



TAP 1X

3 Wait for pairing to each other automatically.



Report serial number automatically : #1...#6

4 Start talking

1. When the number of team members is ≤ 5, you need to double-click the intercom button on the last host in the queue to start group intercom!

2. If there are 6 people in the team, you could start talking directly.




TAP 2X

Note: It's necessary to delete the pairing information in all devices before starting pairing.

5 Group talking disconnecting/reconnecting

Note: In a group talking, short press the "intercom button" will disconnect your device with the previous and next numbers. Then short press the intercom button again will connect to the next number, or "double" click the intercom button to connect to the previous number.

## Music sharing



1. Refer to the "pairing method on P3 to establish a two-person intercom state and then turn off the two devices.  
2. A & B connect to mobile phone and open music APP.

Note: ① Music sharing only support two Hero pairing.  
② Meanwhile, the two device need to be in the music paused state.

2 Double click the intercom button to turn to music sharing mode.



A or B

TAP 2X

3 Short press multi-function button on the one who wants to share music to another one.



A or B

TAP 1X

Note: Only the one who shared the music could control the music.

4 Double click the intercom button of any of the two to get out of reconnect the music sharing mode.



A or B

TAP 2X

Note:  
1. When A shares music to B, press on intercom button of A or B, the music of A won't pause. Both A and B can double click intercom button to reconnect.  
2. Change the one who sharing music: Both A and B pause music, then the sharing one will be the one who press on the play button.

## Connect to two mobile phones

1 Under the power off state, long press on the switch on button for 8" to pair with one of the two phones, and then turn off the device again and repeated the action with another phone to get the another one paired.



HOLD 8"

2 How to operate music between two mobile phones?




It is needed to operate on the mobile phones for the first time playing music from different mobile phones.

3 How to answer calls by the two connected mobile phones?

Short press on the talking headset's multi-function button to hang up, and press again to answer another mobile's calling.

## Switch between manual answering and automatic answering

Under the standby state, short press on switch on/off button & next song button at the same time.



TAP 1X


## To answer a wechat calling

We-chat voice calls can only be answered and hung up via the mobile phone.



## Switch language

Under the standby state, short press on switch on/off button & Multi-function button at the same time.



TAP 1X

## Pair with the the third brand intercom headset

1 Under the standby state, long press the multi-function button for 8".



HOLD 8"

2 Turn the third brand intercom headset into pairing mode.



Other brand headset

(follow it's instruction manual)

3 Short press on hero's multi-function button to start talking.



TAP 1X


## How to check your series number in the team

While you are in a group and your device is power on state, long press the switch on & Multi-function button 3" to check the series number.



HOLD 3"

## Installation steps



1. Attach the base to the appropriate position on the left side of the helmet.




2. Attach the bluetooth host into the base slot.



3. Stick the Velcro pads onto the helmet's inner position nearby your ears.



4. Fix the speakers on the Vecros.




5. Get the USB jack plugged into the USB port on the Bluetooth host.

## Part list



Bluetooth host x1



Fix base x2



Microphone & speaker X1



Velcro pad x4



Soft micro Velcro pad x2



USB-C cable x1



Manual x1

## Product parameters

Bluetooth version: 5.1  
Frequency: 2.4 GHz  
Weight: 48g  
Host size: 90mmx48mmx21mm  
Charging adapter: Direct current 5V 1A  
Battery capacity: 1100mAh  
Battery type: chargeable polymer lithium battery

Battery material: Ternary lithium material  
Battery model: 802060  
Voltage: 3.7V  
Power: 4.07Wh  
Intercom time: 30H  
Music time: 26H  
Charging time: 2H  
Standby time: turn off automatically if there is no any action on the device no connecting with any other device for 15 minutes

## After-sales technical support

Scan the following code:



## **FCC Warning**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.