

Mercury Fritz Box 7360 Fibre Modem Router User Guide

Home » Mercury » Mercury Fritz Box 7360 Fibre Modem Router User Guide 🏗

Mercury Fritz Box 7360 Fibre Modem Router User Guide



Fritz Box 7360 Fibre Configuration

Using your own router? No worries, we've got you covered!
Ensure the Router is connected from LAN1 on Router to GE1 on ONT1

Contents

- 1 Log into the gateway:
- 2 How to add correct settings for the Mercury network:
- 3 Documents / Resources
- **4 Related Posts**

Log into the gateway:

- 1. Ensure your device is connected to the Router (preferably via cable)
- 2. Open a web browser
- 3. Type the following in the address bar at the top: fritz. box

- 4. If the first time you have logged in, then it will not require a username.
- 5. Select: Skip This Step and Continue

This should then give access to the router's user interface

How to add correct settings for the Mercury network:

- 1. From the menu on the left select: Internet
- 2. From the sub-menu select Account Information
- 3. In the page locate the Internet Connection tab

Ensure the following settings are changed:

1. Internet Service Provider: Other

2. Name: Mercury

3. Connect Via: External Modem or Router

4. Operating Mode: Make Own Connection to the Internet

5. Is Account Information Required?: Yes

6. Username: (your mercury acct number) @mercurybroadband.co.nz

7. Password: password

8. Upstream: 320000kbit/s

9. Downstream: 320000kbit/s

10. Select: Change Connection Settings

11. Maintain Permanently: Ticked

12. Use VLAN for Internet Access: Ticked 10

13. Check the Internet connection after "Apply": Ticked

14. Click: Apply15. Click: Submit



Documents / Resources



Mercury Fritz Box 7360 Fibre Modem Router [pdf] User Guide

Fritz Box 7360 Fibre Modem Router, Fritz Box 7360, Fibre Modem Router, Modem Router, Rout er

Manuals+,