

# niko 122-52202 Double Push Button With LEDs And Comfort **Sensors Instructions**

Home » niko » niko 122-52202 Double Push Button With LEDs And Comfort Sensors Instructions





122-52202 Double Push Button With LEDs And Comfort **Sensors Instructions** 



4 year warranty

## **Contents**

- 1 122-52202 Double Push Button With LEDs And Comfort **Sensors**
- 2 Technical data
- 3 Documents / Resources
  - 3.1 References

### 122-52202 Double Push Button With LEDs And Comfort Sensors

Double push button with LEDs and comfort sensors for Niko Home Control, anthracite coated

#### 122-52202

This double push button can be configured to control various actions and routines in a Niko Home Control II installation on bus wiring. It is fitted with programmable LEDs that provide feedback on the action. In addition, the push button can serve as an orientation light when the LEDs are ON.

Thanks to its integrated temperature and humidity sensor, the push button also supports multi-zone climate and ventilation control, increasing your energy efficiency and comfort.

- Its multi-purpose temperature sensor can be set to control a heating/cooling zone within a Niko Home Control II installation, as a basic thermometer (Niko Home Control programming software version 2.20), or to create certain conditions (e.g. control sunscreens)
- The humidity sensor can also be used within routines (Niko Home Control programming software version 2.20), for example, to perform automatic ventilation control in a bathroom or toilet The push button features an easy click-on mechanism for wall-mounted bus wiring controls and is available in all Niko finishings.

### **Technical data**

Double push button with LEDs and comfort sensors for Niko Home Control, anthracite coated.

- Function
  - Combine the push button's temperature sensor with a heating or cooling module for multi-zone control or a switching module for electrical heating
  - Combine its integrated humidity sensor with a ventilation module to perform automatic ventilation control
  - Setpoints and week programmes are managed via the app
  - Calibration is managed via the programming software
  - Maximum number of push buttons set as a temperature sensor per installation: 20
  - − Temperature sensor range: 0 − 40°C
  - Temperature sensor accuracy: ± 0.5°C
  - Humidity sensor range: 0 100 % RH (non-condensing, nor icing)
  - Humidity sensor accuracy: ± 5 %, between 20 80 % RH at 25°C
- Material central plate: The central plate is enamelled and made of rigid PC and ASA.
- Lens: Both keys on the push button are fitted at the bottom with a small amber-coloured LED (1.5 x 1.5 mm) to indicate the status of the action.
- Colour: enamelled anthracite (approximately NCS S 7502 R, RAL 7022)
- Fire safety
  - the plastic parts of the central plate are self-extinguishing (comply with a filament test of 650 °C)
  - the plastic parts of the central plate are halogen-free
- Input voltage: 26 Vdc (SELV, safety extra-low voltage)
- Dismantling: To dismount simply pull the push button off the wall-mounted printed circuit board.
- Protection degree: IP20
- Protection degree: IP40 for the combination of a mechanism and faceplate
- Impact resistance: After mounting, an impact-resistance of IK06 is guaranteed.

- Dimensions (HxWxD): 44.5 x 44.5 x 8.6 mm
- · Marking: CE





## **Documents / Resources**



niko 122-52202 Double Push Button With LEDs And Comfort Sensors [pdf] Instructions 122-52202 Double Push Button With LEDs And Comfort Sensors, 122-52202, Double Push But ton With LEDs And Comfort Sensors, Button With LEDs And Comfort Sensors, And Comfort Sensors, Sensors

## References

User Manual

#### Manuals+, Privacy Policy

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.