




nVIDIA GeForce RTX 4080 16GB GDDR6X Graphics Card User Guide

[Home](#) » [Nvidia](#) » nVIDIA GeForce RTX 4080 16GB GDDR6X Graphics Card User Guide 



GEFORCE
RTX 4080
Quick Start Guide

Contents

- 1 SYSTEM SPECIFICATIONS
- 2 EQUIPMENT
- 3 HARDWARE INSTALLATION
- 4 CONNECTING TO THE DISPLAY
- 5 SOFTWARE INSTALLATION AND CONFIGURATION
- 6 Documents / Resources
 - 6.1 References

SYSTEM SPECIFICATIONS

Thank you for choosing the NVIDIA® GeForce RTX™ 4080 graphics card.
Before you begin, please review the following System Specifications to ensure your PC has the appropriate hardware and software for your new graphics card.

System Specifications

Motherboard:

PCI Express® graphics slot required.

Clearance:

Must have space for 304mm (L) x 137mm (W) x 61mm (H) card.
One additional slot clearance in front of the fans is recommended for better airflow.

System Power Supply:

- 750 W power rating minimum.
- Supported power connector configurations:
- At least three PCIe 8-pin cables (with RTX 4080 PCIe Gen 5 Power Connector Adapter).
- One 450 W or greater PCIe Gen 5 Cable (16-pin).




Operating System:


Microsoft® Windows® 11 64-bit recommended, or Microsoft® Windows® 10 64-bit April 2018 Update v1803 or newer. Linux, 64-bit.


Driver Installation: 2 GB of available disk space required for driver installation.

EQUIPMENT

The following equipment is included in the NVIDIA GeForce RTX 4080 graphics card box.

Quick Start Guide	
Guide Guide	
Gen5 16-pin power connector adapter	

 **Attention:** Use only the included NVIDIA power connector adapter for your GeForce RTX 40 Series Founders Edition graphics card.




GeForce RTX 4080 Graphics Card

HARDWARE INSTALLATION

1. Turn off your computer, disconnect the power cord and remove any existing graphics card(s).


! Attention: It is very important that you wait until the graphics card has cooled before taking the card out of the system.

2. Remove three slot covers if there was no existing graphics card.



Remove three adjacent slot covers that correspond to the PCI Express slot you are installing the graphics card in.


3. Install the GeForce RTX 4080 graphics card into the primary PCI Express x16 slot on your motherboard.



Install your GeForce RTX 4080 into the Primary PCI Express x16 slot (the Primary slot is the one closest to the CPU).

! Attention: This GPU card should not be installed with the I/O brackets facing downwards.

4. Connect the 16-pin plug of NVIDIA power connector adapter to the power receptacle on the top of the GeForce RTX 4080 graphics card.




Connect at least three independent dedicated cables with 8-pin PCI Express plugs from the system power supply to the NVIDIA power connector adapter.

! Attention: Use only the included NVIDIA power connector adapter for your GeForce RTX 40 Series Founders Edition graphics card.

5. Reinstall the covers on your computer and reconnect any cables previously removed.

CONNECTING TO THE DISPLAY

1. Connect the display(s) to the graphics card.
2. Reconnect your power cord to the PC.



SOFTWARE INSTALLATION AND CONFIGURATION

With the hardware installed, the final step is to install the GeForce Experience software to update your drivers and optimize your games.

1. Download and install GeForce Experience software.

Go to <http://www.geforce.com/geforce-experience> and click Download Now.

Accept the NVIDIA software license agreement by selecting Agree and Continue. GeForce Experience software begins to install.

Select Close to finish the installation.

2. Optimize your installed games.

Open GeForce Experience and click Scan for Games and click OK to scan your installed games.

Click on Optimize All to optimize your game settings.

3. Get the latest drivers.

Open GeForce Experience, log in, and select the Drivers tab.

Select Download Driver. Your GPU driver begins to download.

Select Express Installation when the download finishes.

GeForce Experience begins to install the graphics driver.



Note: It may take several minutes for the installation to take place.

Your screen may go blank for a few seconds one or more times during installation. This is normal.

Click CLOSE when the driver install completes.

4. Congratulations! Your GeForce graphics card is now ready to use!



Note: If you have any questions about your NVIDIA product you can Chat live with NVIDIA Customer Care at www.nvidia.com/support or call 1-800-797-6530 (US) or 0800 404 7747 (UK).

Notice

The information provided in this specification is believed to be accurate and reliable as of the date provided. However, NVIDIA Corporation [“NVIDIA™”] does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This publication supersedes and replaces all other specifications for the product that may have been previously

supplied.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and other changes to this specification, at any time and/or to discontinue any product or service without notice. Customer should obtain the latest relevant specification before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer. NVIDIA hereby expressly objects to applying any customer general terms and conditions with regard to the purchase of the NVIDIA product referenced in this specification.

NVIDIA products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on these specifications will be suitable for any specified use without further testing or modification. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to ensure the product is suitable and fit for the application planned by customer and to do the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this specification. NVIDIA does not accept any liability related to any default, damage, costs or problem which may be based on or attributable to: [i] the use of the NVIDIA product in any manner that is contrary to this specification, or [ii] customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this specification. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party.

ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED ~As Is.- NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the NVIDIA terms and conditions of sale for the product.

VESA DisplayPort

DisplayPort and DisplayPort Compliance Logo, DisplayPort Compliance Logo for Dual-mode Sources, and DisplayPort Compliance Logo for Active Cables are trademarks owned by the Video Electronics Standards Association in the United States and other countries.



HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC.

OpenCL

OpenCL is a trademark of Apple Inc. used under license to the Khronos Group Inc.

MPEG LA (H.264/AVC)

THIS PRODUCT IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO [i] ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR [ii] DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE <http://WWW.MPEGLA.COM>.

Trademarks

NVIDIA, the NVIDIA logo, NVIDIA CUDA, NVIDIA GeForce, GeForce RTX, GeForce Experience, NVIDIA NVLink, GigaThread, Lumenex, PureVideo, and PhysX Technology are trademarks or registered trademarks of NVIDIA Corporation. Other company product names may be trademarks of the respective companies with which they are

associated.

Copyright

© 2022 NVIDIA Corporation. All rights reserved.



nVIDIA
www.nvidia.com

© 2022 NVIDIA Corporation.
All rights reserved.

Documents / Resources



[nVIDIA GeForce RTX 4080 16GB GDDR6X Graphics Card](#) [pdf] User Guide
900-1G136-2560-000, GeForce RTX 4080 16GB GDDR6X Graphics Card, GeForce RTX 4080,
16GB GDDR6X Graphics Card, GDDR6X Graphics Card, Graphics Card, Card

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.