



PORTA PHONE ULP16-MDW Dual Speaker with Switch Button User Guide

[Home](#) » [PORTA PHONE](#) » PORTA PHONE ULP16-MDW Dual Speaker with Switch Button User Guide 

Contents

- [1 PORTA PHONE ULP16-MDW Dual Speaker with Switch Button](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
- [4 Power ON/OFF](#)
- [5 Pairing \(Register mode\)](#)
- [6 Talking and listening](#)
- [7 CONFERENCE on MAIN](#)
- [8 Mic Muted](#)
- [9 FCC Warning](#)
- [10 Documents / Resources](#)
 - [10.1 References](#)
- [11 Related Posts](#)



PORTA PHONE ULP16-MDW Dual Speaker with Switch Button



Product Information

Specifications:

- **Model No.:** ULP16-MDW
- **Speaker Type:** Dual speaker
- **Switch Button:** Yes

Features:

- **Conference Mode:** Allows separation of headsets into 2 groups or all in conference mode
- **Mic Muted:** The microphone automatically stops when the Mic boom swivels up
- **FCC Compliant:** Complies with part 15 of the FCC Rules

FCC Warning:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Important Note:

To prevent possible hearing damage, do not listen at high volume levels for long periods.

Product Usage Instructions

Conference Mode:

To separate headsets into 2 groups or enable conference mode:

1. Locate the switch button on the lower side of the ear cup.
2. Press the switch button to toggle between separate groups or conference mode.
3. If a remote headset has been registered in 2 groups, all headsets will be in conference mode.

Mic Muted:

To stop the headset microphone:

1. Swivel up the Mic boom of the headset.
2. The microphone will automatically be muted.

FAQ (Frequently Asked Questions)

- **Q: How many speakers does the ULP16-MDW model have?**

A: The ULP16-MDW model has dual speakers.

- **Q: What does the switch button do?**

A: The switch button allows you to separate headsets into 2 groups or enable conference mode.



- **Q: How does the microphone mute function work?**

A: The microphone on the headset will automatically be muted when the Mic boom is swiveled up.

Power ON/OFF


- **Power ON:** Press and hold the power button till to GREEN LED blinks or lights up.
- **Power OFF:** Press and hold the power button till to the RED LED flashes.

Pairing (Register mode)

- Press and hold the power button to turn the headset power ON, the power LED should blink in Green color.
- Enter the pairing mode: Press the volume down button  3 times continually, then press and hold the volume up  till to the RED and Green LED blinking at alternately.
- The main headset enters the pairing mode first then also the Remote to pairing mode.
- The Green LED of the Remote headset will blink quickly and then turn off after being paired, press the power button to quit the pairing mode and keep the Main headset on the pairing mode can pair with more Remote or press the power button to quit pairing modes.
- Repeat the above step "d" for more Remote headsets paired with the same Main headset, or press the power button to finish the pairing(register).
- Press SW of the Main headset can make a total of 15 Remote headsets register in 2 separate groups. The Main headset can accept a maximum of 15 remotes registered in full duplex, the power LED will flash in an ORANGE color when the register remote reaches 15., press the power button to quit the pairing mode)
- Press the Switch button, and you can change from "Main" mode to "Remote" mode when enter the "Remote" mode, can only pair to the particular Main headset

Talking and listening

- The main headset and remote headset will start to search each other after powering ON, the GREEN LED

- Press the volume up  and down  button to adjust the headset speaker sound volume.

Press the switch located lower side of the ear cup to make 15 headsets to separate 2 groups or all in CONFERENCE if the remote headset has registered in 2 groups.

- **User Manual**

