



Shenzhen Sunveytech SN008X Digital Wireless Backup Camera Systems User Manual

[Home](#) » [Shenzhen Sunveytech](#) » Shenzhen Sunveytech SN008X Digital Wireless Backup Camera Systems User Manual 

Contents

- [1 Shenzhen Sunveytech SN008X Digital Wireless Backup Camera Systems](#)
- [2 System Features](#)
- [3 What You Get](#)
- [4 Wiring Guide](#)
- [5 Getting Started](#)
- [6 Trouble Shooting](#)
- [7 5 Inch Wireless Monitor Specification](#)
- [8 Wireless Backup Camera Specification](#)
- [9 FCC Warning](#)
- [10 Documents / Resources](#)
- [11 Related Posts](#)

SHENZHEN

Shenzhen Sunveytech SN008X Digital Wireless Backup Camera Systems



Before Operating The Set Please Read The Instructions Completely.

System Features

1. Instant Real-time Video Transmission.
2. This is ideal for cars, trucks, SUVs, Pickups or any vehicle where you want to add a backup camera
3. There are no wires from the backup camera to the monitor, they are Separate installations, so it is very easy to install, you do not have to run the wires from the back to the front.
4. The monitor can be fixed on the dash or windshield optional.
5. Monitor viewing is HD color and with guidelines built-in camera.
6. A backup camera design with AUTO-Lighting LED lights makes your night driving much safety.
7. Digital signal transmission is totally different from the analog signal transmission. The signal is the point-to-point. There is no interference from other devices.

What You Get

What's in the Box



5" Wireless
Color LCD Monitor



Wireless
Backup Camera




Camera Cord



Mount Bracket



Mount Bracket



User Manual



Cigarette Lighter
Adapter



Monitor Antenna

NOTE: The contents included may be different based on the kit you purchased. Please take the actual product as standard.

Wiring Guide



TIPS:

1. The camera is powered by the reversing light, please find out the reversing light with the test pencil, then connect the red wire of the camera to it and the black to the iron part.
2. The monitor is directly connected to the cigarette lighter to get the power. You can turn the display on or off with the red button on the cigarette lighter.

Getting Started

- Pairing the Camera and Monitor



Pairing: Power, switch to the channel AV1/AV2 , keep pressing “Menu”, pairing successfully will display image.

Trouble Shooting

If you have a problem when operating this product, please refer to this section. The most common problems are list below, along with the likely causes and solutions.

Signal Problem :

Check if Get Power Correctly for Both the Camera and Monitor, If Yes, Then Check if Get Signal When Working Distance With 2M.

Missing Part:

Not Brand New Without Installation Guide: We Ask Warehouse Guy Checked Again for All Our Stock To Make Sure All set Brand New With All Parts and User Manual

Stop Working No Power: May Be Connection Loose, Just Check the Connections Again, and Make Sure All Voltage is Correctly and Make Sure You are In Reversing Gear to Test it if You Get Power From Revers-ing Lights

5 Inch Wireless Monitor Specification

LCD Size:	5 Inch Color Monitor
Operating Frequency:	2400-2483.5MHZ
Transmitted Power:	17db
Resolution:	800(H) x 480(V)
Brightness:	800 cd/m ²
Response Time	25ms
TV System:	PAL/NTSC
Contrast:	500:1
Power Supply:	DC12V-36V
Operating temperature:	-20°C +70°C
Storage temperature:	-30°C +80°C

Wireless Backup Camera Specification

Waterproof Rating:	IP67
Image Sensor:	1/3" CMOS
Operating Frequency:	2400-2483.5MHZ
TV System:	NTSC/PAL
Resolution:	540 TV Lines
Minimum Illumination:	0 Lux [IR ON]
Transmitted Power:	17db
View Angle:	110°[H] 150°[D]
Power Supply:	DC 12V-36V
Operating temperature:	-20°C +70°C
Storage temperature:	-30°C +80°C

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:


- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

Documents / Resources

	<p>Shenzhen Sunveytech SN008X Digital Wireless Backup Camera Systems [pdf] User Manual</p> <p>M501, 2AQNR-M501, 2AQNRM501, SN008X, 2AQNR-SN008X, 2AQNRSN008X, SN008X Digital Wireless Backup Camera Systems, Digital Wireless Backup Camera Systems</p>
---	---