



# Streamlight 88033 Rechargeable Flashlight Instruction Manual

[Home](#) » [StreamLight](#) » Streamlight 88033 Rechargeable Flashlight Instruction Manual 

## Contents

- [1 Streamlight 88033 Rechargeable Flashlight](#)
- [2 INTRODUCTION](#)
- [3 SPECIFICATION](#)
- [4 BATTERY SAFETY](#)
- [5 BATTERY INSTALLATION/REMOVAL](#)
- [6 LED Charge Indicator](#)
- [7 GENERAL OPERATION](#)
- [8 PRODUCT USE](#)
- [9 Streamlight Limited Lifetime Warranty](#)
- [10 FREQUENTLY ASKED QUESTIONS](#)
- [11 References](#)



**Streamlight 88033 Rechargeable Flashlight**



## INTRODUCTION

A multipurpose, very brilliant, and rechargeable tactical flashlight, the Streamlight 88033 ProTac 2AA-X is made for outdoor activities, daily use, and security. This small 6-inch flashlight, which is made by Streamlight, is made of anodized aluminium for durability and impact resistance. Users can switch between high, low, and strobe modes using TEN-TAP programming to fit their demands. This multi-fuel flashlight, which costs between **\$50 and \$70**, may be powered by USB-C rechargeable batteries (separately sold) or AA batteries (included). It can reach up to 203 meters and produces an amazing 270 lumens when using alkaline batteries and up to 550 lumens when using the Streamlight rechargeable battery. With a 50,000-hour lifespan and C4 LED design, it guarantees dependable performance. The Streamlight 88033 is a strong, portable, and reliable flashlight for professionals, outdoor enthusiasts, and personal security. It is waterproof (IPX7) and impact-resistant up to two meters.

## IMPORTANT:

FULLY CHARGE BATTERY BEFORE FIRST USE.

## Caution:

LED Radiation (RG-2) – Do not stare into the beam. May be harmful to the eyes

- EU Authorized Representative:
- Falcon Logistics B.V., Hoeksteen 26 F,
- 2132 MS Hoofddorp, Netherlands

## SPECIFICATION

<b>Brand</b>	Streamlight
<b>Model</b>	88033 ProTac 2AA-X
<b>Price</b>	Varies by retailer
<b>Color Options</b>	Black, Coyote
<b>Material</b>	Anodized Aluminum
<b>Power Source</b>	Multi-fuel: 2 AA alkaline batteries (included) or Streamlight USB-C rechargeable battery (sold separately)
<b>Light Source</b>	LED (C4 LED technology, impervious to shock, 50,000-hour lifetime)
<b>Brightness &amp; Beam Distance</b>	Alkaline Batteries: 270 lumens, 5,000 candela, 141m beam distance Rechargeable Battery: 550 lumens, 10,250 candela, 203m beam distance
<b>Adjustable Light Modes</b>	TEN-TAP programming with 3 modes: 1) High/Strobe/Low (default) 2) High only 3) Low/High
<b>Run Time (Alkaline Batteries)</b>	High: 250 lumens, 141m beam, 2.5 hours Low: 18 lumens, 40m beam, 48 hours Strobe: 5 hours
<b>Switch Type</b>	Multi-function push-button tactical tail switch for one-handed operation
<b>Portability</b>	Lightweight, pocket-sized, fits in purses, sling bags, backpacks
<b>Durability</b>	Impact resistant (tested up to 2 meters)
<b>Waterproof Rating</b>	IPX7 waterproof
<b>Design Features</b>	Knurled barrel for secure grip, anti-roll face cap
<b>Clip &amp; Holster</b>	Removable, unbreakable pocket clip, includes nylon holster
<b>Length</b>	6.0 inches (15.3 cm)
<b>Serialization</b>	Serialized for positive identification
<b>Included Accessories</b>	2 AA alkaline batteries, nylon holster

**For compliance information, please visit**

- [www.streamlight.com/compliance](http://www.streamlight.com/compliance)

Thank you for selecting the ProTac® 2AA-X multi-fuel, personal carry tactical flashlight. As with any professional tool, reasonable care and maintenance of this product will provide years of dependable service. Please read this manual before using your ProTac®.

SAVE THESE INSTRUCTIONS. This guide contains important safety and operating instructions for your ProTac®.

## **CAUTION**

STROBE MODE MAY CAUSE SEIZURES IN PERSONS WITH PHOTOSENSITIVE EPILEPSY.

## **CAUTION**

LED RADIATION (RG-2). DO NOT STARE INTO BEAM. MAY BE HARMFUL TO THE EYES. PER IEC 62471 Ed 1.0:2006-07.

## **WARNING**

RISK OF INJURY. THE USE OF SUBSTANDARD OR AFTER-MARKET COMPONENTS, MODIFICATIONS TO THE ORIGINAL PARTS, OR USE OF THIS FLASHLIGHT WITH ANY INCOMPATIBLE PRODUCT MAY VOID THE WARRANTY AND COULD LEAD TO PRODUCT FAILURE OR PERSONAL INJURY.

## **BATTERY SAFETY**

### **CAUTION**

EXPLOSION RISK, BURN, AND FIRE HAZARD. DO NOT DISASSEMBLE, CRUSH, SHORT CIRCUIT, HEAT ABOVE 140°F (60°C), OR DISCARD IN FIRE. USE ONLY WITH THE SPECIFIED STREAMLIGHT PRODUCTS. KEEP AWAY FROM CHILDREN. BATTERY MUST BE RECYCLED OR DISPOSED OF PROPERLY.

### **NOTICE**

This product is designed to use two AA batteries or one Stream-light #940215 protected Li-ion rechargeable battery pack. The rechargeable battery contained in this product is recyclable. At the end of its useful life, under various country and state laws, it may be illegal to dispose of this battery in the municipal solid waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal (In USA: RBRC).

## **BATTERY INSTALLATION/REMOVAL**

At the end of battery life, the switch may appear intermittent or non-functional. Replacing or recharging the batteries will restore normal operation.

1. Unscrew the Ttail cap and remove expired batteries.
2. Install new AA batteries or recharge the Li-ion battery positive end first. Polarity is marked on the inside of the body.
3. Replace tailcap.

## **PROTAC® 2AA-X LI-ION BATTERY CHARGING**

### **NOTICE**

- Fully charge batteries before first use.

The ProTac® 2AA-X USB model ships with one Li-ion rechargeable battery with an integrated charge port.

To charge the battery, insert the USB-C plug into the connector near the positive end of the battery. The battery may be left plugged into a USB-C cable continuously, there is no danger of overcharging.

## **LED Charge Indicator**

- Charging...The red LED is on.

- Charged...Green LED is on.
- The charge time is approximately 4 hours.

## GENERAL OPERATION

The ProTac® 2AA-X features a programmable switch with momentary operation (light press or tap) and constant operation (press until click).

- **High:** Tap and hold; click to lock on; click again for off.
- **Strobe:** Fast double-tap (within a half second) and hold; click to lock on; click again for off.
- **Low:** Fast triple-tap (within a half second per tap) and hold; click to lock on; click again for off.

## Accessing Other Programs

The ProTac® 2AA-X features a TEN-TAP® programmable switch allowing the user to select one of two different programs. To change to the next program, starting from the “Off” position, tap the switch rapidly 9 times (within 0.4 seconds per tap) and hold it down the 10th time. Continue holding the switch until the light turns off (approximately 1 second), then release the switch. Available programs are High-Strobe-Low (Factory Default), High Only, or Low-High.

## MAINTENANCE

It is important to keep the tailcap O-ring clean and free of debris.

## PRODUCT USE

Streamlight flashlights are intended for use as high-intensity, heavy-duty, and portable light sources. The use of Streamlight flashlights for any purpose other than as light sources is specifically discouraged by the manufacturer. Streamlight specifically disclaims liability for other than the recommended use.

## NOTICE

Be sure to use only genuine Streamlight replacement parts to ensure product safety. Substitution may invalidate the product approval. Do not try to repair the unit yourself. Send it to a qualified service facility or return it to the factory.

## Streamlight Limited Lifetime Warranty

Streamlight warrants this product to be free of defects for a lifetime of use except for batteries and bulbs, abuse, and normal wear. We will repair, replace, or refund the purchase price of this product should we determine it to be defective. This limited lifetime warranty also excludes rechargeable batteries, chargers, switches, and electronics which have a 2-year warranty with proof of purchase.

THIS IS THE ONLY WARRANTY, EXPRESSED OR IMPLIED, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES ARE EXPRESSLY DISCLAIMED EXCEPT WHERE SUCH LIMITATION IS PROHIBITED BY LAW. You may have other specific legal rights which vary by jurisdiction.

- Go to [www.streamlight.com/support](http://www.streamlight.com/support) for a complete copy of the warranty. To register your product, go to [www.streamlight.com](http://www.streamlight.com) (Online Product Registration). Retain your receipt or any proof of purchase.

## SERVICE OPTIONS

- The ProTac® series contains few or no user-serviceable parts.
- For service options, go to [www.streamlight.com/support/service](http://www.streamlight.com/support/service) and complete the Online Service Request for factory service or to find the location of an authorized Streamlight repair center near you.

### Or contact:

- Customer Service STREAMLIGHT, INC. 30 Eagleville Road Suite 100
- Eagleville, PA U.S.A. 19403-3996
- **Phone:** [800-523-7488](tel:800-523-7488) Toll-Free / +1 [610-631-0600](tel:610-631-0600)
- **Fax:** [800-220-7007](tel:800-220-7007) / +1 [610-631-0712](tel:610-631-0712)

## FREQUENTLY ASKED QUESTIONS

What is the Streamlight 88033 ProTac 2AA-X Tactical Flashlight?

The Streamlight 88033 ProTac 2AA-X is a 270-lumen, rechargeable, multi-fuel tactical flashlight designed for everyday carry (EDC). It is lightweight, portable, impact-resistant, waterproof, and features adjustable light modes via TEN-TAP programming.

What is the maximum brightness of the Streamlight 88033 ProTac 2AA-X flashlight?

With alkaline batteries, it delivers 270 lumens, 5,000 candela, and a 141m beam. With the Streamlight USB-C rechargeable battery (sold separately), it reaches 550 lumens, 10,250 candela, and a 203m beam distance.

What are the different light modes on the Streamlight 88033 ProTac 2AA-X flashlight?

This flashlight features TEN-TAP programming, allowing users to select between High/Strobe/Low (factory default) High only Low/High

What power sources are compatible with the Streamlight 88033 ProTac 2AA-X flashlight?

It supports two AA alkaline batteries (included) or the Streamlight USB-C rechargeable battery (sold separately).

Why is my Streamlight 88033 ProTac 2AA-X flashlight not turning on?

Ensure that the batteries are installed correctly. If using rechargeable batteries, verify they are charged. If the issue persists, try replacing the batteries or performing a TEN-TAP reset.

Why does my Streamlight 88033 ProTac 2AA-X flashlight keep cycling through modes unexpectedly?

This could be due to accidental TEN-TAP programming activation. Try resetting the TEN-TAP function by holding down the tail switch and selecting your preferred mode.

Why is my Streamlight 88033 ProTac 2AA-X flashlight dim or not as bright as expected?

If using alkaline batteries, they may be running low. Consider switching to new batteries or using the Streamlight USB-C rechargeable battery for higher brightness.

**DOWNLOAD THE PDF LINK:** [Streamlight-88033-Rechargeable-Flashlight-Instruction-Manual](#)

## References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.