

# A3002RU Multiple SSID settings

## Contents

- [1 A3002RU Multiple SSID settings](#)
- [2 DOWNLOAD](#)
- [3 Related Posts](#)

## A3002RU Multiple SSID settings

It is suitable for: **N100RE, N150RH, N150RT, N151RT, N200RE, N210RE, N300RT, N301RT , N300RH, N302R Plus, A702R, A850R, A3002RU**

**Application introduction:** Solution about how to configure multiple SSID for TOTOLINK products.

### STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering `http://192.168.0.1` into the address bar of your browser.

5bda6304ed391.png


Note: The default access address varies depending on the actual situation. Please find it on the bottom label of the product.


### STEP-2:

User Name and Password are required, by default both are **admin** in lowercase letter. Click **LOGIN**.

## USER LOGIN

[Forget Password?](#)

 User Name

 Password

**LOGIN**

### STEP-3:

Please go to **Wireless 2.4GHz ->Multiple SSID 1** page, and check which you have selected. Select **Enable** , then Input your own **SSID** and **Pre-Shared Key** , then Click **Apply** and repeat this operation to **Multiple SSID 2 Multiple SSID 3 and Multiple SSID 4.**

**TOTO LINK**  
The Smartest Network Device

Model No. A3002RU (Firmware V1.0.4)

Easy Setup Reboot Help

Status  
Operation Mode  
Network  
IPv6 Network  
Wireless 5GHz  
**Wireless 2.4GHz**  
Basic Settings  
Multiple SSID 1  
Multiple SSID 2  
Multiple SSID 3  
Multiple SSID 4  
Advanced Settings  
WDS Settings  
Access Control  
WPS Settings  
Wireless Schedule  
QoS  
Firewall  
USB Share  
System

**Multiple SSID 1**

Multiple SSID 1  
SSID: TOTOLINK\_A3002RU\_VAP1  
Access: LAN+WAN  
Broadcast SSID: Enabled  
Encryption: WPA-Mixed  
Limit Client AP(3-64): 64  
Download: 0 Mbps (0:Unlimit)  
Upload: 0 Mbps (0:Unlimit)  
Authentication Mode: Enterprise (RADIUS) Personal (Pre-Shared Key)  
WPA Cipher Suite: TKIP AES  
Pre-Shared Key Format: Passphrase  
Pre-Shared Key:   
Apply

#### STEP-4:

Please go to **Wireless 5GHz ->Multiple SSID 1** page, and check which you have selected.

Select **Enable** , then Input your own **SSID** and **Pre-Shared Key** , then Click **Apply** and repeat this operation to **Multiple SSID 2 Multiple SSID 3 and Multiple SSID 4.**

**TOTO LINK**  
The Smartest Network Device

Model No. A3002RU (Firmware V1.0.4)

Easy Setup Reboot Help

Status  
Operation Mode  
Network  
IPv6 Network  
**Wireless 5GHz**  
Basic Settings  
Multiple SSID 1  
Multiple SSID 2  
Multiple SSID 3  
Multiple SSID 4  
Advanced Settings  
WDS Settings  
Access Control  
WPS Settings  
Wireless Schedule  
Wireless 2.4GHz  
QoS  
Firewall  
USB Share  
System

**Multiple SSID 1**

Multiple SSID 1  
SSID: TOTOLINK\_A3002RU\_5G\_VAP1  
Access: LAN+WAN  
Broadcast SSID: Enabled  
Encryption: WPA-Mixed  
Limit Client AP(3-64): 64  
Download: 0 Mbps (0:Unlimit)  
Upload: 0 Mbps (0:Unlimit)  
Authentication Mode: Enterprise (RADIUS) Personal (Pre-Shared Key)  
WPA Cipher Suite: TKIP AES  
Pre-Shared Key Format: Passphrase  
Pre-Shared Key:   
Apply

**DOWNLOAD**

Manuals+.