

N300RT Wireless SSID Password Settings

Contents

- [1 N300RT Wireless SSID Password Settings](#)
- [2 Application introduction:](#)
- [3 Settings](#)
 - [3.1 Questions and Answers](#)
 - [3.2 Q1: Should I restart the router after setup wireless information?](#)
- [4 DOWNLOAD](#)
- [5 Related Posts](#)

N300RT Wireless SSID Password Settings

It is suitable for: **N100RE, N150RH, N150RT, N151RT, N200RE, N210RE, N300RT, N301RT , N300RH, N302R Plus**

Application introduction:


The Wireless SSID and password are the basic information for you to connect Wi-Fi network. But sometimes you may forget or want to change them regularly, so here we will guide you how to check or modify the wireless SSID and password.

Settings

STEP-1: Enter the setup interface

Open a browser, enter **192.168.0.1**. Input User Name and password (default **admin/admin**) on login management interface, as follows:

Note: The default access address varies depending on the actual situation. Please find it on the bottom label of the product.



STEP-2: View or modify the wireless parameters

2-1. Check or modify in Easy Setup page.

Login management interface, first enter the **Easy Setup** interface, you can see **wireless settings**, as follows:

TOTO LINK
The Smartest Network Device

The Smartest Network Device

Model No. N300RT (Firmware V2.2.0)

Advanced SetupHelp

Easy Setup

Connect Status

Connect Status DHCP

Internet Setting

WAN Type DHCP Client

Wireless Setting

SSID TOTOLINK N300RT

Pre-Shared Key 88888888 (length range is 8-63)

IPTV Settings

IPTV Disable

Apply

Refresh

Copyright(C)2017 TOTOLINK Ltd, All Rights Reserved

2-2. Check and modify In the Advanced Setup

If you also need to set more parameters for WiFi, you can enter the **Advanced Setup** interface to set up.

TOTO LINK
The Smartest Network Device

The Smartest Network Device

Model No. N300RT (Firmware V2.2.0)

Advanced SetupHelp

Easy Setup

Connect Status

Connect Status DHCP

Set the SSID and password according to the following procedure.

TOTO LINK

The Smartest Network Device

The Smartest Network Device

Model No. N300RT (Firmware V2.2.0)

Easy SetupRebootHelp

Status

Operation Mode

Network

IPv6 Network

Wireless

Basic Settings

Multiple SSID 1

Multiple SSID 2

Multiple SSID 3

Multiple SSID 4

Advanced Settings

WDS Settings

Access Control

WPS Settings

Wireless Schedule

Basic Settings

Basic Settings

Enabled

SSID

TOTOLINK N300RT

Broadcast SSID

Enabled

Encryption

WPA2

Limit Client AP(3-64)

32

Download:

0

Mbps (0:Unlimit)

Upload:

0

Mbps (0:Unlimit)

Authentication Mode

Enterprise (RADIUS)

Personal (Pre-Shared Key)

WPA2 Cipher Suite

TKIP

AES

Pre-Shared Key Format

Passphrase

88888888

Apply

You are also able to set the **Channel Width, Data Rate, RF Output Power**.

TOTO LINK

The Smartest Network Device

The Smartest Network Device

Model No. N300RT (Firmware V2.2.0)

Easy SetupRebootHelp

Status

Operation Mode

Network

IPv6 Network

Wireless

Basic Settings

Multiple SSID 1

Multiple SSID 2

Multiple SSID 3

Multiple SSID 4

Advanced Settings

WDS Settings

Access Control

WPS Settings

Wireless Schedule

QoS

Firewall

System

Advanced Settings

Band

2.4 GHz (B+G+N)

Channel Width

40MHz

Control Sideband

Upper

Region:

Europe, China

Channel Number

Auto

WMM

Enabled

Data Rate

Auto

Fragment Threshold

2346

(256-2346)

RTS Threshold

2347

(0-2347)

Beacon Interval

100

(20-1024 mc)

Preamble Type

Long Preamble

Short Preamble

IAPP

On

Off

Protection

Enabled

Disabled

Aggregation

Enabled

Disabled

Short GI

Enabled

Disabled

WLAN Partition

Enabled

Disabled

20/40MHz Coexist

Enabled

Disabled

TX Beamforming

Enabled

Disabled

RF Output Power

100%

70%

50%

30%

15%

Copyright(C)2017 TOTOLINK Ltd, All Rights Reserved

Q1: Should I restart the router after setup wireless information?

A: After setting, you need to wait a few seconds for the wireless information to take effect.

DOWNLOAD

N300RT Wireless SSID Password Settings – [[Download PDF](#)]
