



# VARMILO VA Series Mechanical Keyboard User Manual

[Home](#) » [VARMILO](#) » VARMILO VA Series Mechanical Keyboard User Manual 

## VARMILO VA Series Mechanical Keyboard



## Contents

- 1 Layout
- 2 Notes
- 3 Indicator Light Description
- 4 Wireless (Bluetooth & 2.4G) Channel On And Off
- 5 Bluetooth Mode Connection Operation
- 6 2.4G Mode Connection Operation
- 7 Wired Mode And Wireless Mode Switching
- 8 Multimedia Function
- 9 Latency Adjustment
- 10 Lighting Effect
- 11 Low Battery Warning
- 12 Other Functions
- 13 Varmilo Warranty Service Information
- 14 Maintenance Instructions
- 15 FCC WARNING
- 16 Customer Support
- 17 Documents / Resources
  - 17.1 References
- 18 Related Posts

## Layout



## Notes

- All Fn key combinations need to press Fn first, then press other keys; The buttons are released in no particular order.

## Indicator Light Description

1. Charging indicator: The indicator is on when charging, and the indicator is off when charging is complete.
2. Bluetooth channel indicator (is F1, F2, F3 key indicator) : the corresponding channel light blinking indicates that waiting for connecting, the indicator light off after successful connection.
3. 2.4G indicator (is F4 key indicator) : The indicator blinking indicates waiting for pairing, the indicator light off

after successful connection.

4. Keypad area indicator: The indicators light on when keypad area active, and The indicators light off when keypad area off.
5. Caps Lock indicator light: White light on when capitalized, light off when Lower case.
6. freeze lock indicator: lock when the white light on, back to normal when the light off.

## Wireless (Bluetooth & 2.4G) Channel On And Off

- Long press Fn + Insert keyboard for 3 seconds to turn on or trun off the wireless mode.
- Keyboard continuously turn on and off need to pause 3 seconds buffer time.
- After the channel is turned on again, the wireless mode is connected to the wireless mode before the shutdown by default. If the channel is not successfully connected, the corresponding indicator blinks.

## Bluetooth Mode Connection Operation

- 1.Press Fn + F1 / F2 / F3 (corresponding to 1/2/3 channels respectively), and the F1 / F2 / F3 key light blinks slowly, indicating that it is waiting for Bluetooth pairing. The name is “Varmilo VS-1/2” of Bluetooth channel will be found in the device.
- Long press Fn + F1 / F2 / F3 (corresponding to 1/2/3 channels respectively) for 5 seconds to clear the currently connected device and wait for pairing again.

## 2.4G Mode Connection Operation

- Press Fn + F4, When the F4 key light blinks slowly, indicating that it is waiting for 2.4G connection. After the connection is completed, the F4 key light will be steady on. (The included 2.4G receiver has been paired before delivery)
- Long press Fn + F4 for 5 seconds to clear the currently paired 2.4G receiver, and the F4 light will flash. At this point, you can plug in the new 2.4G receiver for pairing, and after the pairing is successful, the F4 key light is on.

## Wired Mode And Wireless Mode Switching

- The keyboard will automatically switch to wired mode after inserting the data cable. Or also can via press Fn + Delete to switch the wireless or wired mode.
- Unplugging the data cable will automatically switch to wireless mode, and it will connect the last connection wireless mode of device (if the device all wireless channels haven't been connected, the F1 light will flashes and Bluetooth channel 1 waits for pairing).

## Multimedia Function

Combinations	Functions	Combinations	Functions	Combinations	Functions
Fn + F7	Last Song	Fn + F8	Play/Pause	Fn + F9	Next Song
Fn + F10	Mute	Fn + F11	Vol Down	Fn + F12	Vol Up

## Latency Adjustment

- Long press Fn + 1 / 2 / 3 (in the main key area) for 3 seconds, the Caps Lock light will flash three times to set the keyboard delay to Fast mode or Normal mode or Slow mode.

## Lighting Effect

- Press Fn + “Left shift” or “Right shift”, to switch light effect to the last one or next one.
- Press Fn + “-” or “+”, to switch the color light effect to the last one or next one.
- Press Fn + “←” or “→” to slow down or speed up the dynamic speed of the backlight effect.
- Press Fn + “↓” or “↑” to reduce or increase the brightness of the backlight effect.
- Press Fn + “X” to turn on/off the keyboard backlight.

## Low Battery Warning

- The charging indicator light will slowly flash indicates that the battery is low. If the keyboard is not charged within 10 minutes, it will power off automatically.

## Other Functions

- Press Fn + “Win” to lock/unlock the Win key.
- Long press Fn + “Left Ctrl” for 3 seconds, the Caps Lock light will flash three times, indicates that the functions of “Caps Lock” and “Left Ctrl” is swapping. In that time, Long press Fn + “Caps Lock” for 3 seconds to swap the functions back.
- Press Fn + D + “Backspace”, the Caps Lock light will flash three times, indicates that the keyboard resetting to the factory settings.
- Long press Fn + “D” for 3 seconds, the Caps Lock light will flash three times, indicates that the key values, lighting effects, and connection history are all resetting to factory settings.

## Varmilo Warranty Service Information

- Varmilo provides one year free warranty service for keyboards and three months for accessories from the date of order receipt.
- The warranty period is based on this card and the date of purchase. Please keep it properly. If you lose this card, you can still use the purchase voucher (invoice, receipt) and the purchase information of e-commerce as the warranty basis.
- Free warranty service is only applicable to non-human quality problems in normal use. If the product is damaged due to human factors or force majeure, the free warranty service cannot be provided. Human factors include external damage (impact, scraping, etc.), liquid (water, beverage, etc.), unauthorized disassembling, removing the serial number or warranty sticker of the product itself, etc. Force majeure includes the damage caused by flood, dampness, rodent damage and other natural disasters.
- For products with printed patterns on the cases, please avoid wiping with alcohol and use clean water or alcohol-free cleaning products.

## Maintenance Instructions

- During the warranty period, you can enjoy the free warranty service. If exceeded free warranty period, Varmilo will still provide paid maintenance service.
- Customers could ask for warranty service from where you purchased the products, or contact [support@zhihaihe.cn](mailto:support@zhihaihe.cn) for further assistant.

## FCC WARNING

**This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:** (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

**NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help. The device has been evaluated to meet general RF exposure statement.

The device can be used in portable exposure condition without restriction.

## Customer Support

Scan the QR code for more detailed and update news of Varmilo.

Official Website



Weibo



WeChat



Instagram



Twitter





Zhihaihe Marketing (Shenzhen) Co., Ltd.

**Tel:** +86-755-2644 4451

**Fax:** +86-755-2644 4428

**Official website WEB:** [keyboard.varmilo.com](http://keyboard.varmilo.com)

**Address ADD:** Building 3, Building 3, Tianliao Community, Yutang Street, Yutang Street, Guangming District, Shenzhen, Guangdong Province, China  
Rm202, 2nd Floor, Block 3, 10th Industrial Zone, Tianliao Community, Yutang Street, Guangming District, Shenzhen, China

# VARMILO

## Documents / Resources



[VARMILO VA Series Mechanical Keyboard](#) [pdf] User Manual  
VA Series Mechanical Keyboard, VA Series, Mechanical Keyboard, Keyboard

## References

- [Varmilo Official Website](#)
- [User Manual](#)

[Manuals±](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.