



VIBE sound PULSE 12-V4 Pulse 12 Inch Component Subwoofer Owner's Manual

[Home](#) » [Vibe sound](#) » VIBE sound PULSE 12-V4 Pulse 12 Inch Component Subwoofer Owner's Manual 



sound PULSE 12-V4 Pulse 12 Inch Component Subwoofer
Owner's Manual



Contents

- [1 PULSE 12-V4 Pulse 12 Inch Component Subwoofer](#)
- [2 TS PARAMETERS](#)
- [3 Documents / Resources](#)
- [4 Related Posts](#)

PULSE 12-V4 Pulse 12 Inch Component Subwoofer

PULSE 12

COMPONENT SUBWOOFER

300 WATTS RMS

900 WATTS PEAK

MINIMUM INPUT: 150 WATTS RMS

MOUNTING DEPTH: 5.1" (130MM)

MOUNTING DIAMETER: 10.8" (276MM)

FREQUENCY RESPONSE: 25HZ 1.5KHZ

IMPEDANCE: RECOMMENDED AMPLIFIER: PULSE STEREO 2



RUBBER SURROUND
CONTROLS THE
MOVEMENT OF THE
WOOFER CONE

RUBBER
SURROUND

IMPP CONE
RIGID POLYPROPELENE
WOOFER CONE FOR
SMOOTH, LOW BASS

IMPP CONE
T T

SINGLE SPIDER
PROVIDES STABILITY
AND CONTROL OF THE
VOICE COIL

SINGLE
spider

SINGLE MAGNET
POWERFUL FERRITE
MAGNET PROVIDES THE
FORCE FOR THE
MOTOR SYSTEM

SINGLE MAG

TORSION BASKET
PROVIDES SUPPORT FOR
THE MOVING PARTS AND
MOTOR

TORSION
BASKET

SPRING TERMINAL
ALLOWS EASY
CONNECTION OF HEAVY
GAUGE CABLE

SPRING
TERMINAL



FOR ENQUIRIES AND SUPPORT PLEASE CONTACT INFO@VIBEAUDIO.CO.UK

TS PARAMETERS

REVC:3.6 OHM
FO : 25.984Hz
SD:13.273mq
MMD:62G
BL:..... 6.238Tm
QMS:3.578
Q:0817
QTS:..... 0.665
NO:0.036%
SPL : 80.6DB
VAS:17358M
PI CMS:..... 693.876uM/N
KRM :2261mOHM
ERM: 0.908 MMS: 54070G
MMD:..... 53.191KG

KXM :20.535MH
EXM : 0.732
RECOMMENDED ENCLOSURE
VOLUME:..... PORT
AREA:..... PORT
LENGTH:..... PORT
TUNING:1.5CUFT 23SQIN 20" 35Hz



Documents / Resources

	VIBE sound PULSE 12-V4 Pulse 12 Inch Component Subwoofer [pdf] Owner's Manual PULSE 12-V4, Pulse 12 Inch Component Subwoofer, Component Subwoofer, PULSE 12-V4 Su bwoofer, Subwoofer
---	---