



Vision X Tremor XD High Output LED Beacon Instruction Manual

[Home](#) » [vision X](#) » Vision X Tremor XD High Output LED Beacon Instruction Manual 

Vision X Tremor XD High Output LED Beacon



Contents

- 1 WARNING
- 2 FEATURE
- 3 FEATURES
- 4 INSTALLATION
- 5 WIRING
- 6 WIRING DIAGRAM
- 7 FLASH PATTERNS
- 8 ADJUSTING FLASH PATTERN
- 9 AMBIENT LIGHT SENSOR FUNCTION
- 10 SPECIFICATIONS
- 11 WARRANTY TERMS & CONDITIONS:
- 12 CUSTOMER SUPPORT
- 13 Documents / Resources
- 14 Related Posts



WARNING

Read carefully and understand all instructions before operating.

- It is not recommended to use magnetically mounted warning devices on the outside of a vehicle in motion. Usage is at the sole risk and responsibility of the user.
- Risk of electrical shock; do not use in an environment with gas, combustible or explosive materials, or hot objects.
- Do not open, repair or modify.
- Use only under the recommended voltage and frequency requirements.
- Do not look directly at the light, as this will result in dazzling.
- Minimum distance from lighted objects 0.1 m.
- The specification in this manual is based on standard lab testing, different environments may influence the data.
- **California Proposition 65 Warning:** This product contains chemicals known to the State of California to cause cancer, and birth defects or other reproductive harm.

For more information, please visit www.P65Warnings.ca.gov

FEATURE



SAE
CLASS 1



CISPR 25
CLASS 3



TITLE 13
CA. APPROVED



ECE R10
APPROVED



MIL SPEC
VIBRATION RATED

FEATURES


- Tough diecast aluminium housing and virtually unbreakable polycarbonate lens.
- Ambient light sensor for Day/Night mode.
- 9-80V multi-volt DC input to suit most applications.

- Flash synchronisation of multiple beacons.
- Virtually unbreakable polycarbonate lens and base.
- SAE and EGE approved.

INSTALLATION

1. Prepare a suitable area on the vehicle's surface by wiping it clean to prevent scratching.
2. Drill a 10mm (3/8") hole into the surface for the wires to exit through for connection to a power source.
Alternatively, the wires can be directed through the side of lamp's base for connection to a power source.
3. Using the lamp as a template, drill four 4.7mm (6/16 11) holes for fitment and secure to the surface using the supplied mounting bolts. A mounting pad is included and can be installed between the surface and the lamp.
4. Route the wires as planned in step 2. Connect the red(+) wire to 9-80VDC and the black(-) wire to ground.

Test.



WIRING

RED:	To 9-80V DC(+)
BLACK:	To chassis/ ground(-)
YELLOW:	Flash pattern selection
WHITE:	Synchronisation
GREY:	Ambient light sensor override(+)

WIRING DIAGRAM

LED	8x5W	Width	125mm / 4.92"
Housing Material	Aluminium Base	Height	91mm / 3.58"
Lens Material	Polycarbonate	Depth	125mm / 4.92"
Mounting	4-Bolt Flange	PCD	111.5mm / 4.39"
Operating Temp.	-22°F – 176°F (-30°C – + 80°C)	Shock/Vibration	ISO 16750-3, MIL-STD-810G
Voltage	9-80V DC	Approvals	CE, ROHS, REACH
Wattage (W)	40W	IP Rating	IP-67, IP-69k
Amperage	2A@12V	ECE Ratings	ECE R65, ECE R10
Weight	0.6kg / 1.31bs	EMC Approval	CISPR25 Class 3
		SAE Compliance	J845 Class 1, W3-1

WARRANTY TERMS & CONDITIONS:

1. Warranty items will be replaced or repaired to working condition and returned without cosmetic alterations.
2. A proof of purchase is required to validate all warranty claims. The warranty period is valid starting from the original date of purchase.
3. All products must have been purchased through a Vision X Authorized Dealer/Reseller to be eligible for warranty.
4. Damage resulting from any improper installation, accident, abuse, neglect or normal wear are not covered under warranty.
5. Any product used in mining applications is warranted for one year only.
6. Actions which void the warranty include:
 - a. Opening of the lighting fixture
 - b. Cutting any connectors or cords
 - c. Broken Glass
 - d. Damage caused by physical abuse
 - e. Lights operated in environments outside their stated specifications•
7. All customer warranties should be handled through the Dealer/Reseller the product was originally purchased from. The customer is responsible for delivery to the Vision X Returns in Auburn, Washington.

8. If a product is deemed not covered under warranty, customer will be responsible for the return shipping charges.
9. Items not covered under warranty can be repaired at the customer's expense for parts and labor, at the discretion of Vision X Lighting, who will provide an estimated repair cost before proceeding with the repair.

CUSTOMER SUPPORT

Distributed by:
Vision X Lighting
1601 Boundary Blvd.
Auburn WA, 98001 USA
Made in China
For more info visit
www.visionxusa.com



Documents / Resources



[Vision X Tremor XD High Output LED Beacon](#) [pdf] Instruction Manual
TREM-85250, Tremor XD High Output LED Beacon, Tremor XD, Tremor XD LED Beacon, High Output LED Beacon, Output LED Beacon, Output Beacon, LED Beacon, Beacon