



# WIZARD 4MP 4 in 1 IR Bullet Camera Instructions

[Home](#) » [WIZARD](#) » WIZARD 4MP 4 in 1 IR Bullet Camera Instructions

## WIZARD 4MP 4 in 1 IR Bullet Camera Instructions



|              |                               |
|--------------|-------------------------------|
| Model No.    | ON-FB347IZ-V4                 |
| Image Device | 1/3" 4MP CMOS(OV4689+FH8538M) |

|                       |                                                                |
|-----------------------|----------------------------------------------------------------|
| Horizontal Resolution | 4.0 Mega Pixels                                                |
| Effective Pixels      | 2688H x 1520V                                                  |
| Electronic Shutter    | 1/25(1/30)~1/5,0000sec                                         |
| Image System          | PAL/ NTSC                                                      |
| Synchronization       | Internal                                                       |
| S/N                   | More than 50dB (AGC off)                                       |
| Mini. Illumination    | 0.05Lux(F1.2,AGC ON),0 Lux with IR ON                          |
| Video Standard        | AHD                                                            |
| Video Output          | AHD/TVI/CVI/CVBS                                               |
| <b>Menu</b>           |                                                                |
| OSD Menu              | OSD Cable optional / UTC Coaxial Control (via DVR) s<br>upport |
| Noise Reduction       | 2D_DNR                                                         |
| BLC                   | OFF/HSBLC/BLC                                                  |
| AGC                   | 0-15 Level                                                     |
| White Balance         | ATW/AWC-SET/Indoor/Outdoor/Manual/AWB                          |

|                     |                                  |
|---------------------|----------------------------------|
| Flicker less        | PAL: 25Hz / NTSC: 30Hz           |
| DEFOG               | OFF/AUTO                         |
| D-WDR               | ON/OFF                           |
| SENSE-UP            | ON/OFF                           |
| Motion Detection    | OFF/ON(4 AREAS)                  |
| <b>Feature</b>      |                                  |
| Max. IR LEDs Length | 4pcs Array Leds , 40M , Smart IR |
| Day/Night           | IR Cut Filter Auto Switch        |
| Focal Length        | Lens 3.6mm Mega Pixel Lens       |
| Mount Type          | M14                              |
| <b>General</b>      |                                  |
| Power Supply        | DC12V±10%                        |
| Working Environment | -10°C +50°C, Humidity 10%-90%    |
| External Protection | IP66 Grade (waterproof IP66)     |
| Power Consumption   | 450mA                            |

|                       |                                  |
|-----------------------|----------------------------------|
| Transmission Distance | Over 500m via 75-3 coaxial cable |
| Ingress Protection    | Metal Bullet                     |

**Contents** [ [hide](#)

[1 Documents / Resources](#)

[2 Related Posts](#)

**Documents / Resources**

|                                                                                    |                                                                                                              |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|
|  | <p><a href="#">WIZARD 4MP 4 in 1 IR Bullet Camera</a> [pdf] Instructions<br/>4MP 4 in 1 IR Bullet Camera</p> |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|