



# Wireless Keyboard FOR IOS/Windows/ Android

BK3231

1

## User Manual

### Specifications

Connection via:	Bluetooth V3.0
Dimensions	285.5x120.5x18mm
Operating Range	Up to 10 meters
Pairing Name	Bluetooth Keyboard
Power Supply	2x AAA batteries (Not included)
Key Life	3 Million clicks

### Getting Started

#### 1.Buttons

- On/Off slider switch: Turn the power on or off.
- Bluetooth connect button: When the unit is powered On, press the **[connect]** button, the keyboard is now ready to be connect to your device (e.g. computer, smartphone, tablet, game console, etc).

#### 2.Led Display

The  icon will flash blue (±3 min. long) after pressing the "connect" button until a BT connection is established. It disappears when connected.

**Low power:** The blue light will rapidly flash when the battery is weak and batteries need be replaced.

**Power:** The blue light will light up ± 4 seconds when the unit is turned on.

#### 3. System requirements

- iPad, iPhone – All versions
- Bluetooth-enabled PCs or Laptops with Windows XP ~10
- Bluetooth-enabled iMac / Macbooks with Mac OS X 10.2.8 or above (note that some exceptions may apply. This keyboard may not be compatible with the Mac mini.
- Smartphones or tablets with Android 3.0 and above (with Bluetooth HID profile)
- Windows Mobile 5.0 and above

#### 4. Pairing keyboard methods

##### Pairing with an iPad/ iPhone

- Step 1: On the keyboard, slide the power button to on. The blue status light will illumination for 4 seconds and then turn off to save power. Note: your keyboard is still on.
- Step 2: Press the [connect] button, the [Bluetooth] indicator light will be blinking blue.
- Step 3: On the iPad/iPhone, select: Setting- General- Bluetooth- On.
- Step 4: The iPad/iPhone will display "Bluetooth keyboard" as an available device.
- Step 5: Select "Bluetooth keyboard"; the iPad/iPhone will display a code.
- Step 6: Type the code on the keyboard and press enter; keyboard will now be paired to the iPad/iPhone.

##### Pairing with Tablets , Smartphones, Laptop and Desktop computers, etc.

- Step 1: On the keyboard, slide the power button to on. The blue status light will illumination for 4 seconds and then turn off to save power. Note: your keyboard is still on.
- Step 2: Press the [connect] button, the [Bluetooth] indicator light will be blinking blue.
- Step 3: Go to your "settings" screen on your tablet, laptop, smartphone or other Bluetooth –enabled devices and go to the Bluetooth setting menu and activate its Bluetooth function and search for the keyboard.
- Step 4: Once the Bluetooth keyboard has been found, select its name to connect.
- Step 5: Enter the password code as displayed on the screen.
- Step 6: Once the Bluetooth keyboard has successfully been connected to your device, the Bluetooth indicator will turn off.

2















### Note:

- Only one device can be actively paired at one time.
- After pairing for the first time, your device will connect to the keyboard automatically when switching on the keyboard.
- In case of connection failure, delete the pairing record from your device, and try the above pairing procedures again.

### Power Saving Mode

The keyboard will enter into the sleep mode after being idle for 15 minutes. To activate the keyboard, press any key and wait 3 seconds.

### 5. Function Keys

Keys	Fn on Android	For All w/o Fn	Fn on Windows	Fn on iOS
	Home	ESC	Home	Home
	Return		Return	Brightness down
	Email		Outlook Mail	Brightness up
	Menu		Virtual Keyboard	Virtual Keyboard
	Media player		Screen Capture	Screen Capture
	Search	Search	Search	Search
	Language exchange	Language exchange	Language exchange	Language exchange
	Previous track	Previous track	Previous track	Previous track
	Play/pause	Play/pause	Play/pause	Play/pause
	Next track	Next track	Next track	Next track
	Mute	Mute	Mute	Mute
	Volume down	Volume down	Volume down	Volume down
	Volume up	Volume up	Volume up	Volume up
	Screen Lock	Screen Lock	Screen Lock	Screen Lock


### Note:

Press Fn and Q (iOS), W (Android) or E (Windows) keys together to shift between Android, Windows or iOS systems after connected successfully with a corresponding device. Otherwise the keyboard's function key will only be partial valid.

3

### Important guidelines:

- Read the user manual carefully and keep it for reverence.
- Use this product only as described in this user manual.
- If the instructions are not followed, the manufacturer may not be held responsible for damage that may result from incorrect use of this product.
- Let repairs be done by a qualified mechanic. Never try to repair the product yourself.
- Do not place heavy objects on the keyboard cover.
- Keep the product away from water, oil, chemicals, and organic liquids.
- Clean the product by lightly rubbing it with a slightly damp cloth.



**GUIDELINES FOR PROTECTION OF THE ENVIRONMENT**  
(WEEE, directive on waste of electrical and electronic equipment)

Your product is designed and manufactured with high quality materials and components which can be recycled and reused. This appliance should **not** be put into the domestic garbage at the end of its durability, but must be offered at a central point for the recycling of electric and electronic domestic appliances. This crossed-out wheelee bin symbol on the appliance, instruction manual and packaging puts your attention to this important issue.

The materials used in this appliance can be recycled. By recycling used domestic appliances you contribute an important push to the protection of our environment. Ask your local authorities for information regarding the point of recollection.

**Battery/batteries disposal**

Check the local regulations concerning the disposal and processing of batteries or contact the town hall or your waste disposal company or with the store where you purchased the product.

The battery/batteries should never be disposed of in the normal garbage waste. Use a battery processing authority in your area or community, when and where available.

### Disclaimer

Apple™ is a trademark of Apple Corporation.  
Android™ is a trademark of Google Inc.  
Windows™ is a trademark of Microsoft Corporation.  
All images, logo's, brand-and product names used in this documentation are used as an example and illustrative indication only and all images, logo's, brand-and product names are trademarks or registered trademarks and proprietary of their respective companies and owners.  
Product specification can be changed without notice

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
  - Increase the separation between the equipment and receiver.
  - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
  - Consult the dealer or an experienced radio/TV technician for help
- Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
- (1) this device may not cause harmful interference, and  
(2) this device must accept any interference received, including interference that may cause undesired operation.

4