



ZEBRA MotionWorks Enterprise ZLA Software User Guide

[Home](#) » [ZEBRA](#) » ZEBRA MotionWorks Enterprise ZLA Software User Guide 

Contents

- 1 ZEBRA MotionWorks Enterprise ZLA Software
- 2 MWE 2.0.5.0 Release Notes
- 3 Introduction
- 4 What is New
- 5 CLAS ATR Alerts
- 6 New ZLA Software
- 7 Pagination in History Reports
- 8 API Support for Historical Data
- 9 New Blink Since Filter
- 10 New First Blink Time Column
- 11 New Mobile Application Logs Report
- 12 Eliminated log4j 1.2.17 Vulnerability
- 13 New Camel Version
- 14 Z-Lock Functionality
- 15 New Technology Field in Tag Blink Messages
- 16 Bug Fixes
- 17 Known Issues
- 18 Requirements
- 19 Installation
- 20 References
- 21 Specifications
- 22 Frequently Asked Questions (FAQ)
 - 22.1 Q: Can I directly upgrade to MWE 2.0.5 from MWE 1.4.x?
 - 22.2 Q: What should I do if I encounter issues with Camel route files after upgrading to MWE 2.0.5?
- 23 Documents / Resources
 - 23.1 References
- 24 Related Posts

ZEBRA MotionWorks Enterprise ZLA Software

USER GUIDE

MWE 2.0.5.0 Release Notes

Introduction

Product: MotionWorks Enterprise (MWE) Release Number: 2.0.5

Release Date: January 2024

MWE 2.0.5 is the latest release of the MWE 2.0.x series. It includes all the functionality of the MWE 2.0.0 – 2.0.4.1 releases in addition to new functionality and bug fixes.

The MWE 2.0.5 installation package is used to perform a fresh installation or to upgrade from the previous MWE 2.0.x release. If upgrading from MWE 1.4.x, the upgrade path is MWE 1.4.x > MWE 2.0.4.1 > 2.0.5. Refer to the MWE 2.0 Installation Guide for detailed installation and upgrade instructions.

See **What is New** for brief descriptions of the new functionality, and refer to the MWE 2.0.x release notes for details on the functionality included in previous releases.

NOTE: MWE 2.0.5 includes a new version of the Camel interface (version 3.21.0). This new version requires a slightly different syntax in the Camel route files than the Camel version in previous MWE releases. If using Camel in an existing MWE deployment, DO NOT upgrade to 2.0.5 until Zebra Product Support reviews the existing Camel route files, as upgrading may break communication between Camel and external systems.

More details on the MWE 2.0 functionality can be found in the MWE 2.0 Installation Guide, the MWE 2.0 Configuration Guide, the MWE 2.0 User Guide, and the MWE 2.0 Device Manager User Guide.

What is New

This section describes the new functionality implemented in this release.

CLAS ATR Alerts

The Zebra CLAS software processes RFID tag blinks and calculates the x,y coordinates of the tags. A CLAS server forwards this information to an MWE server via a ZLA (Zebra Location Appliance), which subscribes to CLAS to pull the data. This has been supported in previous MWE releases. Starting with MWE 2.0.5, in addition to tag blink data, MWE also pulls from the CLAS server and displays ATR related alerts. See the **System Alert Settings** report in the MWE web client to review the ATR alerts that MWE reports.

New ZLA Software

ZLA software version 2.0.5-1 is included with MWE 2.0.5, and is required for supporting CLAS ATR alerts. Though not required by the ZLA 2.0.5-1 software, we recommend upgrading the **nodejs** version on the ZLA to the following:

ZLA Operating System	Recommended nodejs Version
CentOS 7.9	17.9.0 or 17.9.1
Red Hat 7.9	17.9.0 or 17.9.1
Red Hat 8.x	18.x.x
Ubuntu 22	18.x.x

ZEBRA and the stylized Zebra head are trademarks of Zebra Technologies Corp., registered in many jurisdictions worldwide. All other trademarks are the property of their respective owners. © 2024 Zebra Technologies Corp. and/or

its affiliates. All rights reserved. | zebra.com P1128233-03EN Rev A

Refer to the MWE 2.0 Installation Guide (rev. 1.12 or higher) for instructions on installing or upgrading nodejs on the ZLA.

Pagination in History Reports

The previous MWE 2.0.4.1 release supports pagination for the **Tags** and **Resources** reports in the MWE web client; that is, report data is displayed on several pages with a maximum number of records per page configured by the user. MWE 2.0.5 adds pagination support for the following reports:

- Tags Blink History
- Call History
- Resource Zone Correlation History

NOTE: A future MWE release will include pagination for the System Alert History and Resource Event History reports.

API Support for Historical Data

The API calls in previous MWE releases retrieve data related to the current state and configuration of the system. The MWE API in MWE 2.0.5 also supports calls to retrieve the same historical data displayed in the following reports:

- Tags Blink History
- Resource Event History
- System Alert History
- Call History

- Resource Zone Correlation History

New Blink Since Filter

The MWE web client **Resources** report includes a new **Blink Since** filter in the filter column. The default value is ALL, which displays all data regardless of the value in the **Blink Timestamp** column which indicates when the resources last blinked. This new filter allows specifying a particular date and time so the report displays only those resources that have blinked since.

NOTE: The Blink Since filter has a dependency on the Location Snapshot Time filter in the same report. The Blink Since filter is enabled when Location Snapshot Time = Now, but is disabled when Location Snapshot Time = Custom. Refer to the MWE 2.0.4.1 release notes for an explanation of the Location Snapshot Time filter.

New First Blink Time Column

The MWE web client **Tags** report includes a new column for **First Blink Time**. This column displays for each tag the timestamp for the first blink received by MWE.

New Mobile Application Logs Report

A new companion MWE Mobile application runs on Zebra Android handheld devices and computers. An MWE Mobile application setting sends application logs to the MWE servers. The new **Infrastructure > Mobile Application Logs** report in the MWE web client displays an entry for every set of logs sent by the application. Clicking the link in the **Download** column in this report downloads the log set to the Windows machine running the browser.

Eliminated log4j 1.2.17 Vulnerability

The MWE services **kelasticsvc** and **wso2** were discovered to have the **log4j** 1.2.17 vulnerability. **log4j**

has been replaced with a different component to eliminate the vulnerability.

New Camel Version

A new Camel version (3.21.0) included in MWE 2.0.5 supports additional functionality, including support for the FIPS security protocol in the AWS cloud.

NOTE: This new Camel version requires a slightly different syntax in the Camel route files than the Camel version in previous MWE releases. If using Camel in an existing MWE deployment, DO NOT upgrade to 2.0.5 until Zebra Product Support reviews the existing Camel route files, as upgrading may break communication between Camel and external systems.

Z-Lock Functionality

The MWE 2.0.5 release includes the Z-Lock functionality available in the Zebra legacy software VSS (Visibility Server Software). Useful in multi-story buildings where tag blinks can be detected by readers or sensors in the floors above and below, this feature places a Z-lock WherePort device at each floor entry point. When a tag is hit by the magnetic field of this device, the tag remains locked on that floor, even if the tag blinks are located by readers or WherePorts on other floors. A WherePort is configured as a Z-lock WherePort in the System Builder configuration tool. This is also referred to as the map-lock functionality as it can lock tags to specific maps regardless of whether the maps correspond to floors of a multi-story building. Refer to the MWE 2.0 Configuration Guide, rev. 1.06 or higher, for details.

New Technology Field in Tag Blink Messages

The **Source** field in MWE tag blink events was previously used for both tag product names and tag technologies. MWE 2.0.5 includes a new **Technology** field that specifies the tag technology, and can include the following values:

Source (Zebra Product Name for tag)	Technology (Technology underlying the tag)
WhereNet	ISO24730, BLE, WherePort, GPS
Dart	UWB
MPACT	BLE
EPC	RFID
	Unknown (if technology cannot be determined)

The **Source** and **Technology** fields also appear in the MWE web client **Tags** report.

Bug Fixes

- The environment variable **RESVC_AUTOASSOC_EPCTAG** in **/data/mwe/.env** enables/disables automatic association of resource IDs to EPC tag IDs. The default value is **false** (disabled); setting the value to **true** enables this. MWE upgrade was resetting this variable to **false**. The installation/upgrade script has been modified so the existing value of this variable does not change during MWE upgrade.
- The **Dashboard > Resources** report in the MWE web client was displaying an incorrect number of unassigned tags. This issue has been corrected in MWE 2.0.5.
- In previous MWE 2.0.x releases, zooming into some maps in the MWE web client suddenly shifts the map, causing the coordinates of a point on the map to change, although usually only slightly. This issue has been fixed in 2.0.5.
- In MWE 2.0.4 and earlier 2.0.x releases, the MWE web client reports swapped Latitude and Longitude values. This issue existed only in the UI, not in MWE events or API calls. This issue has been corrected in MWE 2.0.5.
- In earlier releases of MWE, resource ID values in the GPS related columns (fields) were not cleared when associating the resource ID with a new tag ID. These values are now cleared in MWE 2.0.5.

Known Issues

In the **Device Manager** report > **Edit Device** page, if you select **Operation Mode = Portal**, you must provide values for the **GPI Port** and **Signal** fields before attempting to publish the configuration to the reader, otherwise the publish operation fails. The next MWE release will display a message and block the **Publish** operation until the

required values are entered.

Requirements

Refer to the MWE 2.0 Installation Guide (rev. 1.12 or higher) for software and hardware requirements for installing MWE 2.0.5 software.

The MWE 2.0.5 installation package can be used to perform a fresh installation or to upgrade from previous MWE 2.0.x releases. If upgrading from MWE 1.4.x, the upgrade path is MWE 1.4.x > MWE

2.0.4.1 > MWE 2.0.5.

For MWE 2.0.5 deployments that require a ZLA, use ZLA software 2.0.5-1 or higher.

Firmware version 3.21.23 or higher is recommended for FX RFID readers added to MWE 2.0.5 via Device Manager. Verify the required upgrade path for FX RFID reader firmware in the firmware release notes (for example, 3.10.30 > 3.21.21 > 3.21.23). Consult with Zebra on the latest FX firmware to use with MWE 2.0.5.

Installation

Refer to the MWE 2.0 Installation Guide (rev. 1.12 or higher) and the MWE 2.0 Configuration Guide (rev. 1.06 or higher) for MWE installation and configuration instructions.

References

Other useful reference documents are as follows:

- MWE 2.0 Installation Guide, rev. 1.12 or higher
- MWE 2.0 Configuration Guide, rev. 1.06 or higher
- MWE 2.0 User Guide, rev. 1.02 or higher
- MWE 2.0 Device Manager User Guide, rev. 1.01 or higher

Specifications

- Product: MotionWorks Enterprise (MWE)
- Release Number: 2.0.5
- Release Date: January 2024
- Camel Interface Version: 3.21.0
- ZLA Software Version: 2.0.5-1
- Node.js Version: Recommended versions provided

Frequently Asked Questions (FAQ)

Q: Can I directly upgrade to MWE 2.0.5 from MWE 1.4.x?

A: If upgrading from MWE 1.4.x, follow the upgrade path MWE 1.4.x > MWE 2.0.4.1 > 2.0.5 for a smooth transition.

A: Contact Zebra Product Support to review and address any compatibility issues with existing Camel route files to prevent communication disruptions.

The image shows a PDF document titled "ZEBRA MotionWorks Enterprise ZLA Software [pdf] User Guide". The document is a user guide for the Zebra MotionWorks Enterprise ZLA Software. The page displays a table of contents with sections such as "Introduction", "What's New", and "New ZLA Software". The "What's New" section lists updates for the 2024.1 release, including new features and improvements. The "New ZLA Software" section provides information about the software's architecture and components. The document is presented in a clean, professional layout with a white background and black text.

- [User Manual](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.