

LINEAR TECHNOLOGY LTC2951-2 Demonstration Circuit User Guide


[Home](#) » [LINEAR TECHNOLOGY](#) » LINEAR TECHNOLOGY LTC2951-2 Demonstration Circuit User Guide 

Contents

- [1 LINEAR TECHNOLOGY LTC2951-2 Demonstration Circuit](#)
- [2 DESCRIPTION](#)
- [3 QUICK START PROCEDURE](#)
- [4 OPERATING PRINCIPLES](#)
- [5 PUSH BUTTON ON/OFF CONTROLLER](#)
- [6 Documents / Resources](#)
- [7 Related Posts](#)



LINEAR TECHNOLOGY LTC2951-2 Demonstration Circuit



DESCRIPTION

Demonstration Circuits 826B-A and 826B-B feature the LTC2950-2 and the LTC2951-2 respectively, which are low power, wide input voltage range, Push Button On/Off Controllers. A push button switch shorts the /PB pin to ground which in turn sets the /EN pin low (see Note 1). Shorting /PB to ground a second time subsequently resets the /EN pin high. The /EN pin is used to connect to a DC/DC converter shutdown to control the turn on and off of the circuit, simulated with a green LED on the DC826B-A/DC826B-B.

JP1 and JP2 on the DC826B-A provide the selection of timing options for the /PB on and off times. For the DC826B-B, JP1 selects /KILL times while JP2 selects off times. JP3 ties and unties /KILL to /INT for immediate or delayed turn off. The /INT status is shown with a red LED. DC826B-A/DC826B-B accepts an input voltage range of 2.7V to 26.4V or a 9V battery for portable demonstration and evaluation.

Design files for this circuit board are available. Call the LTC factory.

Note 1: The inversion of /EN of the LTC2950-2/LTC2951-2 is found in the LTC2950-1/LTC2951-1. Table 1 provides an IC selection guide.

QUICK START PROCEDURE

Demonstration circuit 826B-A/826B-B is easy to set up to evaluate the performance of the LTC2950-2/LTC2951-2:

1. Place jumpers in the following positions:

- JP1 0.033uF
- JP2 0.033uF

- JP3 UNTIE

2. Connect the input power supply of 2.7V to 26.4V across VIN and GND or a 9V battery to the battery connector.
3. Push and hold the push button once to turn on the green LED.
4. Push and hold the push button again to turn off the green LED.

Table 1. LTC2950/2951 Selection Guide (typical timing values, Cap. Adjust = 212ms on DC826B-A/ DC826B-B)

PART	ENABLE	ONT	OFFT	KILLT	DEMO BOARD
LTC2950-1	EN	32ms + Cap. Adjust*	32ms + Cap. Adjust*	1000ms	N/A
LTC2950-2	/EN	32ms + Cap. Adjust*	32ms + Cap. Adjust*	1000ms	DC826B-A
LTC2951-1	EN	128ms	32ms + Cap. Adjust*	128ms + Cap. Adjust*	N/A
LTC2951-2	/EN	128ms	32ms + Cap. Adjust*	128ms + Cap. Adjust*	DC826B-B

The additional Cap. Adjust time is selected by an external capacitor. The DC826B-A and DC826B-B adjust times have been pre-selected with a 0.033uF capacitor to provide an additional 212ms. The additional time is calculated with the following equations as shown in the LTC2950/LTC2951 data sheets:

- $CONT = 1.56E-4 [\mu F/ms] \cdot (t_{ONT} - 1ms)$
- $COFFT = 1.56E-4 [\mu F/ms] \cdot (t_{OFFT} - 1ms)$
- $CKILLT = 1.56E-4 [\mu F/ms] \cdot (t_{KILL, OFF DELAY, ADDITIONAL} - 1ms)$

OPERATING PRINCIPLES

The duration that /PB must be shorted to ground in order to turn on/off the DC/DC converter is independently programmed (LTC2950-2) by two external capacitors C1 and C2 and selected on the DC826B-A with jumper JP1 and JP2. The status of the /EN pin, and simulation of the turn on/off of a DC/DC converter, is displayed with green LED D2 on the board.

Figure 1 shows how the /EN is connected to the /SHDN pin of a DC/DC converter and how /INT and /KILL interfaces with a μP or μC . An internal 500ms timer blanks (ignores) the /KILL signal during system power up. This allows sufficient time for the DC/DC converter and a μP to perform power up tasks. During turn off, a power down timer provides a delay (LTC2950-2: 1000ms, LTC2951-2: adjustable) from interrupting the μP (/INT=low) to turning off the DC/DC converter (/EN=high). This delay gives the μP time to perform power down and housekeeping tasks. On the DC826B-B, JP1 selects the power down timer, while JP2 is used to adjust the turn off /PB duration. The red LED D1 shows the state of the /INT pin. A μP can turn off the converter with no delay by asserting /KILL low. By tying /KILL to /INT through JP3, /KILL is forced low during the /INT blanking time and thus force a turn off.

The RC (RRPP and CRPP) at VIN on the DC826 provides reverse polarity protection to the LTC2950-2/LTC2951-2. If power is connected in an application such that the polarities are ensured to be in the correct configuration, this RC may be removed from the circuit.

An additional RC (RF and CF), located at the /PB pin, acts as a filter and used in an application where the switch is located far from the LTC2950-2/LTC2951-2. In such a case, the RC would be placed next to the switch rather than the part. If the switch is located near the LTC2950-2/LTC2951-2, then the RC may be removed from the circuit.

An LDO (U2) is used on the DC826 to provide a pull-up voltage of 2.6V which is well below the absolute maximum on the /INT, /EN, and /KILL pins for the full range of input voltage of 2.7V to 26.4V. In an application, pull these

pins up to a voltage no higher than their rated absolute maximum shown in the data sheet. Optional zener diodes (D3-D5) can be used if the pull-up voltage exceeds the rated absolute maximum. (If the interface pins on the DC826B-A

/DC826B-B will be pulled up to an external supply, LEDs D1 and D2 should be removed.)





Figure 1. DC826B-A/DC826B-B Example Setup

PUSH BUTTON ON/OFF CONTROLLER



REVISION HISTORY				
ECO	REV	DESCRIPTION	DATE	APPROVED
	0	1st PROTOTYPE	<DATE>	<APPROVED>
	B	SILKSCREEN CHANGE & U2 CHANGE TO LT3014BES5	9/13/06	DILIAN REYES

APPROVALS		LINEAR TECHNOLOGY CORPORATION 1630 McCARTHY BLVD www.linear.com MILPITAS, CA. 95035 LTC Confidential - (408) 432-1900 For Customer Use Only (408) 434-0507 (FAX)	
DRAWN: Rudy Bautista		Title: On/Off Controller Size: Document Number: Demo Circuit 826B Rev: 0	
ENGINEER: Dilian Reyes			
APPROVED:			
CHECKED:			
DCxxxA_00.PCB	xxxA_x.DSN	Date: Thursday, April 23, 2009	Sheet 1 of 1

C:\ORCADWIN\CAPTURE\ARCHIVE\826A1826B REVO.DSN

This circuit is proprietary to Linear Technology and supplied for use with Linear Technology parts. Customer Noticetlinear Technology has made a best effort to design a circuit that meets customer-supplied specifications; however, it remains the customers responsibility to verify proper and reliable operation in the actual application, Component substitution and printed circuit board layout may significantly affect circuit performance or reliability. Contact Linear Applications Engineering for assistance.

Documents / Resources

QUICK START GUIDE FOR DEMONSTRATION CIRCUIT BOARD

REVISION 1.0

DATE 01/15/2015

DESCRIPTION

This document provides a quick start guide for the LTC2951-2 Demonstration Circuit Board. It includes information on the board's components, connections, and operation. The board is designed to demonstrate the LTC2951-2 IC, which is a precision, low-power, single-supply, 2-channel, 24-bit digital-to-analog converter (DAC).

QUICK START PROCEDURE

1. Connect the board to a power source. The board is powered by a 5V supply.

2. Set the DAC output voltage using the DAC control register. The DAC output voltage is set by writing a value to the DAC control register. The DAC output voltage is set by writing a value to the DAC control register.

3. Measure the DAC output voltage using a multimeter. The DAC output voltage is measured at the DAC output pin.

4. Repeat steps 2 and 3 for different DAC control register values.

LINEAR TECHNOLOGY LTC2951-2 Demonstration Circuit [pdf] User Guide

LTC2950-2, LTC2951-2, Demonstration Circuit, LTC2951-2 Demonstration Circuit, Circuit

Manuals+.com