



Mircom i3 Series Reversing Relay Synchronization Module Owner's Manual

[Home](#) » [Mircom](#) » Mircom i3 Series Reversing Relay Synchronization Module Owner's Manual 

Contents

- [1 Mircom i3 Series Reversing Relay Synchronization Module](#)
- [2 Description](#)
- [3 Features](#)
- [4 Engineering Specifications](#)
- [5 Electrical Specifications](#)
- [6 Physical Specifications](#)
- [7 Ordering Information](#)
- [8 Documents / Resources](#)
 - [8.1 References](#)
- [9 Related Posts](#)



Mircom i3 Series Reversing Relay Synchronization Module



Description

The CRRS-MODA reversing relay/synchronization module enhances the operation of 2 and 4-wire i3 series detectors equipped with a sounder.

Installation Ease

The module includes a Velcro attachment for easy installation into the fire alarm control panel cabinet. A quick-connect harness and colour-coded wires simplify connections.

Intelligence

The module's design is flexible to accommodate virtually any application. The CRRS-MODA is compatible with both 2 and 4-wire i3 series detectors operating over 12V and 24V systems. The module can be used with either bell/alarm, alarm relay, or NAC outputs, and its field-selectable switch accommodates both coded and continuous alarm signals.

Instant Inspection

To meet fire alarm requirements, the CRRS-MODA activates all i3 sounders on a loop when one alarms. Additionally, the module synchronizes the output of the i3 sounders, regardless of whether the panel's alarm signal is continuous or coded, to ensure a clear alarm signal.

Features

- Compatible with 2- and 4-wire i3 detectors equipped with a sounder
- Activates all i3 sounders on a loop when one alarms
- Synchronizes all i3 sounders on the loop for a clear alarm signal
- Can be used with bell/alarm, alarm relay, or NAC outputs
- Includes a field-selectable switch to accommodate both coded and continuous alarm signals

- Allows i3 detector silencing from the panel or keypad
- Operates on 12- and 24-volt systems
- Quick-connect harness and color coded wires facilitate connections

Engineering Specifications

Reversing relay/synchronization module shall be a an i3 Series model number CRRS-MODA, listed to Underwriters Laboratories as a smoke detector accessory. The module shall allow all 2-wire and 4-wire i3 Series detectors equipped with a sounder on a loop to sound when one alarms. The module shall provide a switch to toggle between coded mode and continuous mode. When in coded mode, the module shall synchronize the i3 sounders on the loop to mirror the input signal. When in continuous mode, the module shall synchronize the i3 sounders on the loop to the ANSI S3.41 temporal coded pattern. In either coded or continuous modes, the module shall permit sounders to be silenced at the panel. The module shall operate between 8.5 and 35 VDC, and shall provide 18 AWG stranded, tinned conductors connected to a quick-connect harness.

Electrical Specifications

Operating Voltage

- Nominal: 12/24 V
- Min: 8.5 V
- Max: 35 V

Avg. Operating Current

- 25 mA

Relay Contact Rating

- 2 A @ 35 VDC

Physical Specifications

Operating Temperature Range

- 32°F–131°F (0°C–55°C)

Operating Humidity Range

- 5 to 85% non-condensing

Wire Connections

- 18 AWG stranded, tinned, 16" long

Dimensions

Wire System Triggered from Alarm/Bell Circuit



U.S.A.

4575 Witmer Industrial Estates Niagara Falls, NY 14305
Toll Free: (888) 660-4655 Fax Toll Free: (888) 660-4113

Canada

25 Interchange Way Vaughan, Ontario L4K 5W3 Telephone: (905) 660-4655 Fax: (905) 660-4113
Web page: <http://www.mircom.com>
Email: mail@mircom.com

Documents / Resources

	<p>Mircom i3 Series Reversing Relay Synchronization Module [pdf] Owner's Manual i3 Series Reversing Relay Synchronization Module, i3 Series, Reversing Relay Synchronization Module, Synchronization Module</p>
	<p>Mircom i3 SERIES Reversing Relay-Synchronization Module [pdf] Owner's Manual i3 SERIES Reversing Relay-Synchronization Module, i3 SERIES, Reversing Relay-Synchronization Module, Relay-Synchronization Module, Synchronization Module, Module</p>

References

-  [Fire Alarm Resources | Download fire alarm documents](#)
-  [Mircom - Smart Buildings. Smarter Solutions.](#)