

A3 WISP settings

Contents

- [1 A3 WISP settings](#)
- [2 Diagram](#)
- [3 Preparation](#)
- [4 Set up steps](#)
- [5 DOWNLOAD](#)
- [6 Related Posts](#)

A3 WISP settings

It is suitable for: **A3**

Diagram

5bd6d0d90eaeb.png

Preparation

- Before configuration, make sure that both A Router and B Router are powered on.
- make sure you know the SSID and password for A router
- Connect your computer to the same network of router A and B.
- Set both Router A and B should to the same band 2.4G or 5G.

Feature

1. B router can use PPPOE, static IP. DHCP function.
2. WISP can build its own base stations in public places such as airports, hotels, cafes, teahouses and other places, providing wireless Internet access services.

Set up steps

STEP-1: B-router wireless setting

You need to enter the settings page of the router B, then follow the steps illustrated.

① In the navigation bar, select **Basic Setup**-> ② **Wireless Setup**-> ③ Select **2.4GHz Basic network**

④ Setting **Network SSID, channel, Auth, password**

⑤ Click the **Apply** button

Repeat the steps 3 through 5 to complete the 5GHz Wi-Fi configuration

5bd6d200cd8c4.png

STEP-2: B-Router WISP setting

Enter the settings page of the router B, then follow the steps illustrated.

① In the navigation bar, select **Advanced Setup**-> ② **Wireless**-> ③ **Wireless Multibridge**

④ For **Wireless Multibridge**, select **2.4GHz**, if you want to use **5GHz** for **WISP**, choose **5GHz**.

⑤ In **Mode list**, select **Wireless Wan**.

⑥ Click the **Ap Scan** button

⑦ Click AP you need repeater, **check SSID**

⑧ Enter the password for router A (**You can check the box next to check the password you entered**)

⑨ Click the **Apply** button, Wait for the configuration to finish.

5bd6d20882339.png

STEP-3: Check whether the B route IP address conflicts with route A. Option

If there is a conflict between the LAN IP addresses of the two routes, you need to check the Change LAN IP address automatically. Then click the Apply button and the router restarts. We can obtain the new IP address and login B route setting with the new IP address page.

5bd6d2382ff30.png

STEP-4: B Router position display

Move the Router B to a different location for a best Wi-Fi access.

5bd6d24f0f972.png

DOWNLOAD

A3 WISP settings – [[Download PDF](#)]

