



8Bitdo SN30 / SF30 User Manual

[Home](#) » [8Bitdo](#) » 8Bitdo SN30 / SF30 User Manual

Contents [[hide](#)]

1 SN30 and SF30

1.1 Instruction Manual

1.2 Bluetooth Connection

1.2.1 Android (D-Input)

1.2.2 Windows (X-Input)

1.2.3 macOS

1.2.4 Switch (by default)

1.2.5 Battery

1.2.6 Power Saving

1.2.7 Related Posts

SN30 and SF30

Instruction Manual

- Please turn off the controller before swapping controller modes.
- Press and held START for 3 seconds to turn off the controller.

Bluetooth Connection

Controllers will auto reconnect to your devices once they have been paired.

Android (D-Input)

1. Press and hold START for 1 second to power on the controller, LED will blink once per cycle.
2. Press and hold SELECT for 3 seconds to enter pairing mode Blue LED will rapidly blink.

3. Go to your Android device's Bluetooth setting, pair with [8Bitdo GamePad],
4. LED will be solid blue when Connection is successful,

USB Connection: connect your 8Bitdo controller to your Android device via USB Cable after step 1.

Windows (X-Input)

1. Press and hold START + X for 1 Second to power on the controller, LED will blink twice per cycle.
2. Press and hold SELECT for 3 seconds to enter pairing mode. Blue LED will rapidly blink.
3. Go to your Windows device's Bluetooth setting; pair with [8Bitdo GamePad(X)].
4. LED will be solid blue when connection is successful.

USB Connection: connect your 8Bitdo controller to your Windows device via USB Cable after step 1.

macOS

1. Press and hold START+A for 1 second to power on the controller, LED will blink three times per cycle.
2. Press and hold SELECT for 3 seconds to enter pairing mode. Blue LED will rapidly blink.
3. Go to your macOS device's Bluetooth setting, pair with [Wireless Controller].
4. LED will be solid blue when connection is successful.

USB Connection: connect your 8Bitdo controller to your macOS device via USB Cable after step 1.

Switch (by default)

1. Press and hold START + Y for second to power on the controller, LED will blink four times per Cycle.
2. Go to your Switch Home Page to click on Controllers, then click on Change Grip/Order.
3. Press and hold SELECT for seconds to enter pairing mode. Blue LED will rapidly blink.
4. LED will be solid blue when connection is successful.

When Connected to your Switch, DOWN+SELECT = Switch HOME button.

Battery

Status	LED indicator
Low battery mode	LED blinks in red
Battery Charging	LED blinks in green
Battery fully charged	LED stops blinking in green

- Built-in 480 mAh Li-ion with 18 Hours of play time.
- Rechargeable via USB cable with 1-2 hour charging time.
- Press START for 8 seconds to force turn off your controller.

Power Saving

1. Sleep mode - 1 minute with no Bluetooth connection.
2. Sleep mode – 15 minutes with Bluetooth connection but no use.

Press START to wake up your controller.