

FPi 700 Folder Inserter User Guide

Home » FP » FPi 700 Folder Inserter User Guide 🖫

Contents

- 1 FPi 700 Folder Inserter
- **2 Product Information**
- **3 Product Usage Instructions**
- 4 Using an Existing Job
- **5 Job Settings**
 - 5.1 Editing a Job
 - 5.2 Deleting a Job
 - 5.3 Resetting the Job

Counter

- **6 Configuring Feeder Options**
- 7 Saving a Job
- 8 Running a Job
- 9 Address position
 - 9.1 A Daily Mail job
- 10 Documents / Resources



FPi 700 Folder Inserter



Product Information

The product is a job management system designed for tasks that require sealing and mailing documents. It allows users to work with existing jobs, create new jobs, edit job settings, delete jobs, reset the job counter, configure feeder options, save jobs, and run jobs.


- Using an existing (saved) job: Existing jobs are shown in the Job list. These jobs have been saved via the job creation process.
- Using a new, unsaved job: after tapping the [New Job] button and finishing the Job Wizard just tap the start button. It is not needed to save the job first.

Product Usage Instructions

Using an Existing Job

To use an existing job:


- Ensure the sealing liquid reservoir is filled if sealing is required for the job.
- From the home screen, choose a job. The job information will be displayed.
- Load envelopes as specified in the job.
- Load the documents face up and trailing, as specified in the job.
- Place the address carrier in feeder 1.
- Tap the [1x] button to start a test run or tap the [Start] button to start the job. If you tap the [1x] button, the system will help you adjust the address position.



Creating a New Job

To create a new job:

- In the home screen, tap [New job]. The New job Wizard starts and helps you to choose;
 - Envelope type (size); Custom is only available if defined by the supervisor
 - Closing type; if the envelopes should be sealed or not.
 - Document size; for feeder 1.
 - Feeding type; Automatic feeding or Daily mail (manual).
 - Document size; for feeder 2. If you choose None, you can use feeder 2 as a linked feeder. This means that when one feeder is empty, the system automatically starts picking documents from the other feeder.
 - Enclosure type (size); from feeder 3.
 - Fold type
- Tap the [1x] button to make sure that the address position is correct
- Tap the [Start] button to start the job or tap the [Save] (disk symbol) button to save the job.
- If you tap the [Save] button:
 - Enter a name for the job. Use the backspace button to clear a character left of the cursor position.
 - Tap [OK] to confirm the job name.




Job Settings

Job Settings menu


When you tap in the Home screen on the [Edit job] button, the "Job Settings" menu opens. This menu enables you to:

- · Edit a job
- · Delete a job
- · Reset the job counter: sets the counter to zero
- Switch per feeder the double feed control (DFC) on or off

Editing a Job



- From the home screen, choose a job.
- Tap the [Edit job] button. The Job Settings menu will open.



- In the Job Settings menu, tap the [Edit job] button. The Job Wizard will help you change job settings.
- Tap [Save] to save the job with the changed settings.
- Press the [1x] button to ensure the address position is correct.

Deleting a Job

- From the home screen, choose a job.
- Tap the [Edit job] button. The Job Settings menu will open.
- · Tap [Delete job].




• Tap [Yes] to confirm. The job will be deleted without a warning.

Resetting the Job Counter

The job counter shows the total number of mail sets that have been processed with the selected job. If you want to set the job counter of the job to zero proceed as follows:

- From the home screen, tap the [Edit job] button. The Job Settings menu will open.
- In the Job Settings screen, tap the [Reset job counter] button.



• You will be asked if you want to reset the job counter. Tap [Yes] to reset it.




• The job counter will be reset to zero, and the Job Settings screen will appear again.


Configuring Feeder Options

For some applications it is preferred to switch the double feed control (DFC) off per feeder. For example, if you have a document with an address sticker on it, the DFC may see the sticker as a double feed; an error message will be generated. To prevent this you can switch the DFC off per feeder. Proceed as follows:

- From the home screen, tap the [Edit job] button. The Job Settings menu will open.
- Tap the [Feeder options] button.



• Select per feeder if you want to have the double feed control switched on or off.



• Tap the [Disk] button to save the settings.

Saving a Job

When you have created a new job or edited a job, save the job as follows:

- After completing the job definition, tap the [Save] button.
- Enter the job name. You can delete the existing name using the [clear] button.




• Tap [OK] to save the job. It will be added to the job list.

Running a Job

Before you run a job where sealing is required, make sure the sealing liquid reservoir is filled.

- From the home menu, choose a job. The job information will appear.
- · Load envelopes as specified in the job.
- Load the documents face up and trailing, as specified in the job. Place the address carrier in feeder 1.
- Tap the [1x] button to start a test run. If you tap the [1x] button, the system helps you to adjust the address position



- Tap the [Start] button to start the run. The system starts processing your mail sets.
- Tap the [Stop] button to stop the run. The system completes and inserts the current set and stops. This results in a cleared system which is ready to process a new job.



Address position

The address on the document set should be positioned in a way that you can read it from the envelope window. If it is not readable, adjust the address position as follows:

- Choose a job and tap the [1x] button.
- Use the arrow buttons up/down to adjust the address position.



- Tap the [1x] button again to verify the new position.
- Repeat step 2 and 3 until the address is clearly visible in the envelope window.
- Tap the [OK] button if the position is correct.

A Daily Mail job


To process documents or sets of documents, which can not be processed automatically (e.g. stapled documents), you can use feeder 1 as a daily mail feeder. Daily mail can handle sets with a maximum of five sheets (80 g/m2).

- To use the daily mail function, define a new job with daily mail
- Place the document or document set in the feeder 1.
- 3. Tap the [1x] button to start a test run. If you tap the [1x] button, the system helps you to adjust the address position



- Tap the [Start] button to start the job. The document or document set will be folded and inserted into the envelope as defined in the selected job.
- Place the next document or document set in the feeder. The system will keep running to process the inserted document or document set.
- When finished with Daily Mail, press the [Stop] button to stop the job.

Documents / Resources



Manuals+,