

**ACEBEAM**

L35 2.0 Immense Output  
Tactical Flashlight With Dual  
Switch



# ACEBEAM L35 2.0 Immense Output Tactical Flashlight With Dual Switch User Manual

[Home](#) » [ACEBEAM](#) » ACEBEAM L35 2.0 Immense Output Tactical Flashlight With Dual Switch User Manual 

## Contents

- [1 ACEBEAM L35 2.0 Immense Output Tactical Flashlight With Dual Switch](#)
- [2 Features](#)
- [3 Specifications](#)
- [4 Accessories](#)
- [5 Technical Parameter](#)
- [6 Operation Instruction](#)
- [7 Warning](#)
- [8 Usage and Maintenance](#)
- [9 Product Warranty](#)
- [10 Documents / Resources](#)
  - [10.1 References](#)
- [11 Related Posts](#)

**ACEBEAM**

**ACEBEAM L35 2.0 Immense Output Tactical Flashlight With Dual Switch**



## Features

- Powerful pocket tactical flashlight with breakthrough 5000 lumens
- Maximum beam intensity of 105625cd and maximum throw of 650 meters
- Equipped with one single CREE XHP70.3 HI LEO
- Powered by a 21700 battery, Acebeam USB-C rechargeable 21700 Li-ion battery included
- The customized TIR lens provides better light quality with a soft and balanced beam
- The aggressive strike bezel is used to break windows or defend in an emergency
- Dual switches for easy and fast operation
- Strobe mode for law enforcement
- The power indicator indicates the remaining battery pOW8f
- Lockout mode prevents accidental activation
- Highly efficient constant current circuit design (Non-PWM)
- Intelligent temperature regulation and protection adjusts output performance to prevent overheating
- Made of Aerospace-grade aluminum body with HAUi military hard-anodized finish
- 1-meter Impact resistance and waterproof rate to 5 meters submersible

## Specifications

Dimensions: 152mm (Length) x 54.2mm (Head Diameter) x 25.4mm (Tube Diameter) Weight: 250g w/battery

## Accessories

1xHolster; 1xPocket clip; 1xlanyard; 1xSpare rubber button cap; 2xO-rings; 1xWamnty card; 1xUser manual

## Technical Parameter

CREE XHP70.3 HI	FL1 STANDARD	Turbo	High	Mid 2	Mid 1	Low	Moonlight	Strobe	<div>FL1 STANDARD</div> <div>1m</div> <div>FL1 STANDARD</div> <div>5m</div>
		5000~1800 lumens	1800 lumens	800 lumens	230 lumens	80 lumens	1 lumen	1800 lumens	
		1min+ 1h 15min	1h 30min	4h	12h 45min	33h 30min	12days	2h 30min	
		650m	370m	250m	150m	90m		370m	
		105625cd	34225cd	15625cd	5625cd	2025cd		34225cd	

**Notice.** The above-mentioned parameters (tested with 1xACEBEAM 21700 battery) are approximate and may vary from flashlights, batteries, and environments. The L352.0 needs to be installed 1x21700 high drain battery that can produce at least 20 Amps of current.

## Operation Instruction

### Tactical Tail Swtch:

When the flashlight is Unlocked, elicit the tactical tail switch for momentary on and constant activation at Turbo mode Please note if elicit the tactical tail switch all first, Any operation of the side switch is useless.

### Side Switch:

**ON/OFF:** Single click the side switch.

**Mode Selection:** When the flashlight Is ON, press and hold the side switch to cycle from low -Med1→Med2→Hlgh modes, and loosen the switch at your selected mode. Next ON will memorize the last mode you selected.

**Turbo:** Double elicit the side switch to exchange between Turbo mode and memorized mode. Strobe: Triple elicit to access Strobe mode regardless the flashlight is ON or OFF. Moonlight: When the flashlight is OFF, press and hold the side switch for 0.5 seconds to go to Moonlight.

### Lock

When the flashlight Is OFF, press and hold the side switch for 5 seconds, the flashlight will be Locked after 3 seconds' Moonlight output. It is useless for both side switch operation end tactical tail switch.

### Unlock

When the flashlight is Locked, press and hold the side switch for 3 seconds, the flashlight will be Unlocked and light in Moonlight mode.

**(Remark: To unlock, the tail switch needs to be turned off first, the power IndJcatcw can indicate the tail switch Is on or off)**

Moonlight and Turbo can not be memorized.

### Power Indicator

**Greenlight:** >30%

**Red light:** among 30%- 10%, low battery warning **Red flashlight:** below 10%

## Warning

1. By using this device, you certify you have read the included User Manual and Warning Card and release the manufacturer and retailers from all liabilities.
2. Please use in accordance with applicable laws and regulations.
3. Quality batteries with circuit protection will reduce the potential risk.
4. Do not aim this light directly at eyes or exposed skin to prevent Injuries. Keep this flashlight out of the reach of children.

## Usage and Maintenance

1. Unauthorized disassembly may damage the light and void the warren.
2. This Is a normal case the light will accumulate a lot of heat when used on Turbo/output levels for extended periods.
3. Lubricate the threads with professional-grade lubricant regular.
4. Please swap out the O-rings regularly to maintain the water resistance level.
5. Maintain and keep clean any contact surfaces of the flashlight with an alcohol swab. This may prevent irregular flashes during use.

6. Remove batteries during storage. Keep lithium-ion batteries charged approximately every 4 months.
7. This flashlight may not be used as a diving light.

## Product Warranty

1. If the customer experiences any problems with an Acebeam product within 15 days of purchase, the dealer will replace that product.
2. If an Acebeam flashlight fails during normal use within five years (60 months) of purchase, the dealer will repair or replace the flashlight with the same or similar model.
3. ACEBEAM batteries, accessories, and lanterns with built-in batteries are warranted for one year (12 months) from the date of purchase.
4. The warranty does not cover damage or failure caused by:
  - A. Rough usage or operation which does not comply with the user manual or product specifications.
  - B. Unauthorized disassembly, repair, or modification. Defects or damage caused by factors out of Acebeam's control.
  - C. Battery leakage damaged products.
5. If there are any questions about Acebeam products, please consider the warranty and contact Acebeam or your original Acebeam dealer for warranty return instructions.

Email: [Info@acebeam.com](mailto:Info@acebeam.com)

**Acebeam is not liable for damages or injuries sustained resulting from the usage of the product inconsistent with the warnings in the manual.**

## SHENZHEN ZENBON TECHNOLOGY CO. LTD

+86-0755-23036551

[www.acebeam.com](http://www.acebeam.com)

[info@acebeam.com](mailto:info@acebeam.com)

1/F, No.1 Building, Yijiyang Industrial Park, Dalang, Longhua, Shenzhen 518100, Guangdong, China

## Documents / Resources

	<p><a href="#">ACEBEAM L35 2.0 Immense Output Tactical Flashlight With Dual Switch</a> [pdf] User Manual L35 2.0 Immense Output Tactical Flashlight With Dual Switch, L35 2.0, Immense Output Tactical Flashlight With Dual Switch, Tactical Flashlight With Dual Switch, Dual Switch</p>
---	---

## References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.